

Clearspan[®] Hosted Thin Call Center Agent/Supervisor User Guide

RELEASE 22

March 2018



NOTICE

The information contained in this document is believed to be accurate in all respects but is not warranted by Mitel Networks™ Corporation (MITEL®). The information is subject to change without notice and should not be construed in any way as a commitment by Mitel or any of its affiliates or subsidiaries. Mitel and its affiliates and subsidiaries assume no responsibility for any errors or omissions in this document. Revisions of this document or new editions of it may be issued to incorporate such changes.

No part of this document can be reproduced or transmitted in any form or by any means - electronic or mechanical - for any purpose without written permission from Mitel Networks Corporation.

TRADEMARKS

Clearspan and Mitel are trademarks of Mitel Networks Corporation.

Other product names mentioned in this document may be trademarks of their respective companies and are hereby acknowledged.

Clearspan Hosted Thin Call Center Agent/Supervisor User Guide
Release #22
2850-008
March 2018

®,™ Trademark of Mitel Networks Corporation
© Copyright 2018 Mitel Networks Corporation
All rights reserved

REVISION HISTORY	1
ABOUT THIS DOCUMENT	2
Audience	2
Additional Resources	2
INTRODUCTION TO CALL CENTER.....	3
Call Center – Agent.....	4
Call Center – Supervisor	5
GETTING STARTED	8
Launch Call Center from Web Portal.....	8
Sign in from Web Browser	9
Hot Desk Sign-in	11
Launch JNLP File.....	12
Sign-in Restrictions	13
Get Help.....	14
Sign Out.....	14
Set Up Call Center	15
Change Your Password	16
Change Your ACD State (Agents).....	16
Change Your Instant Messaging and Presence State	17
Enable or Disable Services	18
EXPLORE WORKSPACE.....	20
Logo Pane	23
Global Message Area.....	23
Links to Other Interface Elements and Functions	23
Logged User Information.....	23
Call Console	24
Header Bar	25
Dialer	26
Current Calls	26
Conference Call.....	28

Call States and Actions	29
Call Redirection Reasons	30
Contacts Pane	30
Search Panel	33
Enterprise/Group Panel	33
Common Panel	33
Personal Panel	34
Agents Panel (Supervisors)	34
Supervisors Panel (Agents)	35
Speed Dial Panel	35
Queues Panel	35
Custom Directories Panels	36
Instant Message Panel	36
Outlook Panel	37
Directories Panel	37
Call History	38
Controls	39
Call Action Buttons	41
MANAGE CALLS	45
Call Management Operations Quick Reference	46
Drag and Drop Call onto Contact	48
View Calls	48
View Current Calls	48
Group Calls	49
View Incoming Call Details	50
Assign Disposition Codes (Premium Call Center)	52
Assign Disposition Codes to Current Call	52
Assign Disposition Codes in Wrap-Up	52
Generate Call Trace	53
Generate Call Trace for Selected Call	53
Generate Call Trace for Last Released Call	53
Record Calls	54
Manually Record Call	54
Pause and Resume Call Recording	54
Stop Call Recording	55
View and Change Security Classification of Calls	55
Change Security Classification	56

Receive, Answer, and End Calls	56
Answer Call	56
Auto Answer Calls	57
Open URL	57
Save vCard.....	58
End Call.....	58
Make Outbound Calls.....	58
Set Your Outgoing Calling Line Identity (Premium Call Center)	58
Dial Ad Hoc Number.....	59
Redial Number	59
Dial Contact.....	60
Dial from Search.....	61
Dial from History.....	61
Place Calls on Hold, Resume, and Camp Calls.....	63
Place Call on Hold.....	63
Resume Held Call	63
Conduct Busy Camp On.....	63
Transfer Calls	64
Blind Transfer	64
Transfer with Consultation.....	64
Transfer to Queue	65
Escalate Calls	65
Make Emergency Call	65
Blind Escalate Call	67
Escalate with Consultation	67
Escalate with Conference or Handover.....	67
Escalate with Mid-Conference Hold	68
Manage Conference Calls.....	68
Start Three-Way Conference	69
Add Participant to Conference	70
Hold Conference	70
Resume Conference	70
Hold Participant	70
Take Participant Off Hold	71
Leave Conference	71
End Participant	71
End Conference	71

MANAGE CALL HISTORY	72
View Call History.....	72
Delete Call History	73
E-MAIL CONTACTS	74
Send E-mail Message to Contact.....	74
MANAGE CONTACTS.....	75
View Contacts.....	77
Show or Hide Directories.....	77
Display Directory Below Call Console	78
Show or Hide Directory Content.....	80
Show Contact Details	80
Select Display Order	81
Organize Contacts	82
Sort Contacts.....	82
Search for Contacts	83
Perform Contact Search.....	84
Manage Personal Contacts.....	85
Add Personal Contact	85
Delete Personal Contact	86
Manage Speed Dial Numbers	87
Add Speed Dial Entry	87
Modify Speed Dial Entry.....	88
Delete Speed Dial Entry	88
MONITOR IM&P CONTACTS AND CHAT WITH CONTACTS	90
Monitor IM&P Contacts	90
Subscribe to Contact	91
Add Contact to Instant Message Directory.....	91
Modify Contact Name.....	92
Unsubscribe from Contact.....	93
Accept or Reject Subscription Request.....	93
View Unified Presence State of Contacts	94
Chat with IM&P Contacts	95
Start Instant Messaging Session.....	96
Place Call from Chat Window	97
Establish Multiuser Chat Session.....	98

Manage Instant Messaging Sessions	99
MONITOR SUPERVISORS (AGENT)	101
Select Supervisors to Monitor	101
Supervisor Phone States	102
MONITOR CALL CENTERS (AGENT)	103
Dashboard Pane	103
Select Call Centers to Monitor	105
Select Information to Display	106
Order Call Centers	107
MANAGE AGENTS (SUPERVISOR)	108
Select Agents to Monitor	108
Make Agents Join Queues	110
Agent Phone and ACD States	111
View Agent's Details	112
Change Agent ACD State	113
Silently Monitor Agent's Call	113
Barge in on Agent's Call	114
Pick Up Agent's Ringing Call	115
MANAGE QUEUED CALLS (SUPERVISOR)	116
Queued Calls Pane	116
Select Call Centers to Monitor	119
Modify Number of Calls to Display	120
Show or Hide Call Center Panels	120
View Queued Calls	121
Group Queued Calls	121
Order Queued Calls	122
Monitor Next Call	122

Enable Night Service Override or Forced Forwarding (Premium Call Center)	123
Retrieve Call from Queue.....	124
Promote Call in Queue (Premium Call Center).....	124
Transfer Call to Another Queue	124
Transfer Call from Queue to Agent.....	125
Transfer Call to Ad Hoc Number	125
Change Position of Call in Queue	125
Transfer Call to Top of Queue (Premium Call Center).....	126
VIEW REAL-TIME STATISTICS (SUPERVISOR)	127
Display Dashboard.....	127
Queue Information	128
Agent Information.....	129
Select Information to Display.....	131
Navigate to Agent in Agent Directory or Queue in Queued Calls Pane	132
GENERATE REPORTS.....	134
Run Report	134
Schedule Report.....	140
Manage Scheduled Reports.....	145
CONFIGURE CALL CENTER.....	147
Settings – General	149
Account.....	150
Hotel/Flexible Seating Host.....	150
Language	150
Screen Pop.....	151
Date Format	152
Time Format	152
Workspace	153
Settings – Application.....	154
Queue Memberships (Agent)	154
Agent Policies (Agent).....	155
Barge-In & Monitor (Supervisor)	155
Settings – Services	156

Settings – Plug-ins	158
Plug-ins.....	158
Notification.....	159
Microsoft Outlook	159
LDAP v3	160
Program Shortcuts	161
Call Event Log	161
Settings – Messaging	163
E-mail Messaging.....	163
Instant Messaging and Presence.....	164
Settings – Report	164
Default Thresholds	165
Default Start of the Week	165
Default Service-level Calculations.....	165
Settings – About.....	166
CONFIGURE WEB BROWSER.....	167
Internet Explorer Settings for Full Screen Mode	167
Firefox Settings for Quick Link Navigation.....	168
Certificate for Desktop Integration Features	168
Download Desktop Plug-ins Certificate.....	168
Add Certificate to Microsoft Windows Certificate Store	169
Add Certificate to Apple System Keychain.....	175
Add Certificate to Firefox Certificate Store.....	177
Update Certificate.....	178
SECURITY SETTINGS FOR DESKTOP INTEGRATION FEATURES.....	181
JNLP Download	181
On MAC OS X	181
Internet Explorer	182
Restrictions and Limitations	184
Tab Button and PDF Reports in Microsoft Edge	184
Quick Link Navigation in Chrome and Firefox.....	185
APPENDIX A: GLOSSARY AND DEFINITIONS	186
ACD States	186
Agent Skill Levels (Premium Call Centers).....	187

Phone States	188
Unified Instant Messaging Presence States	189
Call States	190
Call Types.....	190
Call Redirection Reasons.....	191
APPENDIX B: DIAGNOSTIC TOOL	193
Launching Diagnostic Tool.....	193
Diagnostic Tool GUI	193
Session Tab	193
Long Polling Tab	194
Calls Tab	195
Service Tab	196
Monitoring Tab	196
Support Tab.....	197
Known Issues	197
APPENDIX C: KEYBOARD SHORTCUTS	198
INDEX.....	200

REVISION HISTORY

The following represents the revision history of this publication.

REVISION NUMBER	DATE COMPLETED	POINT OF CONTACT	DESCRIPTION
2838-008	3/2018	Mitel Technical Publications	R22.0
2838-007	10/2017		R21.0.43
2838-006	09/2016		R21.0.29
2838-005	03/2015		Updated for R20.0.32; Added Diagnostic Tool appendix
2838-004	08/2014		R20.0
2838-003	10/21/13	Bev Marsh	R19.0
2838-002	07/28/12	Bev Marsh	R17.sp4
2838-001	11/9/2011	Bev Marsh	New Document for R17.0

ABOUT THIS DOCUMENT

This user guide provides step-by-step procedures and reference information for using Clearspan Hosted Thin Call Center Release 22 client application.

AUDIENCE

This document is intended for Call Center agents and supervisors who use the Clearspan Hosted Thin Call Center client.

ADDITIONAL RESOURCES

For more information on Call Center and on Application Server procedures used by group administrators, department administrators, and users, see the following Clearspan guides:

- Clearspan Call Center Solution Guide
- Clearspan Call Center Reports Guide
- Clearspan Getting Started Web Interface Administration Guide
- Clearspan Application Server Group Web Interface Administration Guide Part 1
- Clearspan Application Server Group Web Interface Administration Guide Part 2
- Clearspan Application Server Enterprise Web Interface Administration Guide

INTRODUCTION TO CALL CENTER

Clearspan Call Center is a carrier-class, communications management product for Call Center agents and supervisors used with the Clearspan® telephony softswitch platform, on which call centers are hosted.

Clearspan Call Center delivers the following real benefits to users:

- Efficient call handling and automatic call distribution (ACD) state management by Call Center agents
- Integration of online directories with Click-To-Dial capability
- Real-time monitoring of agent and queue activity by Call Center supervisors
- Historical reporting on agent and queue activity by Call Center supervisors

Along with this focus on design, Clearspan Call Center employs the latest technology platforms and communications facilities.

The Hosted Thin Call Center, introduced in Release 17.sp2, is an SaaS Rich Internet Application (RIA) hosted on Clearspan that allows you to manage call center activity from a web browser.



Note: For information about the web browsers supported by Call Center, see the *Clearspan Hosted Thin Call Center Agent/Supervisor Configuration and Administration Guide* or ask your administrator.

This document describes the Clearspan Hosted Thin Call Center client.

Clearspan Hosted Thin Call Center client application herein is referred to as Call Center, Call Center client, Call Center application, or client.

The Call Center functionality available to you depends on your Call Center function (agent or supervisor), the types of queues you are staffing or monitoring (Standard or Premium), and your own services and settings. For more information about the capabilities and services assigned to you, ask your group or enterprise administrator.

The following sections provide an overview of Call Center – Agent and Call Center – Supervisor functions and refer you to other sections for more information.



Note: Call Center functionality available in specific contexts is identified throughout the document.

CALL CENTER – AGENT

The Call Center – Agent client is designed to support the needs of Call Center agents in any environment. It supports the full set of call handling functions, ACD state management, integration of multiple directories, Outlook integration, and other features required in large call centers.

Figure 1 shows the main interface of the Call Center – Agent.




Figure 1 Call Center – Agent Main Interface

The interface contains the following work areas:

- **Logo pane** – The *Logo* pane displays information about you and contains links to other pages and functions.
- **Call Console** – You use the *Call Console* to view and manage your current calls.
- **Contacts pane** – The *Contacts* pane contains your contact directories, the list of your supervisors, and the list of the call centers to which you belong. It allows you to use your contacts to make and manage your calls.
- **Dashboard pane** – The *Dashboard* pane provides real-time summary information about up to 50 call centers selected from the list of call centers to which you are assigned.
- **Call History dialog box** – You use the *Call History* dialog box to view your past calls and make calls from history.
- **Chat windows** – You use *Chat* windows to chat with your IM&P contacts.

- **Report window** – You use the *Report* window, accessed via the Reporting link, to generate reports about your activity and performance in the call centers you are staffing.
- **Settings pages** – You use the *Settings* pages, accessed via the Settings link, to configure various aspects of Call Center.

For more information about the Call Center user interface, see section Explore Workspace.

Call Center functionality available to agents is described in the following sections:

- [Getting Started](#)
- [Manage Calls](#)
- [Manage Call History](#)
- [E-mail Contacts](#)
- [Manage Contacts](#)
- [Monitor IM&P Contacts and Chat with Contacts](#)
- [Monitor Supervisors \(Agent\)](#)
- [Monitor Call Centers \(Agent\)](#)
- [Configure Call Center](#)

CALL CENTER – SUPERVISOR

The Call Center – Supervisor client is designed to support the needs of call center supervisors in any environment. It supports agent monitoring, queue management, real-time and historical reporting, and other features required in large call centers.

Figure 2 shows the main interface of the Call Center – Supervisor.




Figure 2 Call Center – Supervisor Main Interface

The Call Center interface contains the following work areas:

- **Logo pane** – The *Logo* pane displays information about you and contains links to other pages and functions.
- **Call Console** – You use the *Call Console* to view and manage your current calls.
- **Contacts pane** – The *Contacts* pane contains your contact directories and provides you with real-time call and ACD state of the agents you are monitoring.
- **Queued Calls pane** – You use the *Queued Calls* pane to manage queued calls.
- **Call History dialog box** – You use the *Call History* dialog box to view your past calls and make calls from history.
- **Chat windows** – You use *Chat* windows to chat with your IM&P contacts.
- **Dashboard** – The *Dashboard* provides real-time summary information for up to 50 queues and allows you to monitor key performance indicators for monitored call centers and supervised agents.
- **Report window** – You use the *Report* window, accessed via the Reporting link, to generate reports about the activity and performance of call centers and agents you manage.
- **Settings pages** – You use the Settings pages, accessed via the Settings link, to configure various aspects of Call Center.

For more information, see section Explore Workspace.

For information on Call Center functions performed by supervisors, see the following sections:

- [Manage Agents \(Supervisor\)](#)
- [Manage Queued Calls \(Supervisor\)](#)
- [View Real-Time Statistics \(Supervisor\)](#)
- [Generate Reports](#)

In addition, for information about other functions available to you, see the following sections:

- [Getting Started](#)
- [Manage Calls](#)
- [Manage Call History](#)
- [E-mail Contacts](#)
- [Manage Contacts](#)
- [Monitor IM&P Contacts and Chat with Contacts](#)
- [Configure Call Center](#)

GETTING STARTED

Call Center is hosted on Clearspan and you access it over the network either from your web portal or from a web browser. The sign-in procedure is the same for agents and supervisors.

In addition, agents can sign in to Call Center using hot desk functionality, that is, sign in from any available desk configured for that purpose. Upon login, a desk's phone is associated with a certain agent and behaves as if it were the permanent phone of the agent for the duration of the login session. This allows agents to use a single login ID to perform their work independently of their location.



Notes: The minimum screen resolution required for the Call Center is 1024 x 768 pixels.

Call Center does not support logging in as different users from the same machine at the same time.

When using the Outlook Integration feature with Microsoft Outlook 2010 or Outlook 2013 (32- or 64-bit edition), make sure Outlook is running before Call Center is launched; otherwise, the Outlook Integration functionality does not work.

LAUNCH CALL CENTER FROM WEB PORTAL

Clearspan has a Single Sign-On feature. When you access the Call Center client from the web portal, you do not need to provide your credentials since you are already logged in to the web portal.

To launch Call Center:

1. Log in to your Clearspan web portal.
2. From the *Launch* drop-down list at the top right-hand side of the Clearspan logo pane, select the *Call Center* service.




Figure 3 Clearspan Web Portal Logo Pane – Launching Call Center as Agent




Figure 4 Clearspan Web Portal Logo Pane – Launching Call Center as Supervisor

3. If you are presented with a system use notification, click **Accept** to accept the notification. Otherwise, you will be denied access to Call Center.
4. As Call Center starts, a Java Network Launch Protocol (JNLP) file required to run some of the Call Center features is downloaded to your machine. You must agree to run the file; otherwise, the features will not be available. For more information, see section *Launch JNLP File*.

SIGN IN FROM WEB BROWSER

To sign in to the Call Center client, use the same credentials that you use to connect to the web portal.

To sign in to Call Center:

1. In your web browser, enter the Uniform Resource Locator (URL) of the Call Center client. The *Call Center Sign-in* page appears.

Figure 5 Call Center Sign-in Page

2. Enter your Clearspan user ID in *user@domain* format and enter your password.

If you are unsure of your user ID or password, contact your administrator.

You can also enter just the *user* part of your ID. The system then appends the default domain to it before authenticating you. However, if your domain is different from the default domain, you have to enter your user ID with the domain name.

Optionally, if your system has been configured to allow it, you can configure your domain name.

3. Check *Stay signed in* to instruct the client to automatically reconnect and sign in to the server when it detects a network connection.

This should generally be enabled to help mitigate intermittent internet connections. When disabled, the client signs out the user when the connection is lost.

4. To configure your domain name or the Call Center language, click **Show options**. The area expands, displaying advanced options.

The screenshot shows a sign-in dialog box with the following elements:

- User ID:** A text box containing "Tester07@remotesoho.aastra.com".
- Password:** An empty text box.
- Stay signed in:** An unchecked checkbox.
- Sign In:** A dark button.
- Hide options** and **Bookmark this page:** Two blue hyperlinks.
- Append Domain:** An empty text box.
- Hoteling/Flexible Seating Host:** A text box with the placeholder text "Enter Host".
- Language:** A dropdown menu currently showing "English (US)".

Figure 6 Call Center Sign-in Dialog Box – Advanced Options

5. To configure your domain, in the *Append Domain* text box, enter your domain name. When you enter your user ID without a domain, the system appends the configured domain instead of the system-wide default domain.
6. To change the language, from the *Language* drop-down list, select a new language.
7. To add a bookmark to this page in your browser, click **Bookmark this page** and follow the instructions of your browser.
8. Click **Sign In**.
9. If you are presented with a system use notification, click **Accept** to accept the notification. Otherwise, you will be denied access to Call Center. If you checked *Stay signed in*, you will also be presented with this notification when the client reconnects to the server.
10. As Call Center starts, a JNLP file required to run some of the Call Center features is downloaded to your machine. You must agree to run the file; otherwise, the features will not be available. For more information, see section *Launch JNLP File*.



Note: In some browser/operating system combinations, when you press ENTER instead of the **Sign In** button, a blank page appears instead of the Call Center main interface.

HOT DESK SIGN-IN

If you are a Call Center agent, you can automatically associate yourself with a Hoteling Host or Flexible Seating Host phone device when you sign in to the Call Center client. This is commonly used in a shared workspace environment where users working different shifts share a single computer and phone.

To use hot desk functionality, you must have your Hoteling Guest or Flexible Seating Guest service assigned. You turn on your Hoteling Guest or Flexible Seating Guest service using the Clearspan web portal or voice portal.

To sign in to Call Center as a hot desk user:

1. At the assigned workstation, start a web browser and enter the URL of the Call Center client. *The Call Center Sign-in* page appears.
2. Enter your Clearspan user ID and password.
3. Click **Show options**. The area expands, displaying advanced options.
4. In the *Hotel/Flexible Seating Host* text box, enter the user ID of the Hoteling Host or Flexible Seating Host that corresponds to the desk/device you are using, for example, "station_224@acme.com".
5. To change the language of the user interface, from the *Language* drop-down list, select a new language.
6. If you are presented with a system use notification, click **Accept** to accept the notification. Otherwise, you will be denied access to Call Center.
7. You are signed in and Call Center associates that desk's phone with your user account for the duration of the session. As Call Center starts, a JNLP file required to run some Call Center features is downloaded to your machine. You must agree to run the file; otherwise, the features will not be available. For more information, see section *Launch JNLP File*.



Notes: When you sign out from the Call Center client, the guest session with the host device at the desk is terminated. After sign-out, the host user ID you entered is saved and can be reused on the next sign-in.

The host/guest association can be configured with a time limit. If the association/session expires while you are signed in to the client, you are automatically signed out from the client. The association time limit can be specified both for hosts and for guests. You can configure your association time limit for your

Hoteling Guest or Flexible Seating Guest service on the Clearspan web portal. The host association time limit is usually configured by your administrator.

LAUNCH JNLP FILE

Call Center needs the Java HTTPS server to run desktop integration features such as Outlook Integration. To view the list of Call Center desktop integration features, see section *Settings – Plug-ins*. To configure the browser certificate required to run the HTTP server, see section *Certificate for Desktop Integration Features*.

As you sign in, Call Center starts downloading a JNLP file containing the Java HTTPS server to your machine. Perform the following steps to accept the download and install the server.

1. When a file download pop-up window appears in your browser asking you whether you want to open or save the file, save the file.

Messages about downloading and verifying the application contained in the file appear, followed by a dialog box asking you whether you want to run the application.




Figure 7 Downloading and Verifying Application Pop-up Window




Figure 8 “Do you want to run this application?” Dialog Box

2. Click Run. This starts the Java HTTPS server allowing Call Center to access the desktop integration features.



Note: Desktop integration features will not be available if you click Cancel.

In you refresh the browser after the local HTTPS server has started, the JNLP file is not downloaded again and the HTTPS server simply continues initializing the desktop integration features.

SIGN-IN RESTRICTIONS

You can only have one active Call Center session at a time. When you sign in from a second location, you are automatically signed out from the original location with the following message: “You have been signed out as you have signed in from another location.”




Figure 9 Sign-in Dialog Box with Error Message

You may also be automatically signed out if you signed in from a Hoteling Host or Flexible Seating Host and your session expired.

GET HELP

Call Center provides you with online access to a portable document format (PDF) version of this guide.




Figure 10 Logo Pane with Help Link

To access the document, click the **Help** link in the top right-hand side of the main interface.

SIGN OUT

1. To sign out of Call Center, click **Sign Out** at the top right-hand side of the main interface.

If you are the last agent to sign out of a call center, a message appears, providing the details of queues in which you are the last agent to sign out and asking you to confirm that you want to sign out.



Note: This functionality is not available when you close the application using the browser's Close button or when you refresh (F5) the browser.




Figure 11 Dialog Box – Signing Out Last

2. To stay signed in, click **No**. You are returned to the application.

To continue signing out, click **Yes**.

A message appears asking whether you would like to save your current workspace.




Figure 12 Dialog Box – Saving Workspace on Sign Out

To save your current workspace, click **Yes**. This allows you to retain the same interface setup at your next session. For information about the elements of the Call Center workspace that can be customized and retained between sessions, see section *Workspace*.

If you are signing out from a hot desk, your account is dissociated from the hot desk where you were signed in.

SET UP CALL CENTER

When you sign in to Call Center for the first time, it is recommended that you configure the following settings:

If you are an agent:

- Configure the queues you want to join on sign-in.
- Configure your post sign-in and post call ACD states.

For information, see section [Settings – Application](#).

- Configure the supervisors whose call status you want to monitor. For information, see section [Select Supervisors to Monitor](#).
- Make sure that your web browser is set up to use all the features of Call Center. For information, see section [Configure Web Browser](#).

If you are a supervisor:

- Configure agents you want to monitor. For more information, see section [Select Agents to Monitor](#).
- Configure queues you want to monitor. For more information, see section [Select Call Centers to Monitor](#).

For more information about the settings you can configure in Call Center, see section [Configure Call Center](#).

CHANGE YOUR PASSWORD

You can change your password when you are signed in to Call Center.

1. To change your password, click the **Settings** link at the top right-hand side of the main page.
2. Click the **General** tab and then click **Change Password**.




Figure 13 Changing Password

3. Enter your old and new password in the provided text boxes and click **Change Password**.

Note that the Reset button does not reset your password. It only clears the input boxes.



Note: This password is shared with your web portal and other client applications that share Clearspan Single Sign-On feature. It must meet the password requirements set on Clearspan.

CHANGE YOUR ACD STATE (AGENTS)

When you sign in to Call Center, your ACD state is set to the post sign-in ACD state set on the *Settings* page.

To change your ACD state:

1. At the top right-hand side of the main window, select your ACD state from the *ACD* drop-down list.



Figure 14 Logo Pane – ACD State Control

2. If you selected *Unavailable* and your company requires you to provide a reason for your unavailability, select an *Unavailable Code* from the drop-down list.




Figure 15 Logo Pane – Unavailable Codes

CHANGE YOUR INSTANT MESSAGING AND PRESENCE STATE

When you sign in to Call Center, Call Center connects to the Instant Messaging and Presence (IM&P) server and sets your presence state to *Available*.

Subsequently Call Center displays your unified instant messaging presence, which reflects your presence in various instant messaging clients when you are logged in through several devices and applications.

Your unified presence state can change either when you manually change it or when Call Center receives information about your presence state change from other clients.

The possible states are *Available*, *Busy*, *Away*, and *Offline*. When you are in *Offline* state, you are considered to be online.

Call Center also allows you to provide a status message to display to your contacts.

IM&P capabilities are only available when you have an IM&P service assigned on Clearspan and are online. For more information about the IM&P capabilities of Call Center, see section [Monitor IM&P Contacts and Chat with Contacts](#).

To change your IM&P state:

At the top right-hand side of the main window, select a new state from the *Presence* drop-down list. Your presence state is updated as soon as you select a new value.




Figure 16 IM&P State Drop-down List

When you are online, you can also specify a status message to display to your contacts.

To set the status message:

1. Click the **Edit** button  next to the *Presence* box. The *Set IM Status* dialog box appears.




Figure 17 Set IM Status Dialog Box

2. Enter your message and click **OK**.
3. To see your message, move the mouse over the Edit button . A ToolTip with your presence message appears.




Figure 18 IM&P Status Message in a ToolTip

ENABLE OR DISABLE SERVICES

You can use the following services in Call Center: Call Waiting, Call Forwarding Always, and Do Not Disturb, provided that your administrator has assigned the services to you.

To enable or disable Call Waiting:

1. In the *Call Console*, click **Call Waiting** . The button changes to this  to indicate that the service is enabled.

2. To disable it, click the button again.

To enable or disable Do Not Disturb or Call Forwarding Always:

1. At the top right-hand corner of the main page, click **Settings**. The *Settings* page appears.
2. Click the **Services** tab.
3. On the *Services* page that appears, select the service you want to enable or disable, and check or uncheck the *is Active* box.
4. If you checked the *is Active* box for the Call Forwarding Always service, in the Forward To text box, enter the phone number to forward your call to.
5. Click **Save**.

For more information, see section [Configure Call Center](#).

EXPLORE WORKSPACE

When you sign in to Call Center, the main page appears where you perform most of your call management or monitoring tasks. In addition, the main page provides links to other pages and windows of Call Center, where you perform functions such as configuration and report generation.




Figure 19 Call Center – Agent Main Interface

Many visual aspects of the Call Center workspace are configurable. For example, you can change the size and placement of windows on the screen. You can then save your workspace and retrieve it the next time you sign in. For more information on saving your workspace settings, see section [Workspace](#).

To work in full screen mode, click the **Full Screen** link at the top-right corner of the main window. The link changes to *Exit Full Screen*, which you can click to exit full screen mode.



Notes: To work in full screen mode, you can also click F11 when the main window is in focus .

The Back, Forward, and Refresh operations of the web browser are not supported by Call Center, and if performed, the results are inconsistent.

When a window is vertically resized, the panes do not always resize to fill the window. To resize a window, drag the window from the bottom right-hand corner or collapse and then expand the panes after resizing to adjust them to the window.

Most call center controls are context-based, which means that they appear only when the action they represent can be taken. Context-based controls that allow you to take actions

on calls are called action buttons. For the list of controls available in Call Center, see section [Controls](#). The action buttons are described in section [Call Action Buttons](#).

The Call Center interface contains the following elements:

INTERFACE ELEMENT	DESCRIPTION
Logo Pane	Located at the top of the main interface, the Logo pane displays global messages, information about the logged user, and links to other Call Center interface elements and functions.
Call Console	The Call Console is where you manage your current calls.
Contacts Pane	The Contacts pane contains your contact directories and allows you to manage your contacts and use contacts to make calls or take actions, such as transfer to contact or queue, on existing calls.
Queued Calls Pane (Supervisors)	The Queued Calls pane, available only to supervisors, allows you to manage queued calls for selected call centers that you supervise.
Chat Windows	You chat with your IM&P contacts using Chat windows.
Call History Window	The Call History window, accessible from the Call Console via the Call History button, displays your placed, received, and missed calls, and allows you to make calls from history and delete call logs.
Report Windows	The Report windows, accessible from the main page via the Reporting link, provide access to Enhanced Reporting, allowing you to generate, schedule, and view reports. Agents can only generate reports about themselves.
Dashboard (Supervisors)	The Dashboard, accessible from the main page via the Dashboard link, provides you with real-time summary information about the call centers and agents you supervise (up to 50).
Dashboard Pane (Agent)	The Dashboard pane allows you to view the current state of the monitored call centers.
Settings Pages	The Settings pages, accessible from the main page via the Settings link, allow you to configure various user-level and application settings.
Controls	You use controls, such as buttons and drop-down lists to execute actions on calls, contacts, queues, and so on.

This section describes the following elements of the Call Center interface:

- [Logo Pane](#)
- [Call Console](#)
- [Call Redirection](#) Reasons

The following table lists the possible reasons for redirecting calls.

REDIRECTION REASON	DESCRIPTION
busy	The call was redirected to a specified destination because the Call Forwarding Busy service was activated and the subscriber was busy. A subscriber is considered busy when there are too many active calls.
no answer	The call was redirected because the Call Forwarding No Answer service was activated and the subscriber did not answer within the specified number of rings.
unavailable	The call was redirected because the Call Forwarding Not Reachable service was activated and the subscriber's device was either unreachable or unregistered.
unconditional	The call was redirected because the Call Forwarding Always service was activated. When active, the Call Forwarding Always service redirects all incoming calls.
time of day	The call was redirected because the Call Forwarding Selective service was activated and the incoming call matched the specified time of day value.
do not disturb	The call was redirected because the Call Forwarding Busy service was enabled and the Do Not Disturb service was activated.
deflection	The call was transferred before being answered.
follow me	The call was redirected because one of the following services was activated: Simultaneous Ringing, Sequential Ringing, or Clearspan Anywhere.
out-of-service	The call session was redirected by the network with the reason set to "out-of-service?".
away	The call was redirected by the network with the reason set to "away".
transfer	The call was transferred after being answered.
voice mail	The call was redirected because the Call Forwarding Always to Voice Mail service was activated, the Call Forwarding Busy to Voice Mail service was activated, and the subscriber was busy, or the Call Forwarding No Answer to Voice Mail service was activated and there was no answer.
hunt group	The call was redirected to an agent by a hunt group.
call center	The call was redirected to an agent by a call center.
route point	The call was redirected to an agent by a route point.
unknown	The call was redirected for an unknown reason.

- [Contacts Pane](#)
- [Call History](#)
- [Controls](#)

For information about other interface elements, see the following sections:

- *Queued Calls* pane – Section [Queued Calls Pane](#)

- *Chat windows* – Section [Chat with IM&P Contacts](#).
- *Report windows* – Section [Generate Reports](#)
- *Dashboard pane* – Section [Monitor Call Centers \(Agent\)](#)
- *Dashboard* – Section [View Real-Time Statistics \(Supervisor\)](#)
- *Settings pages* – Section [Configure Call Center](#)

LOGO PANE

The Call Center main window interface contains a logo pane that displays the Call Center client or company logo, global messages, links to other interface elements or Call Center functions, and information about the logged-in user.

GLOBAL MESSAGE AREA

The *Global Message Area*, that is, the center area of the *Logo* pane, is used by Call Center to display various information, warnings, and error messages to the user. A message is displayed for several seconds and then it disappears.

LINKS TO OTHER INTERFACE ELEMENTS AND FUNCTIONS

The *Logo* pane displays links to the *Report* windows, *Settings* pages, the *Dashboard* (Supervisors), and the *Help* and *Sign Out* links.

LOGGED USER INFORMATION

Information about yourself, that is, your name, your availability to take calls, and your voice mail status, is displayed at the top right-hand side of the main interface.

Your current ACD state and presence state are displayed to the left of your name. You can change your ACD state or presence state by selecting a new state from the drop-down list.

- ACD state 
- Presence state 

In addition, information about the following services and features is provided:

- Do Not Disturb (DND) 

- Call Forwarding Always (CFA) 
- Busy phone state 
- Voice Messaging 

The information is presented in the form of icons to the left of your name in the following format:

<DND/CFA/Busy> <Voice Messaging>

The <DND/CFA/Busy> state is represented by one icon, where Do Not Disturb has precedence over Call Forwarding Always, which has precedence over your Busy Phone State. If none of the services is enabled and your phone state is *Idle*, the icon is not displayed.

The Voice Messaging icon is present only if you have outstanding voice messages.

CALL CONSOLE

You use the *Call Console* to view and manage your current calls. For information on managing your calls, see section [Manage Calls](#).




Figure 20 Call Console

The *Call Console* contains the following areas:

- [Header Bar](#)
- [Dialer](#)
- [Current Calls](#)
- [Conference Call](#)

HEADER BAR

The header bar contains various controls that allow you to configure your services and perform call and service-related actions.



Figure 21 Call Console Header Bar

The header bar can contain the following controls:

- Disposition Code button  – This allows you to assign disposition codes to the last call. The button only appears when you are in *Wrap-Up* state.
- Trace Call button  – This allows you to attach a trace to the last call.
- Call History button  – This allows you to access the list of your previous calls.
- Auto Answer button  – This allows you to enable or disable the automatic answering of calls.
- Call Waiting button  – This allows you to enable or disable the Call Waiting service.

DIALER

The *Dialer*, located at the top of the *Call Console*, below the header bar, allows you to make ad hoc calls and set your outgoing calling line identity (CLID) for the next call.



Figure 22 Dialer

It contains the following elements:

- The Outbound CLID button , which allows you to configure the number you want to use for outgoing calls.
- The *Enter Number* text box, in which you enter the number to dial.
- Action buttons, which change depending on the context and allow you to perform operations on calls. For more information, see section [Call Action Buttons](#).

CURRENT CALLS

The *Call Console* displays your current calls, both direct and ACD, and allows you to take actions on them. Direct calls are calls placed from or received on your own phone number, whereas ACD calls are calls routed to you from a call center that you are staffing as an agent.

If you are involved in a conference call, its details are displayed in a separate area of the Call Console, called the *Conference Call* panel. The *Conference Call* panel is described in the following section.




Figure 23 Call Console – Current Calls

The following information is displayed for each call:

- Call State icon – This is a visual representation of the current state of the call. For more information, see section [Call States and Actions](#).
- Remote CLID – This is the name of the remote party (if available) and the phone number in parenthesis.
- Diversion CLID – This is the name (if available) of the party who diverted (transferred, forwarded) the call before you received the call and the phone number is in parenthesis. If the call was diverted more than once, the last party who diverted the call is listed first; the second to last party is listed second; and so on.
- Redirecting reason – This specifies why the call was redirected. When you move the mouse over the reason, a ToolTip appears providing more details on the reason for redirecting the call. For more information, see section [Call Redirection Reasons](#).
- Call State name – This is the display name of the “call” state the call is currently in.
- Call duration [Held duration] – This is the duration of the call from the time the call was received from Clearspan and it reflects how long the call has been present in the system. In addition, for held calls, the time a call has been on hold is displayed.
- Security Classification (if applicable) – This is the security classification level of the call.

The call entry also displays action buttons for the operations that you can currently take on that call. The actions you can perform depend on the state of the call.

For the list of Call Center action buttons, see section [Call Action Buttons](#) and for the list of actions that can be taken in each call state, see section [Call States and Actions](#).

CONFERENCE CALL

The *Conference Call* panel displays your current conference and allows you to manage your conference calls.



Note: You can only be involved in one conference call at a time.




Figure 24 Call Console – Conference Call

The header bar contains various controls that allow you to manage the conference:

-  End Conference button – This allows you to end the current conference.
-  Leave Conference button – This allows you to leave the conference.
-  Hold Conference button – This allows you to place the conference on hold.
-  Resume Conference button – This allows you to resume the conference that you previously placed on hold.

The *Conference Call* panel, when expanded, lists the call legs that make up your current conference. Each two-way call is displayed on a separate line. The information displayed for each call leg is the same as the information displayed for two-way calls. For information, see section [Current Calls](#).

For information on managing conferences, see section [Manage Conference Calls](#).

CALL STATES AND ACTIONS

The following table lists the possible call states and actions that can be performed on calls in each state.

CALL STATE	DISPLAY NAME	DISPLAY ICON	CALL PERSONALITY	CALL ACTIONS
Ringing In (Local)	Incoming Local		Click-To-Dial	Answer, End
Ringing In (Remote)	Incoming		Terminator	Answer, Conference, End
Ringing Out, Outgoing	Outgoing		Originator	Conference, End
Active	Active		Any	Transfer, Hold, End, Conference
On Hold	Held		Any	Transfer, Resume, End, Conference
On Hold (Remote)	Remote Held		Any	Transfer, Hold, End, Conference
Active (In Conference)	Active		Conference	Transfer, Hold, End
Held (In Conference)	Held		Conference	Resume, Transfer, End
Ringing In (Recalled Call)	Call Recalled		Terminator	Answer, Conference, End

CALL REDIRECTION REASONS

The following table lists the possible reasons for redirecting calls.

REDIRECTION REASON	DESCRIPTION
busy	The call was redirected to a specified destination because the Call Forwarding Busy service was activated and the subscriber was busy. A subscriber is considered busy when there are too many active calls.
no answer	The call was redirected because the Call Forwarding No Answer service was activated and the subscriber did not answer within the specified number of rings.
unavailable	The call was redirected because the Call Forwarding Not Reachable service was activated and the subscriber's device was either unreachable or unregistered.
unconditional	The call was redirected because the Call Forwarding Always service was activated. When active, the Call Forwarding Always service redirects all incoming calls.
time of day	The call was redirected because the Call Forwarding Selective service was activated and the incoming call matched the specified time of day value.
do not disturb	The call was redirected because the Call Forwarding Busy service was enabled and the Do Not Disturb service was activated.
deflection	The call was transferred before being answered.
follow me	The call was redirected because one of the following services was activated: Simultaneous Ringing, Sequential Ringing, or Clearspan Anywhere.
out-of-service	The call session was redirected by the network with the reason set to "out-of-service?".
away	The call was redirected by the network with the reason set to "away".
transfer	The call was transferred after being answered.
voice mail	The call was redirected because the Call Forwarding Always to Voice Mail service was activated, the Call Forwarding Busy to Voice Mail service was activated, and the subscriber was busy, or the Call Forwarding No Answer to Voice Mail service was activated and there was no answer.
hunt group	The call was redirected to an agent by a hunt group.
call center	The call was redirected to an agent by a call center.
route point	The call was redirected to an agent by a route point.
unknown	The call was redirected for an unknown reason.

CONTACTS PANE

The *Contacts* pane contains your contact directories and allows you to use your contacts to make or manage calls. For information on using contacts to manage calls, see section

[Manage Calls](#). For information about organizing and managing your contact directories, see section [Manage Contacts](#).



Figure 25 Contacts Pane

The *Contacts* pane contains the following panels:

- [Search Panel](#)
- [Enterprise/Group Panel](#)
- [Common Panel](#)
- [Supervisors Panel \(Agents\)](#)
- [Speed Dial Panel](#)
- [Queues Panel](#)
- [Custom Directories Panels](#)

- [Instant Message Panel](#)
- [Outlook Panel](#)
- [Directories Panel](#)

The contact directories you have access to depend on your system configuration as well as the services assigned to you. For more information, contact your administrator.

The directories you see in the *Contacts* pane also depend on your setup. For information on selecting the directories to display in the *Contacts* pane, see section [Show or Hide Directories](#).

When you click a contact, the entry expands and the contact's information, such as phone numbers and the action buttons for the operations that you can currently take on that contact appear.

You can only view the details of one contact per directory at a time. When you click another contact in the same directory, the details of the currently expanded contact are automatically hidden.




Figure 26 Group Panel – Contact in Focus with Action Buttons

For the list of Call Center action buttons, see section [Call Action Buttons](#).

SEARCH PANEL

You use the *Search* panel to look for specific contacts in your contacts' directories and, if available, in the configured *LDAP* directory. For information about performing contact searches, see section [Search for Contacts](#).




Figure 27 Contacts Pane – Search Panel

ENTERPRISE/GROUP PANEL

The *Enterprise/Group* panel contains the contacts in your Clearspan group directory (if your group is part of a service provider) or enterprise directory (if your group is part of an enterprise. However, if your enterprise administrator restricted your access to the enterprise directory, you can only see the contacts from your group.)




Figure 28 Contacts Pane – Group Panel

COMMON PANEL

The *Common* directory contains the contacts in your group's common phone list configured by your administrator on Clearspan.




Figure 29 Contacts Pane – Common Panel

PERSONAL PANEL

The *Personal* panel contains the contacts from your Clearspan Personal Phone List. It displays the name/description and phone number of each contact.

For information about managing your personal contacts, see section [Manage Personal Contacts](#).




Figure 30 Contacts Pane – Personal Panel

AGENTS PANEL (SUPERVISORS)

The *Agents* panel is used by supervisors to monitor and manage agents under their supervision. For more information, see section [Manage Agents \(Supervisor\)](#).



Figure 31 Contacts Pane – Agents Panel

SUPERVISORS PANEL (AGENTS)

The *Supervisors* panel, available to agents, contains the list of your supervisors. The main purpose of this directory is to allow you to contact a supervisor quickly.



Figure 32 Contacts Pane – Supervisors Panel

Selected supervisors have their call status displayed. For more information, see section [Monitor Supervisors](#).

SPEED DIAL PANEL

The *Speed Dial* panel allows you to manage your Speed Dial 8 and Speed Dial 100 contacts. It is available to users who have been assigned Speed Dial 8 and/or Speed Dial 100 services. If you only have one of these services, you only see the entries for that service in your *Speed Dial* directory.

For each configured speed dial number, Call Center displays the speed dial code and description. The description is what you entered when configuring the number.

For information about managing your *Speed Dial* directory in Call Center, see section [Manage Speed Dial Numbers](#).




Figure 33 Contacts Pane – Speed Dial Panel

QUEUES PANEL

The *Queues* panel is available to both agents and supervisors. It lists the call centers you are staffing as an agent or monitoring as a supervisor and the associated Dialed Number Identification Service (DNIS) numbers. The primary purpose of this panel is to provide you with a quick way to transfer calls to queues.




Figure 34 Contacts Pane – Queues Panel

CUSTOM DIRECTORIES PANELS

If your administrator has configured custom contact directories for your group, you can access them from Call Center. A custom directory contains a subset of the contacts in your Clearspan group or enterprise directory.



Note: A custom directory has the same properties as the Group/Enterprise directory.




Figure 35 Contacts Pane – Custom Panel

INSTANT MESSAGE PANEL

The *Instant Message* panel displays IM&P contacts you are subscribed to and their presence state. You can chat with any contact that has an IM&P service assigned on Clearspan, but you can only see the presence state of the contacts to which you are subscribed. For information on subscribing to and chatting with IM&P contacts, see section [Monitor IM&P Contacts and Chat with Contacts](#).




Figure 36 Contacts Pane – Instant Message Panel

The *Instant Message* panel appears only if you have been assigned an IM&P service on Clearspan.

When your presence state is set to “Offline”, this panel is empty. To change your IM&P presence state, see section [Change Your Instant Messaging and Presence State](#).

OUTLOOK PANEL

The *Outlook* panel contains your Outlook contacts.




Figure 37 Contacts Pane – Outlook Panel

DIRECTORIES PANEL

The *Directories* panel consolidates the contacts from the following directories: *Enterprise/Group*, *Custom*, *Personal*, *Outlook*, and *Speed Dial*. This panel is always visible. You can choose which directories to display in the *Directories* panel and you can collapse the panel, but you cannot close it.



Figure 38 Contacts Pane – Directories Panel

You can also place a copy of a directory below the *Call Console*. This allows you to view more than one directory at a time easily. For more information, see section [Manage Contacts](#).

CALL HISTORY

The *Call History* dialog box, accessed from the *Call Console* via the Call History button, allows you to view your past calls. You can place a call to a number from Call History and manage call logs. For information on making calls from Call History, see section [Manage Calls](#), and for information on managing your call logs, see section [Manage Call History](#).




Figure 39 Call History Dialog Box

Each call log is displayed on a separate line. Call logs are grouped in three categories: Missed calls, Received calls, and Placed calls. The following information is displayed for each call log:

- The name or phone number of the remote party
- The date and time when the call was initiated

In addition, if you have the Enhanced Call Logs service assigned, the following information is displayed, as applicable:

- Duration
- Outgoing DNIS
- Redirection Number
- Redirection Type

If you also have the Security Classification service assigned, the security classification of calls is displayed.

When you click a call log, the Call Action button appears, allowing you to place a call to the remote party.



Figure 40 Call History Dialog Box – Call Log with Call Action Button

For the list of action buttons available in Call Center, see section [Call Action Buttons](#).

CONTROLS

Call Center controls are designed in a contextual manner, that is, most controls appear only when the action they represent can be taken. For example, when you enter a number or select a contact, a Dial button appears, allowing you to place a call. The contextual controls that correspond to call operations such as dialing, transferring calls, or putting calls on hold are called action buttons. They appear on the Dialer, in a call entry, in a directory entry (contact), in a call log, or on a queued call (**Supervisors**).

The following table lists the general controls used in Call Center and the controls displayed on the headers in the panels. For more information on the action buttons, see section [Call Action Buttons](#).

NAME	DESCRIPTION
Common Controls	
 Options	This is located in the upper-right corner of a pane or page. When clicked, it displays a drop-down menu of options that control the display of information in that pane/page. The available options depend on the context.
 Expand/Collapse	This shows or hides the contents of a window or panel.
 Close	This closes an interface element, such as window, pane, or panel.
 Edit	This allows you to edit a list of items, such as agents to monitor or speed dials.
Logo Bar, Dialer, Call Console, Directories Panel, and Search Panel Controls	

NAME	DESCRIPTION
 Web Pop URL	This opens a page in your browser at the configured URL to provide additional information about the caller.
 Outbound CLID	This allows you to select the phone number to use as your Calling Line ID for the next outgoing call.
 Disposition Code	This allows you to apply one or more disposition codes to the last call when you are in <i>Wrap-Up</i> .
Disposition : 	This allows you to apply one or more disposition codes to the selected call.
 Trace Call	This allows you to attach a trace to the last call.
 ACD State	This displays your current ACD state and allows you to change it.
 Presence State	This displays your current IM&P presence state and allows you to change it using the drop-down list.
 Call History	This displays Call History.
 Auto Answer	This allows you to turn Auto Answering on or off.
 Call Waiting	This allows you to turn Call Waiting on or off. It is available only if you have been assigned the Call Waiting service.
 End Conference	This ends a conference call.
 Leave Conference	This disconnects you from the conference while allowing other participants to continue the call.
 Hold Conference	This holds the conference call.
 Resume Conference	This resumes a held conference.
 Barge In	This “un-mutes” your Silent Monitoring call, thereby establishing a Three-Way Conference.
 Pull Out Directory	This places a selected directory below the Call Console.
Call Notification Pop-up Window	
 Web Pop URL	This opens a page in your browser at the configured URL to provide additional information about the caller.
 vCard	This saves the caller’s phone number and personal information as a vCard in Microsoft Outlook. It appears only when Outlook is running.
Chat Window	
 Call	This places a call to your chat partner.

NAME	DESCRIPTION
 Add User to Chat	This allows you to select users to add to the chat.
 Invite	This invites selected users to the chat.
 Pop-out	This takes a chat window out of the main interface and makes it a free-floating window.
 Pop-in	This anchors a free-floating chat window inside the main interface.
 Minimize	This minimizes the chat window.
 Close	This closes the chat window.
Supervisors Panel (Agents)	
 Emergency	This makes an emergency call to a supervisor.
 Escalate	This escalates a call to a supervisor.
Queued Calls Pane – Call Center Queue Panel (Supervisors)	
 Service Mode	This identifies and allows you to change the service mode of a supervised call center.
Scheduled Reports Window	
 Load Report	This loads a scheduled report, allowing you to view and modify it.
 Delete Report	This deletes a scheduled report.

CALL ACTION BUTTONS

Action buttons allow you to perform actions on calls, such as answering or transferring a call, or actions that result in a call being placed, such as dialing a number or contact. They appear on the Dialer, on a call line, in a call history log, in a directory entry, or (for supervisors) in a queued call entry.

Action buttons are contextual, that is, they appear on a line/entry when the corresponding action can be performed on that entry.

For example, when you click a contact in the *Group* directory, the contact expands and the Call button appears on the line for that contact, allowing you to call the contact. This is illustrated in *Figure* . Note that other buttons may appear on the line for a contact, depending on the call state and the contact's configuration.






Figure 41 Group Panel – Contact in Focus

The following table lists the action buttons available in Call Center.

BUTTON	DESCRIPTION
 Dial	This dials the number you entered in the <i>Dialer</i> .
 Call	This places a call to the selected contact or to a number from Call History. This button is used when there is only one number available for the contact.
 split Call	When there is more than one number available for a contact, the split Call button is displayed for the contact. Clicking the Call button, places a call to the default destination number of the contact. Clicking the drop-down arrow (the right Call button), displays the list of available numbers for the contact. Selecting a number places a call to that number.
 Redial	This redials the last dialed number.
 E-mail	This brings up a new e-mail message window with the contact's e-mail address, allowing you to send a message to the contact.
 Transfer	This transfers a call to an ad hoc number entered in the <i>Dialer</i> .
 Transfer	This transfers a call to a selected number or contact. This button is used when there is only one number available for the contact.
 split Transfer	When there is more than one number available for a contact, the split Transfer button is displayed for the contact. Clicking the Transfer button, transfers the call to the default destination number of the contact. Clicking the drop-down arrow (the right Transfer button),

BUTTON	DESCRIPTION
	displays the list of available numbers for the contact. Selecting a number transfers the call to that number.
 Answer	This answers an incoming call, answers an unanswered call for a contact, or resumes a held call.
 Hold	This places a call on hold.
 End	This ends a call.
 Trace	This generates a call trace on a call.
 Conference	This establishes a conference call or adds a call to a conference.
 Record	Starts call recording or marks a call that is already being recorded to be kept.
 Pause	Pauses call recording.
 Resume	Resumes call recording.
 Stop	Ends call recording.
 Camp	This camps a call on a busy contact.
 Escalate Call	This escalates a call to a selected supervisor.
 Emergency Call	This places an emergency call to a selected supervisor.
 Chat	This opens a chat window allowing you to chat with an IM&P contact.
 Web Pop URL	This opens a page in your browser at the configured URL to provide additional information about the caller.
 Delete Call Log	This deletes a call log from Call History.
For Supervisors Only	
 Queue	This allows the supervisor to make an agent join or leave queues.
 Monitor Next Call	This allows the supervisor to silently monitor the next call for a selected agent or call center.
 Monitor	This allows the supervisor to silently monitor the current call for a selected agent with an active call.
 ACD State	This allows the supervisor to change a selected agent's ACD state.
 Barge In	This allows the supervisor to barge in on an agent's call, by establishing a Three-Way Call between the supervisor and the two parties involved in the call.

BUTTON	DESCRIPTION
 Answer	This answers an unanswered call for a monitored agent.
 Promote	This promotes a selected call to the next highest priority bucket within the queue.
 Retrieve	This retrieves a call from the queue to the supervisor's device. When a call is manually retrieved via this action, the call is reported as an <i>Incoming</i> call rather than an <i>ACD</i> call in the reports.
 Reorder	This changes a call's position in the queue.

MANAGE CALLS

This section describes the operations you can perform to make and manage calls.

Your current calls are displayed in the *Call Console* with the calls currently involved in a conference displayed in a separate panel called *Conference Call*.



Note: You can only be involved in one conference at a time.




Figure 42 Call Console

The following subsection provides a quick reference to call management operations. These operations are described in detail in the rest of this section.



Note: For operations on calls that involve a contact, you can drag the call onto the contact and click the button for that contact, which corresponds to the operation you want to perform. For information, see [Drag and Drop Call onto Contact](#).

CALL MANAGEMENT OPERATIONS QUICK REFERENCE

The following table provides a summary of the actions that you can take to manage calls. These actions (operations) are described in more detail in the following sections.

FUNCTION	STEPS
Assign Disposition Code to Selected ACD Call	In the <i>Call Console</i> , click the target ACD call and select a code from the drop-down list that appears.
Assign Disposition Code while in Wrap-Up	In the <i>Call Console</i> , click the Disposition Code button and select a code from the list. The code is applied to the last released call.
Generate Call Trace for Selected Call	In the <i>Call Console</i> , click the Call Trace button for the target call.
Generate Call Trace for Last Released Call	In the <i>Call Console</i> , click the Call Trace button.
Answer Incoming Call	In the <i>Call Console</i> , click Answer for the target call.
Turn Auto Answer On	In the <i>Call Console</i> , click Auto Answer .
Open URL	In the <i>Call Notification</i> dialog box for an incoming call or on any call in the <i>Call Console</i> , click the Web Pop URL button.
Save a vCard	In the <i>Call Notification</i> dialog box for an incoming call, click the Add vCard button.
Place Call on Hold	In the <i>Call Console</i> , move the mouse over the call and click Hold .
Resume Held Call	In the <i>Call Console</i> , move the mouse over the call and click Retrieve .
Blind Transfer Call	Drag the call onto the target contact and click Transfer for that contact. Alternatively, enter the target number in the <i>Dialer</i> and click Transfer on the <i>Dialer</i> .
Transfer with Consultation	- While on the call, enter a number in the <i>Dialer</i> or select a contact in the <i>Contacts</i> pane and click Dial. - When the new call is connected, consult with the party. - When ready to transfer, select the original call. - Move the mouse over the new call that is not selected call and click Transfer.
Transfer to Queue	Drag the call onto the target queue in the <i>Queues</i> panel and click Transfer for that queue.
Make Emergency Call to Available Supervisor	In the <i>Call Console</i> , select the call to escalate and click the Emergency button in the <i>Supervisors</i> panel.
Make Emergency Call to Selected Supervisor	Drag the call to escalate onto an available supervisor in the <i>Supervisors</i> panel and click Emergency for that supervisor.
Blind Escalate Call	- In the <i>Call Console</i>, select the call to escalate. - In the <i>Supervisors</i> panel, click Escalate or click an available supervisor and click Escalate for that supervisor. - In the <i>Call Console</i>, move the mouse over the call to

FUNCTION	STEPS
	the supervisor and click Transfer before the supervisor answers the call.
Escalate with Consultation	- In the <i>Call Console</i>, select the call to escalate. - In the <i>Supervisors</i> panel, click Escalate or click an available supervisor and click Escalate for that supervisor. - Consult with the supervisor. - When ready to transfer, in the <i>Call Console</i>, move the mouse over the call to the supervisor and click Transfer.
Escalate with Conference	- In the <i>Call Console</i>, select the call to escalate. - In the <i>Supervisors</i> panel, click Escalate or click an available supervisor and click Escalate for that supervisor. - In the <i>Call Console</i>, move the mouse over the new call and click Conference.
Start Three-Way Conference	In the <i>Call Console</i>, select a call. Move the mouse over a call that is not selected and click Conference.
Add Participant to Conference	In the <i>Call Console</i> , move the mouse over a call and click Conference .
Hold Conference	In the <i>Conference Call</i> panel, click Hold .
Resume Conference	In the <i>Conference Call</i> panel, click Resume .
Hold Conference Participant	In the <i>Conference Call</i> panel, select the call to put on hold and click Hold for that call.
Take Conference Participant Off Hold	In the <i>Conference Call</i> panel, select a held call and click Resume for that call.
Leave Conference	In the <i>Conference Call</i> panel, click Leave Conference .
End Participant	In the <i>Conference Call</i> panel, select the target call and click End .
End Conference	In the <i>Conference Call</i> panel, click End Conference .
Set Outbound CLID	In the <i>Dialer</i> , click the Outbound CLID button and select the number to use as your calling line identity for the next call from the list.
Dial Ad Hoc Number	In the <i>Dialer</i> , enter the number to call and click Dial .
Re-dial Recent Number	In the <i>Dialer</i> , click Redial and select a number from the list.
Dial Recent Number	- In the <i>Dialer</i>, start entering the number to dial. A list of numbers starting with the entered digits appears. - Select a number from the list and click Dial.
Dial Contact	In the <i>Contacts</i> pane, click the contact and then click Call for that contact.

FUNCTION	STEPS
Dial from History	- In the <i>Call Console</i>, click the Call History button. - Select <i>Missed calls</i>, <i>Received calls</i>, or <i>Dialed calls</i> from the drop-down list. - In the <i>Call History</i> dialog box, move the mouse over a call log and click Call.
Dial from Search	In the <i>Search</i> panel, select a contact and click Dial .

DRAG AND DROP CALL ONTO CONTACT

In Call Center, you can drag a call from the Call Console and drop it on a target contact in one of your contact directories. This provides you with a quick way to perform operations on calls that involve a contact.

As the call is dragged, a green icon is displayed. When the call is dropped onto a contact, no action is taken on the call. The target contact expands and you can select the action button for the operation you want to perform on that call.




Figure 43 Dragging Call and Dropping on Contact

VIEW CALLS

You can view your current calls and your past calls (Call History). For information about Call History, see section [Manage Call History](#).

VIEW CURRENT CALLS

Your current calls are displayed in the *Call Console* with the calls involved in a conference displayed in a separate pane called *Conference Call*.




Figure 44 Call Console – View Current Calls

GROUP CALLS

Your current calls can be grouped by the call center they come from. When calls are grouped, direct calls are placed in a separate category.




Figure 45 Call Console – Grouped Calls

To group or ungroup calls:

1. On the *Call Console* header bar, click **Options** .
2. Select *Group By* and then *Calls From*.
3. To ungroup, repeat the operation by selecting *None* instead of *Calls From*.




Figure 46 Grouping Calls in Call Console

To view or hide calls in a group:

Click the **Show/Hide** button () to the left of the group name.

VIEW INCOMING CALL DETAILS

When you receive a new call, the call appears in the Call Console. If calls are grouped and the corresponding grouping is collapsed, it is expanded to make the call visible.

When the Call Notification feature is enabled, a *Call Notification* pop-up window appears on top of the system tray when you receive an inbound call.

- For calls to your direct number or extension, the following information is displayed:
 - Calling party name
 - Calling party number




Figure 47 Call Notification Pop-up Window for Call that is Not ACD Call

- For calls from a call center, the following information is displayed:
 - Calling party name
 - Calling party number
 - Call center name or DNIS name, followed by the time the call has been waiting in queue (wait time)
 - Number of calls in queue (queued calls)




Figure 48 Call Notification Pop-up Window for ACD Call

- In addition, for diverted calls, that is, calls that were forwarded or transferred before being delivered to you, the diversion information is also displayed.




Figure 49 Call Notification Pop-up Window with Diversion Information



Notes: You must have only one tab open in the browser running Call Center to receive call notifications.

If calls come within eight seconds of each other, the Call Notification pop-up window only appears for the first call of that series.

ASSIGN DISPOSITION CODES (PREMIUM CALL CENTER)

Disposition codes are additional attributes that can be applied to ACD calls to tag calls with comments, results, and so on. More than one disposition code can be assigned to a call.

You can assign disposition codes to current ACD calls or to the latest released ACD call while you are in the *Wrap-Up* state.

ASSIGN DISPOSITION CODES TO CURRENT CALL

To assign a disposition code to a current call:

1. From the *Call Console*, select the call and click it. The call line displays the *Disposition* drop-down list.




Figure 50 Call Console – Assigning Disposition Code to Active Call

2. From the list, select a code.

ASSIGN DISPOSITION CODES IN WRAP-UP

While you are in *Wrap-Up*, you can assign disposition codes to the last released ACD call.

To assign a disposition code to the last released call:

1. In the *Call Console*, click **Disposition Code** .
2. From the drop-down list that appears, select a code.



Figure 51 Call Console – Assigning Disposition Code in Wrap-Up

GENERATE CALL TRACE

Call Center allows you to generate a trace on active, held, released, or missed calls.



Note: You must be assigned the Customer Originated Trace service to use this capability.

A call trace contains the following information:

- The phone number of the user who initiated the trace. When the user does not have a phone number, the group phone number and the extension of the user is provided instead. For intra-group calls, only the caller's extension is used.
- The date and time the call was received.
- The identity (name and number) of the caller, if available.

Issuing more than one call trace request has no effect.

GENERATE CALL TRACE FOR SELECTED CALL

To generate a trace for a selected call:

Click **Trace**  for that call.

GENERATE CALL TRACE FOR LAST RELEASED CALL

You can generate a trace for the most recently released or missed call.

To generate a trace for the last released or missed call:

In the *Call Console*, click **Trace** .

RECORD CALLS

To record calls, you have to have the Call Recording service assigned and configured. You can record calls manually or have the system automatically record your calls. Depending on your Call Recording mode, Call Center may allow you to manually start, pause, resume, or stop recording a call.

For information on configuring your services, see the *Clearspan Web Interface Administration Guide*.

When a call is being recorded, the *Recording* state message appears on the line for the call.




Figure 52 Call Being Recorded

MANUALLY RECORD CALL

To manually record calls, you have to have the Call Recording service assigned and set to “On Demand”. For information on configuring your services, see the *Clearspan Application Server User Web Interface Administration Guide*.

To record a call, select the call in the *Call Console* and click **Record** .

In the *On Demand* mode, the call is recorded from the beginning, and you have to request the recording before the end of the call to keep the recording. In the *On Demand with User Initiated Start* mode, the recording starts from the moment when you click the **Record** button.

PAUSE AND RESUME CALL RECORDING

To pause and resume a recording, you have to have your Call Recording service mode set to On Demand, On Demand with User Initiated Start, or Always with Pause/Resume.

To pause a recording, select a call that is being recorded in the *Call Console* and click **Pause** .

The recording pauses until you resume it or the call ends.

To resume a paused recording, select a call whose recording has been paused in the Call Console and click Resume .

When you pause and resume a recording, only one call recording is generated for the call.

STOP CALL RECORDING

You can only stop recording a call if your Call Recording service mode is set to On Demand with User Initiated Start.

To stop recording a call, select the call that is being recorded (or whose recording has been paused) in the Call Console and click Stop .

If you click Start after a call recording has been stopped, a separate recording is created.

VIEW AND CHANGE SECURITY CLASSIFICATION OF CALLS

Call Center displays the security classification level of your current calls and allows you to change your assigned security classification level if you have the Security Classification service assigned and your security classification level is not “Unclassified”, which is the lowest level.

The security classification level of a call is the lowest security classification level for all call participants. Users who do not have a security level assigned are considered to have the security level of “Unclassified”.



Figure 53 Security Classification of Calls

CHANGE SECURITY CLASSIFICATION

You can change your security classification, but only to a level lower than your assigned level, and you can only do so while in an active call. The security classification level of your calls is then recalculated.

The security classification of a call can also change when other participants change their security classification level or when participants join or leave the call. If the security classification level of a call changes, then the new level is displayed.

After all your calls end, your security classification level is reset to your assigned security classification level.




Figure 54 Security Classification Levels

To change your security classification:

From the *Security Classification* drop-down list, select a new security classification level.

RECEIVE, ANSWER, AND END CALLS

You can answer calls manually or have your phone automatically answer incoming calls.

ANSWER CALL



Note: When using the Remote Office service, the Answer button is disabled.

To answer a ringing call:

Click **Answer**  for that call.

To answer an incoming call from a *Call Notification* pop-up window:

Click anywhere on the text in the pop-up window.

AUTO ANSWER CALLS

This feature is typically used by agents who use headsets with their phones and take care of a high volume of calls. It may be enabled either by you in the client or configured in the system by your administrator.



Note: Auto Answer only works if your device is compliant with Advanced Call Control (ACC).

To answer calls automatically:

In the *Call Console*, click **Auto Answer** . The button changes to this  to indicate that Auto Answer is on.

When Auto Answer is enabled, your phone automatically goes off-hook when it is alerted. This applies to both inbound and Click-To-Dial calls.

The Auto Answer feature may be enabled manually in the Call Center client or by the administrator on Clearspan.



Note: If this feature is enabled by your administrator, you must **not** enable the client-based Auto Answer using the Auto Answer button.

OPEN URL

For any current call, you can open a page in your browser that contains information about the calling party encoded in its URL. This can be done either from the *Call Notification* pop-up window that appears on top of the system tray for an incoming call or from the *Call Console* for any current call.

This feature is configured on the *Settings – General* configuration page. For more information, see section [Screen Pop](#).

To open a URL for an incoming call:

In the *Call Notification* pop-up window, click the **Web Pop URL** button .

To open a URL for any call:

In the *Call Console*, click the **Web Pop URL** button  for the target call.

SAVE VCARD

When you receive a call, a *Call Notification* pop-up window appears on top of the system tray. You can click a button in this window to save the caller's phone number and personal information as a vCard in Microsoft Outlook.

To save a vCard:

In the *Call Notification* pop-up window, click the **Add vCard** button . This button is only present when Outlook is running.

END CALL

To end a call:

Click **End**  for that call.



Note: If the call has not been answered yet, then the calling party continues to ring until there is no answer, until another applicable timer expires, or the user hangs up.

MAKE OUTBOUND CALLS

You can make calls to an ad hoc number, to a contact from any of your contacts' directories, or to a number from Call History. You can also specify the calling line identity to use for your outbound calls.

SET YOUR OUTGOING CALLING LINE IDENTITY (**PREMIUM CALL CENTER**)

As a Call Center agent, you can specify whether your direct number or a DNIS number assigned to one of your call centers should be used as your calling line identity when you make calls. This allows you to conduct outbound calling campaigns with an appropriate calling line identity presented to the called party.

To set your outgoing call identity for the next call:

In the *Dialer*, click the **Outbound CLID** button  and select the number from the drop-down list. The number you select is displayed as your CLID when you make the next call.




Figure 55 Dialer – Setting Outbound CLID

For information on permanently setting your outbound CLID, see section [Agent Policies \(Agent\)](#).

DIAL AD HOC NUMBER

You use the *Dialer*, located at the top of the *Call Console*, to place a call to an ad hoc number.



Figure 56 Dialer – Dialing Ad Hoc Number

To dial an ad hoc number:

In the *Dialer*, enter the phone number and click **Dial** . The client issues a Click-To-Dial attempt to the specified phone number and the call appears in the *Call Console*.

REDIAL NUMBER

Call Center keeps up to ten most recently dialed numbers, which you can redial using the *Dialer*.

To redial one of the recently dialed numbers:

1. In the *Dialer*, place the cursor in the text box and start entering a number. A list of recently called numbers that start with the entered digits appears.




Figure 57 Dialer – Select Recently Dialed Number

2. Select the number to dial and click **Dial** .

The client issues a Click-To-Dial attempt to the selected number.

Alternatively, click the **Redial**  button and select the number from the list that appears.




Figure 58 Dialer – Redialing Number

DIAL CONTACT

You can use any directory in the *Contacts* pane to dial a contact.

To dial a contact:

1. In the *Contacts* pane, expand the directory from which you want to dial a contact.
2. Click the target contact to expand it and click **Call**  for that contact. This places a call to the contact's default number.



Figure 59 Group Panel – Calling Contact's Default Number

Alternatively, to dial the contact's mobile or any other available number, click the right Call button  and select the number from the list.




Figure 60 Group Panel – Calling Contact's Alternate Number

The client issues a Click-To-Dial attempt to the specified phone number and the call appears in the *Call Console*.

DIAL FROM SEARCH

You use the *Search* panel in the *Contacts* pane to search for contacts in your contacts' directories. For more information, see section [Search for Contacts](#).

To dial a number from search:

1. Perform a search.
2. Click the target contact to expand it and then click **Call** .
3. Alternatively, to dial a different number for the contact, click the right Call button  and select the number from the list.




Figure 61 Dial From Search

DIAL FROM HISTORY

You can dial any number that is available in Call History.

To dial from Call History:

1. In the *Call Console*, click **Call History** . The *Call History* dialog box appears.




Figure 62 Call History Dialog Box

2. From the Show drop-down list, select Missed Calls, Received Calls, or Placed Calls.
3. Click the call log from which you want to dial and then click the **Call**  button.

PLACE CALLS ON HOLD, RESUME, AND CAMP CALLS

You can only put an active call on hold.



Note: When using the Remote Office service, Hold/Resume buttons are disabled.

PLACE CALL ON HOLD

To place a call on hold, click **Hold**  for the target call.

RESUME HELD CALL

To resume a held call, click **Answer**  for the target call.

CONDUCT BUSY CAMP ON

Busy Camp On allows you to find a temporary parking place for a call by placing the call on hold for a busy contact. The call is automatically transferred to the destination when the contact becomes available. A call to camp must be active or held and the destination contact's phone state must be either *Busy* or *Ringin*g.

If the camped call is not answered within the predefined time, the call is recalled and reappears in your *Call Console*.

Agents can camp calls on monitored contacts in their *Supervisors* directory and supervisors can camp calls on monitored contacts in their *Agents* directory. For information on monitoring supervisors, see section [Monitor Supervisors \(Agent\)](#). For information on monitoring agents, see section [Manage Agents \(Supervisor\)](#).

To camp a call on a busy contact:

1. From the *Call Console*, select an active or held call.
2. In your Supervisors or Agents directory, select the contact to camp the call on. The contact's phone state must be *Busy* or *Ringin*g.
3. Move the mouse over the contact and click **Camp** .

Once the call is camped, it is removed from the *Call Console*.

If the camped call timer expires before the call is answered, the call reappears in the *Call Console*.

TRANSFER CALLS

There are a number of ways in which you can transfer a call, including blind transfer, transfer with consultation, and transfer to queue.

BLIND TRANSFER

Use this method to transfer a call to another number without providing an introduction to the destination party. Calls may be transferred this way while active, held, or ringing (in) on your phone. In the latter case, the system redirects the call before it is answered.

To blind transfer a call to an ad hoc number:

1. From the *Call Console*, select the call to transfer.
2. In the Dialer, enter the destination number and click Transfer . The call is transferred and removed from the *Call Console*.

To blind transfer a call to a contact:

1. From the *Call Console*, select the call to transfer.
2. In the *Contacts* pane, expand the directory from which you want to select a contact.
3. Click the destination contact and click **Transfer**  for that contact. Alternatively, to transfer the call to the contact's mobile or any other available number, click the right **Transfer** button  and select the number from the list.
4. The call is transferred and removed from the *Call Console*.

TRANSFER WITH CONSULTATION

Use this method to transfer a call with an introduction to the destination party. Calls may be transferred this way while active, held, or ringing (in) on your phone. In the latter case, the system redirects the call before it is answered.

To transfer a call with consultation:

1. Make a call to the person to whom you want to transfer the call. If the first call was active, it is put on hold.
2. Wait until the called party accepts your call and speak to the party.
3. When ready to transfer, from the *Call Console*, select one of the two calls.

4. Move the mouse over the call that is not selected and click **Transfer** .

The calls are connected and removed from the *Call Console*.

TRANSFER TO QUEUE

You can transfer a call back to a queue. A transferred call is placed at the bottom of the queue.

To transfer a call to a queue:

1. From the *Call Console*, select the call to transfer.
2. In the *Contacts* pane, expand the *Queues* panel.
3. Click the destination queue and click **Transfer**  for that queue.

The call is transferred to the selected queue and removed from the *Call Console*.

Alternatively, drag the call onto the target queue and click **Transfer**  for that queue.

ESCALATE CALLS

You can escalate calls to the first available supervisor or to a specific supervisor. You can also make an emergency call, which quickly conferences an available supervisor into your call, without placing the remote party on hold.

You use the *Supervisors* panel located in the *Contacts* pane to escalate calls.

MAKE EMERGENCY CALL

Use this method to escalate a call to a supervisor in an emergency situation. When you make an emergency call, the caller is not placed on hold; instead, a supervisor is immediately conferenced in to the call. You can let Call Center select the supervisor or you can select the supervisor yourself.



Note: To make emergency calls, you must have the Three-Way Call or N-Way Call service assigned.

To make an emergency call to an available supervisor:

1. While on the call, click Emergency  in the *Supervisors* panel.




Figure 63 Supervisors Panel – Making Emergency Calls

This places the call to the first available supervisor. When the supervisor answers the emergency call, a Three-Way call or an N-Way call is started, without putting the caller on hold.

2. To transfer the call to the supervisor, click **LEAVE** in the Conference Call panel after the conference is established.



Figure 64 Conference Call Panel – Leave Conference

To make an emergency call to a specific supervisor:

1. While on a call, expand the *Supervisors* panel.
2. Click the target supervisor and click the **Emergency** button  for that supervisor. Make sure the supervisor you selected is available.

Alternatively, drag the call onto the target supervisor and click the **Emergency** button  for that supervisor.

This places the call to the selected supervisor. When the supervisor answers the emergency call, a Three-Way call or an N-Way call is started, without putting the caller on hold.

3. To transfer the call to the supervisor, click **LEAVE** in the Conference Call panel after the conference is established.

BLIND ESCALATE CALL

Use this method to escalate a call to a supervisor without consulting the supervisor. You can escalate a call to the first available supervisor or select the supervisor yourself.

To blind escalate a call:

1. In the *Supervisors* panel, click **Escalate**  to let the system select a supervisor; or, to select the supervisor yourself, click an available supervisor and click the **Escalate** button  for that supervisor. Your original call is placed on hold and a call to the supervisor is initiated.
2. Without waiting for the supervisor to answer, in the Call Console, select the original call.
3. Move the mouse over the call to the supervisor and click **Transfer** .

ESCALATE WITH CONSULTATION

Use this method to escalate a call to a supervisor and provide an introduction beforehand. You can escalate the call to the first available supervisor or select the supervisor yourself.

To escalate a call with consultation:

1. In the *Supervisors* panel, click **Escalate**  to let the system select a supervisor; or, to select the supervisor yourself, click an available supervisor and click **Escalate**  for that supervisor.
2. Wait until the supervisor accepts your call and speak to the supervisor.
3. When ready to transfer the call, in the Call Console, select the original call.
4. Move the mouse over the call to the supervisor, and click **Transfer** .

ESCALATE WITH CONFERENCE OR HANDOVER

Use this method to escalate a call to a supervisor through a conference call. You can then leave the call.

To escalate a call with conference or handover:

1. In the *Supervisors* panel, click **Escalate**  to let the system select a supervisor; or, to select the supervisor yourself, click an available supervisor and click **Escalate**  for that supervisor.
2. When the supervisor accepts your call, speak to the supervisor about the issue.
3. In the *Call Console*, select the original call.
4. Move the mouse over the call to the supervisor and click **Conference** . A conference call is established and the calls appear in the *Conference Call* panel.
5. To hand the call over to the supervisor, click **Leave Conference**  in the *Conference Call* panel.

ESCALATE WITH MID-CONFERENCE HOLD

Use this method to escalate a call to a supervisor through a conference call and provide an opportunity for the customer to speak to the supervisor.

To escalate a call with mid-conference hold:

1. In the *Supervisors* panel, click **Escalate**  to let the system select a supervisor; or, to select the supervisor yourself, click an available supervisor and click **Escalate**  for that supervisor.
2. When the supervisor accepts your call, speak to the supervisor about the issue.
3. In the *Call Console*, select the original call.
4. Move the mouse over the call to the supervisor and click **Conference** . A conference call is established and the calls appear in the *Conference Call* panel.
5. In the *Conference Call* panel, click **Hold Conference** . This puts both calls on hold but allows the customer and the supervisor to continue their conversation.
6. To drop a specific party from the conference, select their call from the *Conference Call* panel and click **End** .
7. To leave the call, click **Leave Conference**  in the *Conference Call* panel.

MANAGE CONFERENCE CALLS

You manage conferences in the *Call Console*. You use the:

- Current calls area to establish a conference and add participants to it.

- *Conference Call* panel to manage or end an active conference call.

You can only have one active conference at a time.



Figure 65 Call Console – Conference Call Panel



Note: To start conference calls, you must have the Three-Way Call or N-Way Call service assigned.

START THREE-WAY CONFERENCE

To start a conference call, you must have at least two current calls. The calls can be received or made by you. If required, make calls using any of the methods described in section [Make Outbound Calls](#).

To start a conference:

1. In the *Call Console*, select a call.




Figure 66 Call Console – Starting Conference Call

2. Move the mouse over a call that is not selected and click **Conference** . A Three-Way Conference is established and the connected calls appear in the *Conference Call* panel.




Figure 67 Conference Call Panel – Conference Call

ADD PARTICIPANT TO CONFERENCE



Note: To add participants to a conference, you must have the N-Way Calling service assigned.

To add a participant to a conference:

1. If the call you want to add to the conference is not yet established, place the call.
2. In the *Call Console*, move the mouse over the call and click **Conference** . The call is added to the conference.

HOLD CONFERENCE

To put an active conference on hold:

In the *Conference Call* panel, click **Hold Conference** . This allows other conference participants to continue their conversation.

RESUME CONFERENCE

To resume a conference call that you previously put on hold:

In the *Conference Call* panel, click **Resume Conference** . All the calls in the conference become active.

HOLD PARTICIPANT

To put a specific conference participant on hold:

1. Expand the *Conference Call* panel.
2. Move the mouse over the target call and click **Hold** .

TAKE PARTICIPANT OFF HOLD

To resume a participant's held call:

1. Expand the *Conference Call* panel.
2. Move the mouse over the target call and click **Answer** .

LEAVE CONFERENCE

To leave the conference:

In the *Conference Call* panel, click **Leave Conference** . The other parties continue their conversation.



Note: This function is only available for Three-Way Conferences.

END PARTICIPANT

To end a selected call in a conference:

1. Expand the *Conference Call* panel.
2. Move the mouse over the call and click **End** .

END CONFERENCE

To end the conference:

In the *Conference Call* panel, click **End Conference** . This releases all the calls that participated in the conference.

MANAGE CALL HISTORY

Call Center collects call logs for your placed, received, and missed calls. You can call any number available in Call History. For information on making calls from Call History, see section [Manage Calls](#).

This section explains how to view and delete call logs.

VIEW CALL HISTORY

You can view your placed, received, and missed calls.



Note: The format in which date and time are displayed in the Call History dialog box depends on the date and time settings selected on the Settings – General configuration page.

To view your call history:

1. In the *Call Console*, click **Call History** . The *Call History* dialog box appears displaying your past calls. The calls are grouped into placed, received, and missed calls. By default, missed calls are displayed.




Figure 68 Call History Dialog Box

2. To show calls in a specific group, select that group from the *Show* drop-down list.

DELETE CALL HISTORY

You can delete a selected call log or all call logs from Call History.

To delete calls from Call History:

1. In the *Call Console*, click **Call History** . The *Call History* dialog box appears.
2. To delete all call logs, click **Delete All** .
3. To delete a selected log, move the mouse over the log and click **Delete** .

E-MAIL CONTACTS

Call Center allows you to send an e-mail message to a contact that has e-mail configured on the system. You must also have messaging enabled within Call Center settings. For information, see section [Settings – Messaging](#).

The **EMAIL** button appears when you select a contact that has an e-mail address configured.

SEND E-MAIL MESSAGE TO CONTACT

To send an e-mail message to a contact:

1. In the Group/Enterprise directory, move the mouse over a contact who has e-mail.
2. Click EMAIL . This brings up a new e-mail window for the configured Messaging service.
3. Write your message and click **Send**.

MANAGE CONTACTS

You use the *Contacts* pane to perform call and monitoring operations on your contacts as well as to manage your contacts' directories.




Figure 69 Contacts Pane

Call Center provides access to the contacts' directories listed in the following table.

INTERFACE ELEMENT	DESCRIPTION
Enterprise/Group	The <i>Enterprise/Group</i> directory contains the contacts in your Clearspan group or enterprise directory.
Common	The <i>Common</i> directory contains the contacts in the common phone list configured by your administrator on Clearspan.
Personal	The <i>Personal</i> directory contains all contacts in your Personal Phone List on Clearspan.
Supervisors (Agents)	The <i>Supervisors</i> directory, available only to agents, contains the list of your supervisors and allows you to view their phone state.

INTERFACE ELEMENT	DESCRIPTION
Agents (Supervisors)	The <i>Agents</i> directory, available only to supervisors, contains the list of agents you supervise and allows you to manage them and view their phone and ACD state.
Speed Dial	The <i>Speed Dial</i> directory contains the numbers configured for you or by you for your Speed Dial services (Speed Dial 8 and/or Speed Dial 100).
Queues	The <i>Queues</i> directory lists the call centers and associated DNIS numbers for the call centers you are either supervising or staffing. It allows you to transfer calls to queues quickly.
Custom	A <i>Custom</i> directory contains selected contacts from your Clearspan group or enterprise directory. You can have access to zero, one, or several custom directories. Custom directories are configured by your administrator.
Outlook	The <i>Outlook</i> directory contains your Outlook contacts.
Instant Message	The <i>Instant Message</i> directory lists IM&P contacts to which you are subscribed.
LDAP (Search Access Only)	Call Center provides search access to a configured <i>LDAP</i> directory. When you make a search on the <i>LDAP</i> directory and your search returns results, these results are displayed in the <i>Search</i> panel (in the <i>Contacts</i> pane). By default, no LDAP contacts are displayed in the <i>Contacts</i> pane.

Access to certain directories depends on your permissions and the system setup. For information, contact your administrator.

The *Contacts* pane also contains the *Directories* panel, which consolidates the contacts from the following directories: *Enterprise/Group*, *Custom*, *Personal*, *Outlook*, and *Speed Dial*. The *Contacts* pane is always visible. You can choose which directories to display in the *Directories* panel and you can collapse the panel, but you cannot close it.

For information about the operations you perform to manage your contact directories, see the following sections:

- [View Contacts](#)
- [Organize Contacts](#)
- [Search for Contacts](#)
- [Manage Personal Contacts](#)
- [Manage Speed Dial Numbers](#)
- [Monitor IM&P Contacts and Chat with Contacts](#)

VIEW CONTACTS

Call Center allows you to select directories to display in the *Contacts* pane and below the *Call Console*, show or hide directory contents, and select the order of appearance for information in certain directories.

SHOW OR HIDE DIRECTORIES

You can decide which of the directories that you are allowed to access appear in the *Contacts* pane.

All directories can be displayed individually in the *Contacts* pane.

In addition, you can decide which directories to display in the *Directories* panel (on their own or with other directories), and below the *Call Console*.

To show or hide a directory in the *Contacts* pane:

1. In the *Contacts* pane, click **Options** .
2. Select *View*, *Directories*, and then select or unselect the directory to display/hide. To display all directories, select *All*.

To hide a directory, you can also click the **Close** button  for that directory.



Note: You cannot close the *Directories* panel.




Figure 70 Contacts Pane – Show/Hide Contact Directories

To show a directory in the Directories panel:

In the *Directories* panel, select the directory to display from the drop-down list. To display all directories, select *Show all*.




Figure 71 Directories Panel – Selecting Directory to Display

DISPLAY DIRECTORY BELOW CALL CONSOLE

To display a directory below the Call Console:

1. In the *Directories* panel, select *Show all*.




Figure 72 Directories Panel – Selecting Directory

2. Click the **Pullout Directory** button  for the directory to display.

The directory appears below the *Call Console*.




Figure 73 Custom Directory Displayed Below Call Console

To close the directory, click the **Close** button .

SHOW OR HIDE DIRECTORY CONTENT

By default, your directories are collapsed, with only the title bar visible. You can selectively expand the directories that you want to consult or use.

To show or hide contacts in a directory:

In the *Contacts* pane, click the **Expand/Collapse**  button for that directory.




Figure 74 Group Panel Expanded

SHOW CONTACT DETAILS

You can view the details of a contact in any directory.

To view contact details:

1. Expand the target directory.
2. Click the contact. The entry expands, displaying the contact's details. The information depends on the target directory and includes the contact's phone numbers or IDs and action buttons.

Only one contact per directory can be expanded at a time. When you click a contact, the system automatically hides the details of the previously expanded contact.




Figure 75 Group Panel – Contact Details

SELECT DISPLAY ORDER

Contacts in the *Group/Enterprise*, *Agents*, and *Supervisors* directories can be displayed by either their first name or last name first. Your selection applies to all of these directories. You cannot specify the display order for each directory individually.

To specify the contacts' display order:

1. In the *Contacts* pane, click the **Options** button .
2. Select *View*, then *Display Name*, and then the order in which you want to display the contacts: *Last Name, First Name* -or- *First Name, Last Name*.




Figure 76 Contacts Pane – Displaying Contacts by First Name, Last Name

Figure shows supervisors displayed by their last name followed by their first name.




Figure 77 Supervisors Panel – Supervisors Listed by First Name, Last Name

ORGANIZE CONTACTS

SORT CONTACTS

You can sort contacts in the following directories: *Group/Enterprise*, *Queues*, and *Agents*.

To order contacts in a directory:

1. In the *Contacts* pane, click **Options** .
2. Select *Sort*, followed by the name of the directory in which you want to sort contacts, and then the sorting option.




Figure 78 Contacts Pane – Sorting Contacts

Figure shows a *Group* directory sorted by the contact's first name.



Figure 79 Group Panel – Contacts Sorted by First Name



Note: When agents are sorted by ACD state and there is a change in an ACD state, the agents are not automatically re-sorted.

SEARCH FOR CONTACTS

Call Center provides you with a search function that allows you to search for specific contacts in your directories.

You use the *Search* panel in the *Contacts* pane to look for contacts.




Figure 80 Contacts Pane – Search Panel

PERFORM CONTACT SEARCH

To search for contacts:

1. In the *Search* text box, enter the text you want to search for and press ENTER. You can enter partial information, such as part of a name or phone number.

For example, if you do not remember whether Mary's last name is spelled "Shelley" or "Shelly", you can enter "Shell", and either name is returned.

2. To restrict the search to contacts that start with the entered text, check the *Begins with* box.
3. From the drop-down list, select the directories to search.
4. Press **Enter**.

The text you enter is matched against all attributes of every entry in the selected directories.



Note: The search is not case-sensitive; the search for "Ann" and "ann" returns the same results.

Search results are displayed in the *Search* panel, each contact listed with the name of the directory where they were found.

Clearspan directories are searched in the following order: Supervisors, Agents, Group/Enterprise. Duplicate search results in Clearspan directories are not displayed; the first match for a given contact is displayed.

Duplicate search results in other directories are displayed.



Figure 81 Contacts Pane – Search Results

The search returns either all the contacts (in the selected directories) that contain the entered keyword or all the contacts that start with the entered keyword.

In the first case (*Contains*), entering “Ann” and selecting “First Name” from the *Keyword Search Filter* drop-down list returns all contacts with the first name “Ann”, but it also returns all contacts with first names such as “Anne”, “Marianne”, “Marie Ann”, “Ann Marie”, and so on.

In the second case (*Starts With*), entering “Ann” and selecting “First Name” returns all contacts with first names such as “Ann”, “Anne”, and “Ann Marie”, but not “Marianne” or “Mary Ann”.

5. To clear the search results, click **Reset** .



Note: Contact entries displayed in search results follow the same rules as if that entry was accessed in its own directory. This allows you to perform any operations directly from the search results.

MANAGE PERSONAL CONTACTS

You can add or remove personal contacts via the web portal or in Call Center, and the updates appear in both places. However, the updates that you make via the web portal appear only in Call Center at the next sign-in.

To update personal contacts using the client, perform the following operations:

- [Add Personal Contact](#)
- [Delete Personal Contact](#)

You cannot modify a personal contact entry in Call Center. To modify information for a personal contact, delete the entry and add it again.

ADD PERSONAL CONTACT

To add a personal contact:

1. In the *Personal* panel, click **Edit** . The *Edit Personal Contact* dialog box appears.
2. Click **Add**. A new line is added below the existing entries, allowing you to define a new entry.




Figure 82 Edit Personal Contact Dialog Box – Adding Entry

3. In the Name text box, enter the contact's name or description, as you want it to appear on the contact's list.
4. In the Number text box, enter the phone number of the contact.
5. To save the entry, click anywhere in the dialog box outside the entry.

DELETE PERSONAL CONTACT

To delete a speed dial entry:

1. In the *Personal* panel, click **Edit** . The *Edit Personal Contact* dialog box appears.
2. Select the entry to delete and click **Delete**.




Figure 83 Edit Personal Contact Window – Deleting Entry

MANAGE SPEED DIAL NUMBERS

You can add or remove speed dial numbers via the web portal or in Call Center, and the updates appear in both places. However, the updates that you make via the web portal appear only in Call Center at the next sign-in.


To update speed dial entries using the client, perform the following operations:

- [Add Speed Dial Entry](#)
- [Modify Speed Dial Entry](#)
- [Delete Speed Dial Entry](#)

ADD SPEED DIAL ENTRY

To add a speed dial entry:

1. In the *Speed Dial* panel, click **Edit** . The *Edit Speed Dials* dialog box appears.
2. Click **Add**. A new line is added below the existing entries, allowing you to define a new entry.



Code	Phone Number	Description
2	2023454333	My dentist


Figure 84 Edit Speed Dials Dialog Box – Adding Entry

3. From the *Code* drop-down list, select a speed dial code.
4. In the *Phone Number* text box, enter the phone number to assign to the code.
5. In the *Description* text box, enter a description that allows you to identify the entry.
6. To save the changes, click anywhere in the dialog box outside the entry.

MODIFY SPEED DIAL ENTRY

To modify a speed dial entry:

1. In the *Speed Dial* panel, click **Edit** . The *Edit Speed Dials* dialog box appears.
2. Double-click the entry to modify. The entry becomes modifiable.



Code	Phone Number	Description
2	2023454333	My dentist
6	2025849345	Daycare
#00	2025505934	Weather
#02	2407777777	Brad Green

Figure 85 Edit Speed Dials Dialog Box – Modifying Entry

3. Modify information as required.
4. To save the changes, click anywhere in the dialog box outside the entry.

DELETE SPEED DIAL ENTRY

To delete a speed dial entry:

1. In the *Speed Dial* panel, click **Edit** . The *Edit Speed Dials* dialog box appears.
2. Select the entry to delete and click **Delete**.




Figure 86 Edit Speed Dials Dialog Box – Deleting Entry

MONITOR IM&P CONTACTS AND CHAT WITH CONTACTS

When you have an IM&P service assigned on Clearspan, you can chat with other IM&P users and see the unified presence state of selected IM&P users directly from Call Center. The unified presence of a contact is their presence state when they are logged in through multiple devices or applications, such as IM&P or Clearspan Communicator.

IM&P capabilities are available only when you are online. For information on setting your IM&P presence state, see section [Change Your Instant Messaging and Presence State](#).

MONITOR IM&P CONTACTS

To view the presence state of an IM&P contact, you have to first subscribe to the contact. Otherwise, Call Center displays the contact's state as *Unsubscribed*. When you send a subscription request to a contact and are waiting for their reply, Call Center displays the contact's state as *Pending Subscription*.

The following directories display the IM&P state of contacts: Instant Message, Agent, Supervisor, Enterprise/Group, Custom, Search, and Directories.



Note: The Instant Message panel does not include IM&P contacts in the *Unsubscribed* state.

You can subscribe to a contact either by sending a subscription request to the contact or by adding the contact to the *Instant Message* directory.

For information about the operations related to subscribing to contacts and viewing their presence state, see the following sections:

- [Subscribe to Contact](#)
- [Add Contact to Instant Message Directory](#)
- [Modify Contact Name](#)
- [Unsubscribe from Contact](#)
- [Accept or Reject Subscription Request](#)
- [View Unified Presence State of Contacts](#)

SUBSCRIBE TO CONTACT

To send a subscription request to a contact:

1. Click the IM&P presence icon of an unsubscribed contact  in any directory where the presence state of contacts is displayed. The *Contact (IM) Subscribe* dialog box appears.




Figure 87 Contact (IM) Subscribe Dialog Box

2. Click **Yes**.

A subscription request is sent to the contact, and the contact is added to the *Instant Message* directory. The contact's state is set to "Pending Subscription" .

When the subscription is accepted, the contact's presence state is updated to their actual presence state.

3. To resend a subscription request at any time, click the contact's presence icon again and click **Resend** in the dialog box that appears.




Figure 88 Contact (IM) Re-Subscribe Dialog Box

ADD CONTACT TO INSTANT MESSAGE DIRECTORY

When you add a contact to the *Instant Message* directory, the system automatically sends a subscription request to the contact.

To add a contact to the Instant Message directory:

1. In the *Instant Message* panel, click **Edit** . The *Edit Instant Message Contacts* dialog box appears.

2. Click **Add**. A new line is added below the existing entries, allowing you to define a new entry.




Figure 89 Edit Instant Message Contacts Dialog Box – Add Contact

3. In the *Name* text box, enter the display name of the contact to add.
4. In the IM ID text box, enter a valid IM&P ID of the contact.
5. To save the changes, click anywhere in the dialog box outside the entry.

A subscription request is sent to the contact, the contact's presence state is set to "Pending Subscription", and the contact is added to the *Instant Message* panel.

When the subscription is accepted, the contact's presence state is updated to their actual presence state.

MODIFY CONTACT NAME

You can modify the display name of an existing contact.

To modify the name of a contact:

1. In the *Instant Message* panel, click **Edit** . The *Edit Instant Message Contacts* dialog box appears.
2. Double-click the contact and enter the new name in the *Name* text box.
3. To save your changes, click anywhere in the dialog box outside the entry.




Figure 90 Edit Instant Message Contacts Dialog Box – Modify Contact

UNSUBSCRIBE FROM CONTACT

To stop monitoring a contact:

1. Click the presence icon of the contact. The Contact (IM) Unsubscribe dialog box appears.




Figure 91 Contact (IM) Unsubscribe Dialog Box

2. Click **Yes**. The contact is removed from the *Instant Message* directory and its presence status changes to *Unsubscribed* in other directories.

ACCEPT OR REJECT SUBSCRIPTION REQUEST

When you receive a request from another user, a dialog box appears allowing you to accept or deny the request.




Figure 92 Contact (IM) Request Dialog Box

To accept the request, click **Yes**. If the contact is not yet in your *Instant Message* directory, a request is sent automatically to add the user to the directory.

To reject the request, click **No**.

You can also close the dialog box and ignore the request. If you ignore the request, the dialog box will reappear the next time you go online.

VIEW UNIFIED PRESENCE STATE OF CONTACTS

You can view the unified presence state of IM&P contacts in the *Instant Message*, *Agent*, *Supervisor*, *Enterprise/Group*, *Custom*, *Directories*, and *Search* panels. The presence icon is displayed to the left of the contact's name.

Unified instant messaging presence states indicate your contacts' availability to communicate using client applications such as Hosted Thin Call Center, Hosted Thin Receptionist, Clearspan Communicator Desktop, or Clearspan Communicator Mobile.

The actual IM&P state of a contact is displayed only if you are subscribed to the contact. Otherwise the contact's state is displayed as *Unsubscribed* or *Pending Subscription*. Manual states are the states that you can set yourself and automatic states are the states set by the system based on the information received from other applications.




Figure 93 Instant Message Directory – Unified Presence State of Contacts

The following table lists the possible unified presence states in Call Center:

PRESENCE STATE	ICON	DISPLAY NAME	DESCRIPTION
Manual States			
<i>Available</i>		available	The contact is online, available on one or more devices, and not busy on any device.
<i>Busy</i>		busy	The contact is online, but currently busy on one or more devices. Do not disturb.
<i>Away</i>		away	The contact is connected but away from one or more devices and not busy on any device.

PRESENCE STATE	ICON	DISPLAY NAME	DESCRIPTION
<i>Offline</i>		offline	The contact is offline on all devices.
Automatic States			
<i>Mobile Away</i>		mobile	The contact is online on their mobile client but has been idle or away from their device for more than 10 minutes.
<i>Busy-Call</i>		call	The contact is busy due to a call.
<i>Busy-Meeting</i>		meeting	The contact is busy due to a meeting. The Busy-Call state overrides the Busy-Meeting state so this state is only seen if the contact has a meeting but no call.
<i>Offline In-Call</i>		call	The contact is offline and the only available contact method is calling or leaving a chat message.
Unsubscribed states			
<i>Pending Subscription</i>			You sent a subscribe request to the contact, but it has not yet been accepted. Clicking the icon resends the request.
<i>Not subscribed</i>			The contact has the IM&P service but you are not subscribed to monitor their state. The contact does not appear in the <i>Instant Message</i> pane. Clicking this icon sends a subscription request to the contact.

CHAT WITH IM&P CONTACTS

You can have several concurrent one-on-one or multiuser instant messaging sessions open.

You can chat with more than one contact at the same time, either in one-on-one sessions or by participating in multiuser chats. Each session requires a separate window.

Chat windows appear at the bottom-right hand side of the Call Center main interface. Subsequent windows open to the left of the latest opened *Chat* window.

Chat windows can be taken out of the main interface and placed elsewhere on the screen.

The number of concurrently open *Chat* windows depends on the browser window size and screen resolution. The oldest *Chat* window is closed when there is no more room for a new *Chat* window to open. This only applies to *Chat* windows that are placed within the main interface.

You can start a chat session with a contact or accept a session request from another user. A one-on-one session can be converted into a multiuser chat by inviting more participants. You can also receive an invitation to a multiuser chat from another user.

When your IM&P contact is in your group/enterprise, you can also phone them directly from the *Chat* window.

The tasks related to instant messaging are described in the following sections:

- [Start Instant Messaging Session](#)
- [Place Call from Chat Window](#)
- [Establish Multiuser Chat Session](#)
- [Manage Instant Messaging Sessions](#)

START INSTANT MESSAGING SESSION

You can start an instant messaging session with an IM&P contact from any of the following panels: *Instant Message*, *Agent*, *Supervisor*, *Enterprise/Group*, *Custom*, *Search*, and *Directories*.

To start an instant messaging session with a contact:

1. In the *Contacts* pane, click the target contact. The entry expands displaying available action buttons.




Figure 94 IM&P Contact with Chat button

2. Click **Chat**  on the line for the contact. A *Chat* window appears, displaying your contact's information on the title bar.




Figure 95 Chat Window



Note: A *Chat* window also appears when another IM&P user initiates a chat session with you.

3. Type your message in the text box at the bottom of the window and click ENTER. Your message is sent to your contact.

The messages you send and receive appear in the *Chat Logs* area at the top of the window, below the title bar. Up to 50 messages per contact are kept in the log for the duration of your IM&P session, even if you close the *Chat* window and later start exchanging messages again with the same contact. The messages are cleared when you go offline.

PLACE CALL FROM CHAT WINDOW

If the user with whom you are chatting is also a contact in your *Group/Enterprise* directory, you can call them directly from the *Chat* window.

To place a call from the *Chat* window:

Click the **Call** button  at the top-right of the *Chat* window.

The Call Center client issues a Click-To-Dial attempt to the contact's phone number and the call appears in the *Call Console*.

ESTABLISH MULTIUSER CHAT SESSION

You can invite other contacts to your chat, thus converting your one-on-one chat to a multiuser chat. An incoming multiuser chat invitation opens a window for a new multiuser chat.

To add users to a chat session:

1. Click the **Add User to Chat** button  in the *Chat* window. A drop-down list of available contacts appears.




Figure 96 Add Participants to a Chat

2. Select the check box next to each contact to invite and click the **Invite** button. When a contact joins the chat, a notification appears in the *Chat Logs* area of the *Chat* window. The participants (other than you) are also listed at the top of the window.




Figure 97 Multiuser Chat

3. To leave the multiuser chat, close the *Chat* window.

MANAGE INSTANT MESSAGING SESSIONS

If a *Chat* window is not in focus and an incoming message is available for you to read, the color of the window is light brown as shown in the following figure. This changes to black as soon as the window is in focus.




Figure 98 Managing Chat Sessions

You can also close, minimize, or pop out a *Chat* window, that is, take the *Chat* window out of the Call Center main interface and place it elsewhere on the desktop.

To pop out a *Chat* window:

Click the **Pop-out** button  at the top-right of the window.

The window is placed on the desktop outside of Call Center and the Pop-out button becomes the Pop-in button.

To place the window back within the Call Center main interface:

Click the **Pop-in** button  at the top-right of the window.

To minimize or close a *Chat* window:

Click the **Minimize** or **Close** button at the top-right of the window. When a window is closed, the windows to the left (if present) shift to the right. This applies only to *Chat* windows that are placed within the Call Center main interface.

MONITOR SUPERVISORS (AGENT)

Call Center allows you to monitor the phone state of selected supervisors (up to 50). This is useful when you are escalating a call and want to find a supervisor who is available to take a call quickly.

You use the *Supervisors* panel to view the phone state of selected supervisors and to select supervisors to monitor. Supervisors who are not monitored have their state set to "Unknown".




Figure 99 Supervisors Panel



Note: This capability is designed to monitor the supervisor's state related to normal calls. Conference calls are handled differently, and it may happen that the state of a supervisor who was in a conference call is temporarily not reflected properly. For example, if the supervisor is in a conference and then all other parties hang up, the supervisor's status shows as *Idle* even though their phone may still be off-hook.

SELECT SUPERVISORS TO MONITOR

The list of selected supervisors is saved when signing out as part of your workspace and is restored on subsequent logins.

To select the supervisors to monitor:

1. In the *Supervisors* panel, click **Edit** . The *Supervisor Favorites* dialog box appears.




Figure 100 Supervisor Favorites Dialog Box

2. Check the box next to each supervisor to monitor and click **Save**.

SUPERVISOR PHONE STATES

The following table lists the possible states for a supervisor's phone line:

PHONE STATE	ICON	DESCRIPTION
<i>Idle</i>		Supervisor's phone is on-hook, which means the supervisor is not on a call.
<i>Busy</i>		Supervisor's phone is off-hook, which means that the supervisor is on a call.
<i>Ringing</i>		Supervisor's phone is in alerting state; a call is currently being delivered to the supervisor.
<i>Do Not Disturb</i>		Supervisor has enabled the Do Not Disturb service.
<i>Private</i>		Supervisor has enabled phone state privacy. NOTE: This terminates monitoring of the supervisor's phone state for the current login session. To be able to monitor their phone state again, you must sign out and then sign in after the supervisor has disabled their phone state privacy.
<i>Call Forwarding Always</i>		Supervisor has enabled the Call Forwarding Always service.
<i>Unknown</i>		Supervisor is currently not monitored.

MONITOR CALL CENTERS (AGENT)

Call Center provides you with real-time information about monitored queues. This information is displayed in the *Dashboard* pane.

DASHBOARD PANE

The *Dashboard* pane lists the monitored call centers and provides key indicators for each. For information about selecting call centers to monitor, see section [Select Call Centers to Monitor](#).

Some fields are color-coded to provide visual indicators of threshold severity. Threshold values are configured by your administrator. The visual Indicators of threshold severity are as follows:

SEVERITY	COLOR
0 (no threshold crossed)	No color
1 (yellow threshold crossed)	Yellow
2 (red threshold crossed)	Red

Dashboard			
Account			
Current Calls in Queue	8/10	Longest Waiting Call	05:10
EWT	01:55	AHT	01:45
ASA	00:16	Staffed	3/9
Technical			
Current Calls in Queue	2/20	Longest Waiting Call	00:00
EWT	04:30	AHT	04:30
ASA	00:15	Staffed	1/5
CustomerSupport			
Current Calls in Queue	16/500	Longest Waiting Call	01:10
EWT	00:40	AHT	00:20
ASA	00:15	Staffed	25/100
Finance			
Current Calls in Queue	10/50	Longest Waiting Call	02:35
EWT	00:06	AHT	02:00
ASA	00:06	Staffed	10/20
Sales			
Current Calls in Queue	0/10	Longest Waiting Call	00:00
EWT	00:00	AHT	00:00
ASA	00:00	Staffed	1/1

Figure 101 Dashboard Pane (Agents)

The following information is provided for each monitored call center:

- *Call center name* – The name of the call center.
- *Service Mode* (Premium call centers) – The mode in which the call center currently operates. This field can have one of the following values:
 - Night Service – The call center is processing calls according to the Night Service schedule and policy.
 - Night Service Override – The call center has been manually forced to follow the Night Service policy.



Note: The *Night Service* or *Night Service Override* status appears only if the Night Service policy is triggered, either by the *Night Service* schedule or by a manual override, and if the action to apply to incoming calls is set either to “Perform busy treatment” or “Transfer to phone number/SIP-URI”. Setting the action to “None” acts as if the Night Service policy was not triggered and the *Night Service/Night Service Override* status is not displayed in Call Center.

- Holiday Service – The call center is processing calls according to the Holiday Service schedule and policy.



Note: The *Holiday Service* status appears only if the *Holiday Service* policy is triggered and if the action to apply to incoming calls is set by a Clearspan administrator to either “Perform busy treatment” or “Transfer to phone number/SIP-URI”. Setting the action to “None” acts as if the *Holiday Service* policy was not triggered and the *Holiday Service* status is not displayed in Call Center.

- Forced Forwarding – All calls to this call center are forwarded to a specified destination.
- None – Call center is in normal mode of operation; none of the above modes are enabled.



Note: When the call center is in Normal service mode, the *Service Mode* field displays “None”.

- *Current Calls in Queue* – This is the number of queued calls expressed as a ratio of the total queue capacity for that call center. For example, “6/10” means that there are six calls in the queue, which can queue a maximum of ten calls.
- *Longest Waiting Call* – This is the waiting time of the call that has been in the queue the longest.
- *EWT (Expected Waiting Time)* – This is the estimated time a caller has to wait in this queue before their call is answered.
- *AHT (Average Handle Time)* – This is the average time it takes to process a call in this queue.
- *ASA (Average Speed of Answer)* – This is the average time a caller spends in the queue before the call is offered to an agent.
- *Staffed* – This is the number of agents that are in *Sign-In*, *Available*, *Unavailable*, or *Wrap-Up* ACD state, as a ratio of all agents assigned to this call center.

The fields that provide visual indicators are *Current Calls in Queue*, *Longest Waiting Call*, *EWT*, *AHT*, and *ASA*.

SELECT CALL CENTERS TO MONITOR

You can select up to 50 call centers to monitor in the *Dashboard* pane. You can only monitor call centers to which you have been assigned.

To select call centers to monitor:

1. In the *Dashboard* pane, click **Options**  and select the *Select Queues* option. The *Select Queues* dialog box appears.




Figure 102 Select Queues Dialog Box

2. Check the call centers you want to monitor and click **Save**.

SELECT INFORMATION TO DISPLAY

You can select which performance indicators you want to display in the *Dashboard* pane.

To select information to display:

1. In the *Dashboard* pane, click **Options**  and select the *Select Visible Fields* option. The *Select Fields* dialog box appears.




Figure 103 Select Fields Dialog Box

2. To display all performance indicators, check *Select All*. Or to show or hide some fields, check to uncheck the corresponding check boxes.
3. Click **Save**.

ORDER CALL CENTERS

By default, call centers displayed in the *Dashboard* pane are ordered by name. You can change the order in which call centers are displayed.

To change the order of call centers:

1. In the *Dashboard* pane, click **Options** 
2. Select *Sort By* and then select the ordering options you want.




Figure 104 Dashboard – Options – Sort By

MANAGE AGENTS (SUPERVISOR)

You use the *Agents* panel to view the agents who you are supervising and to perform actions on them. You can also monitor the call and the ACD state of selected agents and make agents join or leave queues. For information on selecting agents to monitor, see section [Select Agents to Monitor](#).



Figure 105 Agents Panel

SELECT AGENTS TO MONITOR

Call Center allows you to monitor the call and the ACD state of selected agents, but agents are not automatically monitored. To monitor the state of an agent, you must select the agent.

To select agents to monitor:

1. In the Agents panel, click **Edit** . The *Edit Monitored Agents* dialog box appears.




Figure 106 Edit Monitored Agents Dialog Box

2. Select the check box next to each agent to monitor. If an agent is staffing multiple call centers, by selecting that agent for monitoring in one call center, you are also selecting them for monitoring under all call centers that they are staffing.
3. Click **Save**.

The selected agents have their call and ACD state displayed. The state of agents who are not monitored appears as unknown (dimmed).



Figure 107 Agents Panel – Monitored Agents

The list is saved and is available during subsequent sessions.

MAKE AGENTS JOIN QUEUES

Call Center allows you to force an agent's join status in queues, effectively making the agent join or leave queues.




Figure 108 Agents Panel – Contact with Queue Button

To make an agent join or leave one or more queues:

1. In the *Agents* panel, click the target agent. The entry expands displaying available action buttons.
2. Click the Queue button. The *Agent Queue Membership* dialog box appears listing the call centers to which the agent is assigned.




Figure 109 Agent Queue Membership Dialog Box

3. To make the agent join a queue, check the Joined box in the row of the queue you want the agent to join.
4. To make the agent leave a queue, uncheck the Joined box in the row of the queue you want the agent to leave.
5. Click **Save**.

AGENT PHONE AND ACD STATES

Monitored agents have their phone and ACD state displayed. A single icon, to the left of the agent's name, represents the agent's combined phone and ACD state, which indicates the agent's ability to take calls. In addition, the agent's ACD state is also displayed in text following their name. If the agent's ACD state is set to "Unavailable", the unavailable code is also displayed (if applicable).

Other agents have their state set to "Unknown".



Figure 110 Agents Panel – Agents with Phone and ACD State Displayed

The possible agent's phone and ACD states are as follows:

PHONE STATE	ACD STATE	ICON	DESCRIPTION
<i>Idle</i>	<i>Available</i>		Agent's phone is on-hook and the agent is available to take ACD calls.
<i>Ringing</i>	<i>Available</i>		Agent's phone is ringing and the agent is available to take the call.
<i>Any</i>	<i>Unavailable, Sign-In, Sign-Out</i>		Agent is not available to take ACD calls.
<i>Idle, Ringing</i>	<i>Wrap-Up</i>		Agent is performing post call work. They may or may not be available to take calls.
<i>Busy</i>	<i>Available, Wrap-Up</i>		Agent's phone is off-hook, which means that the agent is on a call. Calls may be delivered to agents depending on their call waiting settings and the call center's call waiting and wrap-up settings.
<i>Do Not Disturb</i>	<i>Any</i>		Agent has enabled the Do Not Disturb service. ACD calls are not delivered to agent in the Do Not Disturb call state. This state is not recommended for Call Center agents. Agents should use the Unavailable ACD state when they need

PHONE STATE	ACD STATE	ICON	DESCRIPTION
			to block new incoming calls temporarily.
<i>Call Forwarding Always</i>	Any		Agent has enabled the Call Forwarding Always service.
<i>Private</i>	Any		Agent has enabled phone state privacy. NOTE: This terminates monitoring of the agent's phone state for the current login session. To be able to monitor their phone state again, you must sign out and then sign in after the agent has disabled their phone state privacy.
<i>Unknown</i>	Any		Agent is currently not monitored.

VIEW AGENT'S DETAILS

Clicking an agent expands the entry to show all queues the agent is assigned to and all the agent's current calls, in order of arrival.

For each call, the following information is displayed:

- Call number
- Calling name (if available) and calling number (and for direct calls, extension), for example, "Joe Smith +12403645125"
- Call length in the following format: "MM:SS" (or "HH:MM:SS" if the call lasts longer than an hour), for example, "10:22"

For each queue, the following information is displayed:

- Call Center ID
- Whether the agent has joined the queue
- The agent's skill level in that queue, if applicable



Figure 111 Agents Panel Entry Expanded

CHANGE AGENT ACD STATE

You can force an ACD state change for an agent. This action can only be performed on monitored agents.

To change an agent's ACD state:

1. In the *Agents* panel, click the agent and then click the **ACD State** button .




Figure 112 Agents Panel – Agent ACD States

2. From the drop-down list, select the new state.
3. If you selected Unavailable, you may have to select the reason for their unavailability.

SILENTLY MONITOR AGENT'S CALL

Call Center allows you to listen to monitored agents' calls without being heard. You can listen in on agents who you selected for phone and ACD state monitoring.



Note: This function is available if you have the Directed Call Pickup with Barge-in and Call Center Monitoring services assigned.

You can silently monitor one agent at a time, and the agent you monitor must have the Call Center – Premium service assigned.

You can choose to monitor the agent's current call or next incoming call. To monitor the current call, the agent must have exactly one active call.

To listen in on an agent's current call silently:

1. In the *Contacts* pane, expand the *Agents* panel and click the agent to monitor. The agent must have exactly one active call.

2. Click **Monitor**  for that agent.

A new call is created in the *Conference Call* panel. You are conferenced in to the call and muted (Silent Monitoring).

To listen in on an agent's next call silently:

1. In the *Contacts* pane, expand the *Agents* panel.
2. Click the target agent and click **Monitor Next Call**  for that agent. A monitoring call is established for the selected agent.

When the next call is received and answered by the agent, you are conferenced in to the call and your call is muted. Both calls appear in the *Conference Call* panel.




Figure 113 Silently Monitored Call

To barge in on a call you are silently monitoring:

In the *Conference Call* panel, click **Barge In** . You are conferenced in to the call.

For information on operations that can be performed on conference calls, see section [Manage Conference Calls](#).

BARGE IN ON AGENT'S CALL

Supervisor Barge-In allows you to barge in on an agent's call. This is useful when you want to enter an already established call between two other people. You can only barge in on agents who you selected for phone and ACD state monitoring.



Note: This functionality is only available if you have been assigned the Directed Call Pickup with Barge-in service.

To barge in on an agent's call:

1. In the *Contacts* pane, expand the Agents panel and select an agent. The agent must have exactly one active call.
2. Click the agent to expand the entry and click **Barge In** . A Three-Way Conference is established.

For information on operations that can be performed on conference calls, see section [Manage Conference Calls](#).

PICK UP AGENT'S RINGING CALL

Call Pickup allows you to pick up an unanswered call on behalf of an agent. This is useful when the agent is away or busy.



Notes: This functionality is only available if your group has been assigned the Call Pickup service.

A call that is retrieved using Call Pickup is treated in the Call Center reports as a direct inbound call to the retrieving party and not as an ACD call, because it was not answered by the agent selected using the ACD process.

Supervisor Call Pickup is only supported if the agent and supervisor are in the same group. In an enterprise, this function can be disabled.

To pick up an unanswered call for an agent:

1. In the Agents panel, select an agent whose phone is ringing.
2. Move the mouse over the agent and click **Answer** .

You are now answering the call, and the call appears in the *Call Console*.

MANAGE QUEUED CALLS (SUPERVISOR)

Call Center allows you to manage queued calls in the selected call centers (up to five) and to monitor calls in real time. You use the *Queued Calls* pane to manage queued calls under your supervision.

Section [Queued Calls Pane](#) describes the *Queued Calls* pane. The rest of this section describes the operations you perform to manage queued calls:

- [Select Call Centers to Monitor](#)
- [Show or Hide Call Center Panels](#)
- [View Queued Calls](#)
- [Group Queued Calls](#)
- [Order Queued Calls](#)
- [Monitor Next Call](#)
- [Enable Night Service Override or Forced Forwarding \(Premium Call Center\)](#)
- [Retrieve Call from Queue](#)
- [Promote Call in Queue \(Premium Call Center\)](#)
- [Transfer Call to Another Queue](#)
- [Transfer Call to Top of Queue \(Premium Call Center\)](#)
- [Transfer Call from Queue to Agent](#)
- [Transfer Call to Ad Hoc Number](#)
- [Change Position of Call in Queue](#)

QUEUED CALLS PANE

You use the *Queued Calls* pane to manage queued calls.

The *Queued Calls* pane displays the monitored call centers and lists the calls queued in each call center.

You can monitor up to five call center queues at a time, plus one special queue, called the Quick Link Queue, which does not count toward the maximum of the five-queue limit. The monitoring of a Quick Link Queue is triggered from the *Dashboard*.

For information about selecting call centers to monitor, see section [Select Call Centers to Monitor](#).

Each call center is displayed in a separate panel. The panel's header provides the following information and controls:

- Call center name – The name of the call center.
- Call center number – The primary phone number of the call center.



Figure 114 Queued Calls Pane

- Service Mode button  – This identifies the service mode of the supervised call center. Clicking the button launches the *Edit Queued Calls Favorites* dialog box and allows you to activate Night Service Override or Forced Forwarding. The call center can be in one of the following service modes:

- Night Service  – The call center is processing calls according to the Night Service schedule and policy.
- Night Service Override  – The call center has been manually forced to follow the Night Service policy.



Note: The *Night Service* or *Night Service Override* mode appears only if the Night Service policy is triggered. It is triggered either by the *Night Service* schedule or by a manual override, and if the action to apply to incoming calls is set by a Clearspan administrator to either *Perform busy treatment* or *Transfer to phone number/SIP-URI*. Setting the action to “None” acts as if the Night Service policy was not triggered, and as a result, the *Night Service/Night Service Override* mode is not displayed.

- Holiday Service  – The call center is processing calls according to the Holiday Service schedule and policy.



Note: The *Holiday Service* mode appears only if the Holiday Service policy is triggered and if the action to apply to incoming calls is set by a Clearspan administrator to either *Perform busy treatment* or *Transfer to phone number/SIP-URI*. Setting the action to “None” acts as if the Holiday Service policy was not triggered, and as a result, the *Holiday Service* mode is not displayed.

- Forced Forwarding  – All calls to this call center are forwarded to a specified destination.

- Normal  – Call center is in normal mode of operation; none of the above modes is enabled.

When you expand the panel for a call center, the list of calls queued in that call center appears.

- Message Waiting icon  – This icon is displayed if there is one or more outstanding voice messages left in the call center's voice mailbox. This icon performs the role of a message waiting indicator for the call center.
- Ratio of visible calls to display limit – This is the number of calls in the queue that are currently displayed against the maximum number of calls that can be displayed for a queue.
- Ratio of queued calls to queue length – This is the number of calls in queue against the queue length that is displayed.

By default, calls are listed according to their position in the queue, with the oldest call first. They can be grouped by the priority bucket. For more information, see section [Group Queued Calls](#).

The following information is provided for each call:

- Call Status icon – A graphic representation of the state of the queued call:
 - Waiting  – The call is queued, waiting to be answered.
 - Announcement  – An entrance announcement or music is being played to the caller.
 - Reordered  – The position of the call in the queue has been changed.
 - Bounced  – The call has been bounced.
- Caller's identity – The name (if available) and the phone number of the calling party.
- Call time – The total call time, including the time in the current queue (in parentheses).

Clicking a call expands the call to show additional data:

- Priority (**Premium call center**) – The priority bucket of the call.
- Position – The position of the call in the queue.
- Destination – The name (if available) and the phone number of the call center (or DNIS, when applicable) that was called.

When the call is expanded, the action buttons for actions that can be performed on the call appear. For the list of action buttons available in Call Center, see section [Call Action Buttons](#).

SELECT CALL CENTERS TO MONITOR

You can select up to five call centers to monitor. You view the monitored call centers in the *Queued Calls* pane.

To select call centers to monitor:

1. In the *Queued Calls* pane, click **Options**  and select the *Edit Queue Favorite* Dialog option.




Figure 115 Queued Calls – Options – Edit Queue Favorite Dialogue

The *Edit Queue Favorites* dialog box appears.




Figure 116 Edit Queue Favorites Dialog Box

2. Select the *Monitor* check boxes in the rows of the call centers to monitor. Note that the Quick Link Queue can only be selected for monitoring from the *Dashboard*.

If you select a queue that you are currently monitoring as the Quick Link Queue, the queue stops being monitored as the Quick Link Queue when you save your changes and it is monitored as a regular queue.

3. Click **Save**.



Note: Clicking the Close button  in a call center panel in the *Queued Calls* pane, closes the panel but does not stop monitoring the call center.

To stop monitoring a call center, deselect the *Monitor* check box for the call center in the *Edit Queue Favorites* dialog box.

For information about showing or hiding a call center in the *Queued Calls* pane, see section [Show or Hide Call Center Panels](#).

MODIFY NUMBER OF CALLS TO DISPLAY

For each Standard call center that you are monitoring, you can modify the maximum number of calls to be displayed and for each Premium call center you can modify the maximum number of calls that can be displayed in each priority bucket. The total number of calls to display for a call center cannot exceed 50.

1. In the Queued Calls pane, click **Options**  and select the *Edit Queue Favorite Dialog* option. The Edit Queue Favorites dialog box appears.
2. For each Standard call center you are monitoring, set the total number of calls to display.
3. For each Premium call center you are monitoring, set the number of calls to display in each priority bucket. The total number of call in all priority buckets cannot exceed 50.

SHOW OR HIDE CALL CENTER PANELS

You can show or hide call center panels for monitored queues. This is not the same as selecting queues to be monitored. For more information, see section [Select Call Centers to Monitor](#).

To show/hide call center panels:

1. In the Queued Calls pane, click **Options** .
2. Select *View* and then select or unselect the names of the call centers. To show or hide all call centers, select or deselect *All*.




Figure 117 Queued Calls – Options – View

Alternatively to hide a call center, click the **Close** button . The call center is removed from the display but continues to be monitored.



Note: This does not apply to the Quick Link Queue. When you click the Close button for the Quick Link Queue, the queue is no longer monitored.

VIEW QUEUED CALLS

You can selectively expand or collapse call center panels to show or hide calls in the monitored call centers.

To view queued calls for a call center:

Click the *Expand*  button for that call center.

To view call details of a selected call:

Click that call.

GROUP QUEUED CALLS

You can group queued calls by their priority bucket.

To group or ungroup queued calls:

1. In the *Queued Calls* pane, click **Options** .
2. From the drop-down list, select *Group*, and then select or deselect *Group by Priority*. This action applies to all monitored call centers.



Figure 118 Queued Calls – Options – Group

3. To ungroup calls, unselect the *Group by Priority* option.

ORDER QUEUED CALLS

Queued calls can be ordered according to their total waiting time or their waiting time in the current priority bucket.

To order queued calls:

1. In the *Queued Calls* pane, click **Options** .
2. Select *Sort* and then the ordering option you want. This operation applies to all monitored call centers.




Figure 119 Queued Calls – Options – Sort



Note: Ordering does not work with grouped calls. If required, first ungroup calls.

MONITOR NEXT CALL

You can silently monitor the next call that is received by a call center.



Note: To use this feature, you must have Call Center Monitoring service assigned.

To monitor the call center's next call:

1. In the *Contacts* pane, expand the *Queues* panel and click the target call center to expand it.
2. Click the Monitor **Next Call** button  for that call center. A monitoring call is established for the selected call center.

When the next call is received and answered by an agent, you are conferenced in to the call and your call is muted. Both calls appear in the *Conference Call* panel.

To barge in on a call you are silently monitoring:

In the *Conference Call* panel, click **Barge In** . You are conferenced in to the call.

For information on operations that can be performed on conference calls, see section [Manage Conference Calls](#).

ENABLE NIGHT SERVICE OVERRIDE OR FORCED FORWARDING (PREMIUM CALL CENTER)

Call Center allows you to manually override the current mode of operation and enable the Night Service and/or Forced Forwarding of calls for selected call centers.

To enable Night Service Override and/or Forced Forwarding:

1. In the *Queued Calls* pane, click the **Service Mode** button  in the panel for one of the call centers. The *Edit Queue Favorites* dialog box appears.




Figure 120 Edit Queue Favorites Dialog Box

2. For each call center for which you want to override the time schedule and manually initiate Night Service (including the Quick Link Queue if present), check the *Night Service Override* check box.
3. For each call center for which you want to divert calls to a specified destination temporarily (including the Quick Link Queue if present), check the *Force Forwarding* box and enter the phone number to which to forward the calls in the *Enter Number* box.



Note: Night Service Override has precedence over Forced Forwarding.

RETRIEVE CALL FROM QUEUE

You can retrieve queued calls from the queue to your phone device.

To retrieve a call from a queue:

Click the call in the *Queued Calls* pane and click **Retrieve**  for that call.

Once you retrieve a call, the call appears in the *Call Console* and you treat it as any other call. For example, you can transfer it to an ad hoc number or to another queue. For more information, see section [Manage Calls](#).

PROMOTE CALL IN QUEUE (PREMIUM CALL CENTER)

A priority is attached to an incoming call based on the DNIS number on which it is received. Calls are distributed to the agents staffing the queue based on this priority, with calls of the higher priority being exhausted before calls in the next priority are distributed.

You can manually promote calls from a lower priority bucket to a higher priority bucket. A manually promoted call ends up as the last call in the higher priority bucket with a wait time of zero seconds.

To promote a call, that is to change its priority:

1. In the *Queued Calls* pane, expand a *Call Center* panel.
2. Click the call you want to promote and click **Promote**  for that call.

The queued call is promoted to the end of the next highest priority bucket.

TRANSFER CALL TO ANOTHER QUEUE

To transfer a queued call to another queue:

1. In the *Queued Calls* pane, select the call to transfer.
2. In the *Contacts* pane, expand the *Queues* panel.
3. Click the target queue and click **Transfer**  for that queue.

The call is transferred and removed from the queue.

TRANSFER CALL FROM QUEUE TO AGENT

To transfer a call from a queue to an agent:

1. In the *Queued Calls* pane, select the call to transfer.
2. In the *Contacts* pane, expand the *Agents* panel.
3. Click the target agent and click **Transfer**  for that agent.

Alternatively, if available, click the right **Transfer** button  and click the number.

The call is transferred and removed from the queue.

TRANSFER CALL TO AD HOC NUMBER

To transfer a call to an ad hoc number:

1. In the *Queued Calls* pane, select the queued call.
2. In the *Dialer*, enter the destination number and click **Transfer** .



Figure 121 Ad Hoc Queue Transfer

The call is transferred and removed from the queue.

CHANGE POSITION OF CALL IN QUEUE

You can reorder a queued call in a Standard call center or in the “0” priority bucket in a Premium call center.

To change a call's position in a queue:

1. In the *Queued Calls* pane, click the target call to expand it.




Figure 122 Reordering Queued Call

2. Click **Reorder**  and select the new position in the queue from the list that appears.

The call is placed in the new position.



Notes: You cannot place a call ahead of a bounced call.

The list can contain a maximum of 24 reorder positions, which you can choose from to reorder a call in queue, in addition to *Send to Back* and *Sent to Front* options.

TRANSFER CALL TO TOP OF QUEUE (PREMIUM CALL CENTER)

If your administrator has configured the call center with the Transfer to Top feature, follow this procedure to transfer the call to the top of the queue.

You can only transfer a call to the top of the highest priority bucket (bucket with priority "0").

There need to be at least two calls in the target queue.

1. In the *Queued Calls* pane, click the target call to expand it.
2. Click **Reorder**  and select *Send to Front* from the list that appears.



Figure 123 Transferring Call to Top of Queue

To view agents staffing a call center:

Check the *Show Agents* check box in the row for that call center.

Some fields are color-coded to provide visual indicators of threshold severity. Threshold values are configured by your administrator.

SEVERITY	COLOR
0 (no threshold crossed)	No color
1 (yellow threshold crossed)	Yellow
2 (red threshold crossed)	Red

QUEUE INFORMATION

The *Dashboard* displays each call center queue on a separate line and provides the following information about each queue:

- *Name* – This is the name of the call center.
- *Status (Premium call centers)* – This identifies the service mode in which the call center currently operates, which can be one of the following:
 - Night Service – The call center is processing calls according to the Night Service schedule and policy.
 - Night Service Override – The call center has been manually forced to follow the Night Service policy.



Note: The *Night Service* or *Night Service Override* status appears only if the Night Service policy is triggered, either by the *Night Service* schedule or by a manual override, and if the action to apply to incoming calls is set either to “Perform busy treatment” or “Transfer to phone number/SIP-URI”. Setting the action to “None” acts as if the Night Service policy was not triggered and the *Night Service/Night Service Override* status is not displayed in Call Center.

- Holiday Service – The call center is processing calls according to the Holiday Service schedule and policy.



Note: The *Holiday Service* status appears only if the *Holiday Service* policy is triggered and if the action to apply to incoming calls is set by a Clearspan administrator to either “Perform busy treatment” or “Transfer to phone number/SIP-URI”. Setting the action to “None” acts as if the *Holiday Service* policy was not triggered and the *Holiday Service* status is not displayed in Call Center.

- Forced Forwarding – All calls to this call center are forwarded to a specified destination.
- Normal – Call center is in normal mode of operation; none of the above modes is enabled.



Note: When the call center is in Normal service mode, the *Status* field is empty.

- *Calls in Queue* –This is the number of queued calls expressed as a ratio of the total queue capacity for that call center. For example, “6/10” means that there are six calls in the queue, which can queue a maximum of ten calls.
- *Long Waiting Call* –This is the waiting time of the call that has been in the queue the longest.
- *EWT (Expected Waiting Time)* –This is the expected waiting time of calls in the queue.
- *AHT (Average Handle Time)* –This is the average handling time for calls in the queue.
- *ASA (Average Speed of Answer)* –This is the average amount of time a caller spends in the queue before the call is offered to an agent.
- *Staffed (Agents)* –This is the number of agents managed by you that are in *Sign-In*, *Available*, *Unavailable*, or *Wrap-Up* ACD state, as a ratio of all agents managed by you for this call center.
- *Idle (Agents)* –This is the number of agents who are in the *Available* ACD state but presently not on a call.
- *Unavailable* –This is the number of agents who are signed in to the call center but not available to take calls.
- *Show Agents* –When this check box is selected, the agents who are joined in the call center are displayed in the *Agents* area of the *Dashboard*.

The fields that provide visual indicators are *Calls in Queue*, *Longest Waiting Time*, *EWT*, *AHT*, and *ASA*.

AGENT INFORMATION

The *Dashboard* displays information about the agents for the selected queues.

To display agent information:

1. To select the queues for which you want to view agents' information, check the *Show Agents* box on the lines for the queues in the *Queues* area of the *Dashboard*.
2. To hide signed-out agents, check the *Hide Signed Out Agents* box at the top-right corner of the *Dashboard*.



Figure 125 Dashboard – Hide Signed Out Agents Box

The following information is provided for each displayed agent:

- *Status* – This is the agent's combined phone and ACD state. For more information, see section Agent Phone and ACD States.

Note that the Status column is only sorted by the ACD state and it ignores the phone state.

- *Name* –This is the agent's name.
- *Queues (total)* – This is the total number of queues to which the agent is assigned. This number is a link, which when clicked, opens a dialog box that lists the agent's queues.
- *Sign-In Time* – This is the agent's most recent sign-in time.
- *Sign-In Duration* –This is the amount of time that the agent has been signed in.
- *Call State (Time)* –This is the call state and time on the current call. The call state can be Idle, Ringing, or On a call. If an agent is in multiple calls, the call time reflects the time of the longest running call. When a call is released, then the call time reflects the time on the remaining calls.



Note: When the Dashboard is launched, the *Call State Time* for an idle agent is blank and stays blank until the agent's call state changes. The next time the agent becomes idle (after receiving a call and hanging up), the idle time is reset to "0.00" and the Dashboard displays the actual time the agent has been idle.

- *Agent State (Time)* –This is the agent ACD state and time. If an agent is unavailable, the unavailable code is shown.
- *% Available* –This is the time that the agent was available to take calls shown as a percentage of the duration of the current sign-in.
- *Avg Busy In* –This is the average time spent by the agent on an incoming ACD call.
- *Avg Busy Out* –This is the average time spent by the agent on an outgoing ACD call.
- *Avg Wrap-Up* –This is the average time spent by the agent in a post call wrap-up.

Fields that provide visual indicators are Call State (Time), On Call, Idle, Agent State (Time), Unavailable, Avg Busy In, Avg Busy Out, and Avg Wrap-Up.

The *Dashboard* is designed to be used together with the *Queued Calls* pane and the *Agents* panel in the *Contacts* pane. The *Dashboard* provides you with a real-time view of agents and queues, while the *Agents* panel and *Queued Calls* pane allow you to take actions on monitored agents and ACD calls. For more information about the actions you can take to manage agents and queued calls, see sections [Manage Agents \(Supervisor\)](#) and [Manage Queued Calls \(Supervisor\)](#).

SELECT INFORMATION TO DISPLAY

By default, Call Center displays information about call centers and agents as described in sections [Queue Information](#) and [Agent Information](#). You may however modify what information you want to appear in the *Dashboard*.

To select information to display:

1. Right-click the first row in the queued calls or agents table.
2. From the menu that appears, select *Columns*.
3. From the list of available columns, uncheck the columns you want to hide and check the columns you want visible.




Figure 126 Dashboard – Select Columns to Display

4. When you are done, click anywhere in the *Dashboard* outside the menu.

NAVIGATE TO AGENT IN AGENT DIRECTORY OR QUEUE IN QUEUED CALLS PANE

Call Center allows you to navigate to a call center queue in the *Queued Calls* pane or to an agent in the *Agents* directory directly from the *Dashboard*.



Note: Google Chrome does not support this operation and Mozilla Firefox requires specific setting for the operation to work. For more information, see section *Quick Link Navigation in Chrome and Firefox*.

If the selected queue is currently not monitored, the application starts monitoring the queue as a special queue, called Quick Link Queue, which does not count toward the maximum of five queues that can be monitored. You can perform normal call operations on calls in the Quick Link Queue.

- When you close the Quick Link Queue, Call Center stops monitoring the queue and the queue is removed from the *Queue* pane.
- When you click a non-monitored queue while there is already a queue monitored as Quick Link Queue, the new queue replaces the old queue as the Quick Link Queue and Call Center stops monitoring the old queue.

The screenshot shows the Clearspan Call Center Dashboard. It features two main sections: 'Queues' and 'Agents'. The 'Queues' section has columns for Name, Status, Calls In Queue, Longest Waiting, EWT, AHT, ASA, Staffed, Idle, Unavailable, and Show Agents. The 'Agents' section has columns for Name, Status, Queues(Total), Sign-in Time, Sign-in Duration, Call State (Time), Agent State (Time), % Available, Avg Busy In, Avg Busy Out, and Avg Wrap-Up.

Queues										
Name	Status	Calls In Queue	Longest Waiting	EWT	AHT	ASA	Staffed	Idle	Unavailable	Show Agents
Billing Support		0/10	00:00	00:00	00:00	00:00	0/1	0	0	
Customer Contact		0/100	11:40	00:00	00:00	00:00	0/1	0	0	
Finance Support		0/10	00:00	00:00	01:16	00:00	0/1	0	0	
Premium Customer		0/25	00:00	00:00	00:00	00:00	3/12	1	1	☒
Technical Support		0/0	00:00	00:00	00:00	00:00	0/1	0	0	

Agents									
Name	Queues(Total)	Sign-in Time	Sign-in Duration	Call State (Time)	Agent State (Time)	% Available	Avg Busy In	Avg Busy Out	Avg Wrap-Up
Brian Jim	1	12:29:26	05:36:05	Ring (12:18)	Unavailable (05:36:05)	0%	00:00	00:00	00:00
Norma Jim	1	12:40:53	05:24:38	On Call (07:23)	Wrap-Up (56:03)	83%	00:00	00:00	00:00
Greenberg Robert	6	17:08:03	57:28	Idle	Available (57:28)	100%	00:00	00:00	00:00
Rev. Louis	-	-	-	-	-	-	-	-	-

Figure 127 Dashboard – Navigate to Queue or Agent

1. To navigate from the *Dashboard* to a call center queue in the *Queued Calls* pane, click the name of the queue. The main window is brought to the foreground and the selected queue is displayed with an expanded listing of calls in the queue. All other queues are collapsed.

QUEUED CALLS			
▲ Billing Support	0/10 (0/10)		
▲ Customer Contact	0/10 (0/100)		
▲ Finance Support	0/10 (0/10)		
▲ Technical Support	0/10 (0/0)		
▲ Vendor Support	0/10 (0/10)		
▼ Premium Customer	4/10 (4/25)		
Priority 0 (1)			
Veronica Jones (5555551602)	06:08	[06:08]	
Priority 1 (1)			
Mona McKinley (5555551603)	05:36	[05:25]	
Priority 2 (1)			
Louis Roy (5555551604)	04:44	[00:20]	
Priority 3 (1)			
Jim Brian (5555551605)	00:00	[00:00]	

Figure 128 Queued Calls Pane – Quick Link Queue

2. To navigate from the *Dashboard* to an agent in the *Agents* directory, make sure that the *Show Agents* check box (on the row for the queue the agent is staffing), is checked and then click the agent's name. The main window is brought to the foreground and the selected agent is displayed expanded in the *Agents* panel.

GENERATE REPORTS

Call Center provides reporting functions to agents and supervisors. Agents can only generate reports about their own activity whereas supervisors have access to reports on activity and performance of agents and call centers under their supervision.

If the administrator has configured the system to allow multiple *Report* windows to be open at the same time, supervisors can run up to five reports simultaneously. Independent of the configuration, an agent can only run one report at a time.

The Reporting feature allows you to run reports and schedule reports to run in the future using predefined templates. Reports can be of type *Agent* or *Call Center*.

The report templates available to you depend on how your administrator has configured your system.

You use the Reporting link at the top of the main interface to access pages used to generate and schedule reports.



Figure 129 Main Interface (Top of Window)

This section provides an example of a report. For the list of canned report templates available on Clearspan for report generation, see the *Clearspan Call Center Reports Guide*.

RUN REPORT

To run a report:

1. Click the Reporting link at the top right-hand side of the main window. A *Report* window appears.




Figure 130 Report Window

2. Select a report template from the drop-down list. The page displays the input parameters for the report.

Figure 131 Abandoned Call Report – Running Report

3. Fill in the required information. The input that you need to provide depends on the template you select and the report type. The following table explains the input parameters for all reports.

INPUT FIELD	DESCRIPTION	ALLOWED VALUE
<i>Scope</i>	For Agent Reports, it allows you to specify the agents to include in the report. You can check All Agents or Agents. If you check Agents, select agents from the drop-down list. NOTE: This parameter is disabled when an agent runs the report, since agents can only run reports about themselves.	All Agents, Agents
	For Call Center Reports, it specifies the call centers or DNIS numbers to include in the report. You can check All Call Centers, Call Center, or DNIS. - If you check Call Center, select call centers from the drop-down list. - If you select DNIS, select a call center and DNIS numbers from the drop-down lists. For DNIS you can also select ALL DNIS.	All Call Centers, Call Center, DNIS
<i>Call Completion</i>	This setting is used to count the number of ACD calls an agent has completed within a service level during the specified interval. The Call Completion service level can be set to "1" through "7200" seconds.	1 through 72000
<i>Short Duration</i>	This setting is used to count the number of ACD short duration calls completed by an agent during an interval. You can set the maximum length of a short duration call to "1" through "7200" seconds.	1 through 7200
<i>Service Level</i>	This setting allows you to provide up to five service levels, used to perform service-level calculations for each call center or DNIS. Each service level can be set to "1" through "7200" seconds.	1 through 7200
<i>Service Level Options</i>	These settings are used to determine whether certain types of calls should be included in the service-level calculations: - Check Include overflow time transfers in service level to include calls transferred due to time overflow. - Check Include other transfers in service level to include calls transferred for other reasons. - Select one of the following options for abandoned calls: - Exclude Abandoned Calls to exclude all abandoned calls - Include All Abandoned Calls to include all abandoned calls - Include All Abandoned Calls Except Before Entrance Completes to include calls abandoned after the entrance message has finished playing - Include Abandoned Calls Except in Defined	These options can be checked or unchecked.

INPUT FIELD	DESCRIPTION	ALLOWED VALUE
	Interval to include calls abandoned after the time specified by the abandoned call interval parameter.	
<i>Abandoned Call Interval</i>	If you selected the Include Abandoned Calls Except in Defined Interval option, enter the desired interval in this text box in seconds.	1 through 7200
<i>Service Level Percentage</i>	This setting allows you to specify the service-level objective (expressed as a percentage of calls).	
<i>Type</i>	This can be checked as Historical or Real time. - Historical reports show data from the assigned start date to the assigned end date. - Real-time reports show data from the assigned start date to the present, with the current interval refreshed with real-time data. Real-time reports for individual agents contain data for each time interval, with the last interval reflecting real-time data, if requested (subject to the refresh rate). When the interval switches over, the final data for the last time period is captured and shown as historical data and real-time data is reflected in the new time interval.	Historical or Real time
<i>Start Date</i>	This is the date when you want the report to start. It can be set by typing in the text box or clicking the Calendar icon. This is compulsory. The oldest historical date depends on the interval selected: 180 days of half-hour interval statistics 365 days of hourly interval statistics 730 days of daily interval statistics	MMM DD, YYYY
<i>Start Time</i>	This is the time when you want the report to start. You can select the hour format (A.M., P.M., or Military time) from the Hour Selection Type. Time is applicable for hourly and minute intervals only.	1:00am through 12:59am, 1:00pm through 12:59pm, or 0:00 through 23:59
<i>End Date</i>	This is the date when you want the report to end. It can be set by typing in the text box or clicking the Calendar icon. This is required when a Historical report is selected.	MMM DD, YYYY
<i>End Time</i>	This is the time when you want the report to end. You can select the hour format (A.M., P.M., or Military time) from the Hour Selection Type. Time is applicable for hourly and minute intervals only. This is required when a Historical report is selected.	1:00am through 12:59am, 1:00pm through 12:59pm, or 0:00 through 23:59
<i>Sampling</i>	This sampling period is only applicable to interval-based report templates and determines how the report information is presented. For example, an hourly report displays information for each hour of the report time frame.	15 minutes, 30 minutes, Hourly, Daily, Weekly, Monthly
<i>Output Format</i>	This allows you to specify in what format you would like the report output to be generated. If you select Hypertext Markup Language (HTML) or PDF, the report	PDF, XLS, HTML

INPUT FIELD	DESCRIPTION	ALLOWED VALUE
	in displayed in the Report window. If you select Excel File Format (XLS), a file is created that you can save on your computer.	

4. Click **Run Report**.

The results of the report are displayed in the *Report Output* area of the window. See the following section for an example of a report.

- If you are using Edge and selected the PDF output format, a dialog box appears asking you to download the report. Click **Download** to download the report.



Note: Adobe Reader 10.01 has a setting *Enable Protected Mode at startup*, which is enabled by default. If you select the PDF report format and are using Adobe Reader 10.01 (or later, which has this setting), you need to disable the setting; otherwise, report results are not displayed.

To disable the protected mode in Adobe Reader, perform the following steps.

1. Close all opened Internet Explorer and Adobe Reader instances.
2. Open Adobe Reader.
3. From the menu bar, select *Edit* and then *Preferences*. The *Preferences* dialog box appears.
4. From the *Categories* menu on the left, select *General*.




Figure 132 Preferences – General

5. Uncheck *Enable Protected Mode at startup*.
6. Click **OK**.
7. Close Adobe Reader.

Report Results (Example)

Depending on the report type, the report results can contain the following elements: A pie chart, a bar chart, a table, a high-water marks table, and a line chart.

If you select HTML or PDF report format when requesting a report, the report is displayed in the *Report* window. If you select XLS, a file is created that you can save on your computer.

This section provides an example of a report: Abandoned Calls Report. For more information on the reports available in Call Center, see the *Clearspan Call Center Reports Guide*.

The results of the Abandoned Calls Report are presented in a bar chart and table.




Figure 133 Abandoned Calls Report – Bar Chart

Abandoned Calls																	
Date and Time	Call Center Name	Calls Queued	Calls Abandoned	% Calls Abandoned	Calls Abandoned in 10 secs	% Calls Abandoned in 10 secs	Calls Abandoned in 20 secs	% Calls Abandoned in 20 secs	Calls Abandoned in 30 secs	% Calls Abandoned in 30 secs	Calls Abandoned in 40 secs	% Calls Abandoned in 40 secs	Calls Abandoned before Entrance Message Completes	% Calls Abandoned before Entrance Message Completes	Calls Abandoned after Entrance Message Completes	% Calls Abandoned after Entrance Message Completes	Longest Wait Abandoned
12/02/2010, 01:00 PM		0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
	Summary	0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
12/02/2010, 01:15 PM		0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
	Summary	2	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
12/02/2010, 01:30 PM		0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
	Summary	1	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
12/02/2010, 01:45 PM		0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
	Summary	1	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
	W7039_CallCenter/Premium	0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
	Summary	1	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
12/02/2010, 02:00 PM		0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
		0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
		1	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
	W7045_CallCenter/Premium	2	1	50.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	1	50.0%	0	0.0%	00:00:00
Summary		2	1	50.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	1	50.0%	00:01:15
12/02/2010, 02:15 PM		0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00
	Summary	0	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	0	0.0%	00:00:00

Figure 134 Abandoned Calls Report – Table (Fragment)

SCHEDULE REPORT

To schedule reports, your company (group or enterprise) must have Enhanced Reporting enabled. For more information, see your administrator.

To schedule a report:

1. Click the **Reporting** link at the top right-hand side of the main window. A *Report* window appears.





Figure 135 Report Window – Report List

2. Select a report template from the drop-down list. The page displays the input parameters for the report.

Figure 136 Scheduling Report (Abandoned Call Report)

3. For *Type*, select *Scheduled*.
4. Provide the name and the description of the report.
5. Specify the recurrence pattern of the report. From the *Recurs* drop-down list, select one of the following options: *Never*, *Daily*, *Weekly*, *Monthly*, or *Yearly*. *Never* signifies that this is a one-time report.

- If you selected Daily, enter the frequency of recurrence in days.




Recurrence Pattern:

Recurs : Daily

Every : 1 day(s)

Figure 137 Scheduled Report – Daily Recurrence Pattern

- If you selected Weekly, enter the frequency of occurrence in weeks and select the day of the week when you want the report to be generated.



Recurrence Pattern:

Recurs : Weekly


Every : 1 week(s) on:

☒ Sunday ☐ Monday ☐ Tuesday ☐ Wednesday

☐ Thursday ☐ Friday ☐ Saturday

Figure 138 Scheduled Report – Weekly Recurrence Pattern

- If you selected Monthly, enter the frequency of occurrence in months and specify the day when you want the report to be generated. Select one of the following options:
 - To schedule the report on a specific day of the month, for example, the twenty-seventh, check Day <X> of the month and enter the day.
 - To schedule the report on a specific day of the week within the month, for example the second Monday of the month, check The <X> <Day of week> of the month and select X and Day of week from the drop-down lists.



Recurrence Pattern:

Recurs : Monthly

Every : 1 month(s) on:

☒ Day 1 of the month

☐ The First Sunday of the month

Figure 139 Scheduled Report – Monthly Recurrence Pattern

- If you selected Yearly, specify the frequency of occurrence in years, for example every two years, and specify the day for the recurrence of the report. Select one of the following options:
 - To schedule the report on a specific day of the year, check Day <X> of <Month> and select the day and the month.
 - To schedule the report on a specific day of the week and month, for example, the first Sunday of January, check The <X> <Day of week> of <Month> and select X, Day of week, and Month from the drop-down lists.

Recurrence Pattern:

Recurs : Yearly

Every : 1 year(s) on: ☒ Day 1 of January

☐ The First Sunday of January

Figure 140 Scheduled Report – Yearly Recurrence Pattern

6. Specify when the report should run.
- For a non-recurrent report, specify the actual date and time to generate the report.

Report Time:

*Schedule Date : 07/30/2012

*Schedule Time : 12:00pm HH:MM [am|pm]

Figure 141 Report Time for a Non-recurrent Report

- For a recurrent report, specify when the report should be generated for the first time.

Report Time:

*Start Date : 07/30/2012

*Run Time : 12:00pm HH:MM [am|pm]

Figure 142 Report Time for a Recurrent Report



Note: The start date and run time (and for weekly reports the day of the week) determine when the report is generated for the first time. The subsequent times are determined by the recurrence pattern and range.

7. For a recurrent report, specify when the reporting should end. For *Recurrence Range*, select from the following options:
- Never
 - After <X> occurrences, and enter the number of occurrences
 - Date, and select a date from the calendar

Recurrence Range:

Start Date : 7/30/2012 Note: Start Date is always equal to Report Time Start Date value

End : ☒ Never

☐ After occurrences

☐ Date 

Figure 143 Scheduled Report – Recurrence Range

8. Specify the report time frame, that is, the period for which you are requesting the report.
 - For a non-recurrent report, enter the actual dates and times.

Timeframe :  : HH:MM [am/pm] :  : HH:MM [am/pm]

Sampling :

Output Format :

Figure 144 Report Timeframe for a Non-recurrent report

- For a recurrent report, select the time frame relative to the report generation time, for example, the previous month, previous five days, and so on.

Timeframe : Previous :

Sampling :

Output Format :


Figure 145 Report Timeframe for Recurrent Report



Note: A report time frame always has a beginning date and time and an end date and time. For a recurring report the relative time frame is converted to the actual dates and times at the moment when the report is run.

The actual time frame always starts at the top of the hour, day, week, month, or year and is based on the selected time zone and day of the week. For example, if a report is scheduled to run every day at 5:45 P.M. for the previous two hours, then the actual time frame of the report is from 3:00 P.M. to 5:00 P.M. of the day when the report is run.

9. Specify the sampling frequency. From the *Sampling* drop-down list, select a frequency.
10. Specify the output format of the report. From the *Output Format* drop-down list, select a format, for example, PDF.



The screenshot shows a configuration window with three rows of controls. The first row is labeled 'Timeframe : Previous :', followed by a text input containing '1' and a dropdown menu currently showing 'Day'. The second row is labeled 'Sampling :', followed by a dropdown menu currently showing 'Daily'. The third row is labeled 'Output Format :', followed by a dropdown menu currently showing 'PDF'. Each dropdown menu has a small downward-pointing arrow on its right side.

Figure 146 Report Sampling and Output Format

- 11.** Enter the e-mail addresses of the recipients of the report.
- 12.** Enter the remaining parameters, as required. For the description of the remaining parameters, see section Run Report.
- 13.** Click **Schedule Report**.

The report is scheduled. It is run at the specified times and sent to the recipients configured in the report schedule.

MANAGE SCHEDULED REPORTS

You can list, modify, and delete scheduled reports.

To manage scheduled reports:

- 1.** Click the Reporting link at the top right-hand side of the main window. A Report window appears.

2. From the drop-down list, select *Scheduled Reports*. A *Scheduled Reports* dialog box appears, listing the reports that you have scheduled.




Figure 147 Scheduled Reports Dialog Box

3. To edit a report, click the **Load** button  in the row for the report, and modify the report as required.
4. To delete a report, click the **Delete** button  in the row for the report.

CONFIGURE CALL CENTER

You use the *Settings* page, accessed via the Settings link at the top right-hand side of the main page to configure various aspects of the Call Center application.

To return to the main interface, click the **Back To Application** link.



Note: Do **not** use the internet browser's Back button to return to the main interface.

This section provides information about the options that you can use to configure Call Center.

-

- [Settings – General](#)
- [Settings – Application](#)
- [Settings – Services](#)
- [Settings – Plug-ins](#)
- [Settings – Messaging](#)
- [Settings – Report](#)
- [Settings – About](#)



Note: Depending on your system configuration, some settings may not be available.

SETTINGS – GENERAL

You use the General tab to configure miscellaneous settings that improve the usability of Call Center.

General	Application	Services	Plugins	Messaging	Report	About
---------	-------------	----------	---------	-----------	--------	-------

General

Account	Change Password...
Hotel Guest	Enter Host
Language	English (US) ☒ Synchronize language with service profile
Screen Pop	Enter URL ☐ Auto pop incoming calls
Date Format	☒ MM/DD/YYYY ☐ DD/MM/YYYY
Time Format	☒ AM/PM ☐ 24 Hour
Workspace	Save Workspace Load Workspace Restore Workspace ☐ Always save workspace on signout

Figure 148 Settings – General

The following subsections describe the settings that can be configured on this page.

ACCOUNT

You use this area to change your Clearspan password.

Call Center shares logon credentials with Clearspan. So when you change your password in Call Center, remember to use this new password when accessing your web portal.



Note: The password you enter must meet the password requirements set on Clearspan.

To change your password:

1. Click the **Change Password** link. The section expands, allowing you to change your password.

Change Password ...

Old Password :

New Password :

Confirm Password :

Figure 149 Account – Change Password

2. Enter your current and new password and click **Change Password**.

Note that the *Reset* button does not reset your password. It only clears the input boxes.

HOTEL/FLEXIBLE SEATING HOST

This setting allows you to configure the Hoteling Host or Flexible Seating Host, which is required when you use Call Center from a Hoteling desk/device. This way you do not need to enter this information every time you sign in to Call Center if you use the same Hoteling or Flexible Seating device.

In the text box, enter the user name of the Hoteling Host or Flexible Seating Host who corresponds to the desk/device you are using, for example, “station_224@acme.com”.

LANGUAGE

The language settings allow you select the language of the Call Center user interface.

- The drop-down list lists the languages available in your edition of Call Center. To change the language, select a new language from the list.
- *Synchronize language to my profile* – This box, when checked, synchronizes the Call Center language with your Clearspan profile and ignores the language selection on this page.

SCREEN POP

You use the screen pop settings to configure the URL that may be launched on incoming calls.

- *Enter URL* – This text box allows you to enter the URL address of the web page that Call Center opens using the default browser when you click the **Web Pop URL** button in the *Call Notification* pop-up window.
- *Auto pop for incoming calls* – When this option is checked, Call Center launches the Web Pop URL without your having to click the Web Pop URL button in the *Call Notification* pop-up window for each incoming call.

The URL can point to any URL address, but typically points to a web application that parses optional call parameters and passes them to a Customer Relationship Management (CRM) application or other database. For example:

`http://www.mysite.com/webapp.php?remoteNumber=__REMOTE_PHONE__&sp=__SERVICE_PROVIDER__`

This URL passes the incoming calling number and the service provider ID to the web application at www.mysite.com. The web application formats the data for the applicable database and launches the web page on your PC.

There are a number of optional parameters that the client can pass to the browser. The following list summarizes these parameters:

- `__USER__`: The user's Clearspan ID (Note that in this case the "user" is the Clearspan subscriber.)
- `__FIRST__`: The first name of the user
- `__LAST__`: The last name of the user
- `__EMAIL__`: The e-mail address of the user
- `__GROUP__`: The name of the Clearspan group to which the user belongs
- `__SERVICE_PROVIDER__`: The name of the Clearspan service provider to which the user belongs
- `__PHONE__`: The phone number of the user
- `__REMOTE_PHONE__`: The phone number of the remote party

- `__REMOTE_NAME__`: The name of the remote party (when available)
- `__CALL_TYPE__`: “Incoming”, “Outgoing”, or “Alerting”
- `__DNIS_NAME__`: The name of the DNIS on which the call was received
- `__DNIS_PHONE__`: The phone number of the DNIS on which the call was received
- `__CLIENT_SESSION_INFO__`: The identifier of the client session
- `__EXT_TRACKING_ID__`: The external ID used to track the call session
- `__REDIRECTED_NAME_1__`, `__REDIRECTED_NAME_2__`, and so on: The name of a party to whom the call was redirected prior to being delivered to you, from the most recent to the least recent
- `__REDIRECTED_PHONE_1__`, `__REDIRECTED_PHONE_1__`, and so on: The phone number of a party to whom the call was redirected prior to being delivered to you, from the most recent to the least recent
- `__REDIRECTED_USERID_1__`, `__REDIRECTED_USERID_1__`, and so on: The user ID of a party to whom the call was redirected prior to being delivered to you, from the most recent to the least recent



Note: The maximum number of redirections that can be displayed on a *Web Pop URL* page is configured by your administrator.

DATE FORMAT

This setting allows you to select the format for displaying dates in reports. The format is used for all dates that are included in generated reports. The selected date format is also used to display the dates in the Call History dialog box. The possible options are:

- MM/DD/YYYY
- DD/MM/YYYY

TIME FORMAT

This setting allows you to select the format for displaying time in reports. It is used for all times that are included in generated reports. The selected time format is also used to display the time in the chat logs and in the Call History dialog box. The possible options are:

- AM/PM
- 24 hours

Note that this setting does not impact the format in which event duration is reported in generated reports, which is always *DD:HH:MM:SS*.

WORKSPACE

Call Center allows you to customize elements of your workspace, such as the size and placement of windows on the desktop. The system remembers the setup between sessions.

The following elements can be customized:

- The size and position of the web browser window in which the main interface is displayed
- The size of the panes (Call Console, Contacts, and Queued Calls)
- The size and position of the Dashboard window
- The size and position of any Report window



Notes: This functionality does not work in Internet Explorer, due to a technical limitation of Internet Explorer. Moreover, Firefox 7 and later does not provide a standard application programming interface (API) to resize a window without opening a new window. Therefore, saving workspace settings for the main application window size does not work in Firefox 7 and or later.

The browser window running Call Center should be at least 1024 x 768 pixels in size.

When a window is vertically resized, the panes do not always resize to fill the window. To resize a window, drag the window from the bottom right-hand corner or collapse and then expand the panes after resizing to adjust them to the window.

- *Save Workspace* – This button, when clicked, saves the current workspace.
- *Load Workspace* – This button, when clicked, arranges your workspace according to the last saved configuration.
- *Restore To Default* – This button, when clicked, restores the workspace to the system default configuration.
- *Always save workspace on signout* – When you sign out from the client, Call Center asks you whether you want to save your current workspace. To save your workspace automatically when signing out, without being asked, check the *Always save workspace on signout* box.

To customize your workspace:

1. Arrange the windows the way you like.
2. Click the **Save Workspace** button to save the current configuration. To restore the system default, click **Restore To Default**.

- At any time to return to the last saved configuration, click the **Load Workspace** button.

SETTINGS – APPLICATION

You use the Application tab to configure your application settings. The settings are different for agents and supervisors. They are described in the following subsections.

Queue Memberships

☐ Queue	Number	Wrap-Up Policy	Skill Level
☐ Banking	1000001045	1:00	6
☐ Cards	1000001047	1:00	1
☐ General	1000001048	1:00	9
☐ HealthCare	1000001049	1:00	4
☐ Marketing	1000001043	1:00	6
☐ Mortgage	1000001044	1:00	N/A
☐ Payroll	1000001042	1:00	1
☐ Sales	1000001041	1:00	5
☐ Trading	1000001046	1:00	5
☐ Transport	1000001050	1:00	5

Agent Policies

Post Sign-In ACD State :

Post Call ACD State :

☒ Set Wrap-Up timer to : for queues without a policy

☐ Outgoing calls as call center

Outbound Caller Id :

Figure 150 Settings – Application (Agent)

QUEUE MEMBERSHIPS (AGENT)

These settings allow you to select the call center queues you wish to join. The table also displays your skill level in each queue (for more information, see section [Agent Skill Levels \(Premium Call Centers\)](#)).

- To join a call center queue, select the check box on the line for the call center.
- To join all queues, select the check box in the header.



Note: If you are not allowed to join/leave a queue, the line for the queue is dimmed and you can only view your join status in the queue. To change your join status in a queue, if you are not allowed to do it yourself, contact your administrator.

AGENT POLICIES (AGENT)

You use agent policies settings to specify your post sign-in ACD state, post call ACD state, wrap-up timer, and outbound CLID:

- *Post Sign-In ACD State* – To configure your post sign-in ACD state, select a state from the *Sign-In State* drop-down list. Your ACD state is automatically set to the selected state when you sign in to Call Center.

If you selected *Unavailable* and unavailable codes are enabled for your organization, select an unavailable code from the drop-down menu.

- *Post Call ACD State* – To configure your post call ACD state, that is your ACD state upon completion of a call, select a state from the *Post Call State* list.

If you selected *Unavailable* and unavailable codes are enabled for your organization, select an unavailable code from the drop-down menu.

In most cases, when you select *Wrap-Up*, you must also configure your wrap-up timer.

- *Set Wrap-Up Timer to* – To set your post call wrap-up timer, check the *Set Wrap-Up Timer to <mm:ss> for queues without a policy* box and enter the time in minutes and seconds. Your ACD state automatically changes from *Wrap-Up* to *Available* after the specified period of time.



Note: Your post call wrap-up timer setting may be overridden if your administrator sets the timer to a smaller value on Clearspan.

- *Outgoing calls as call center* – Check this box to display a call center CLID instead of your phone number when you make a call.
- *Outbound Caller ID* – If you checked *Make outgoing calls as call center*, select the number to use from the drop-down menu.

BARGE-IN & MONITOR (SUPERVISOR)

The following options only apply if you have the Directed Call Pickup with Barge-in and/or Call Center Monitoring services assigned. If the Call Center Monitoring service is not assigned, then the *Monitor* option is not visible.

The screenshot shows the 'Application' settings tab. Under the 'Barge-In & Monitor' section, there is a heading 'Use warning tone when barging in'. Below this heading are two checkboxes: 'Barging In' (which is checked) and 'Monitor' (which is unchecked). At the bottom of the window, there is a footer that reads 'Manage your Application preferences' on the left and '1 categories' on the right.

Figure 151 Settings – Application (Supervisor)

Use warning tone when:

- *Barging In* – When this option is set, the agent hears a warning tone when you barge in on their call.
- *Monitoring* – When this option is checked, the agent hears a warning tone when you start silently monitoring their call.

SETTINGS – SERVICES

You use the Services tab to configure various services assigned to you by your administrator on Clearspan, which are integrated with Call Center. These settings are only available if you have been assigned such services. For more information, see your administrator.

The services are grouped into two categories: Active and Inactive.

The screenshot shows the 'Services' configuration window. The 'Services' tab is active, displaying a list of 'User Services' under the 'Inactive' category. The 'Call Forwarding Always' service is selected. The 'Service Settings' section for this service shows the 'Active' checkbox checked, the 'Ring Splash' checkbox unchecked, and the 'Forward To' text box containing the number '202551009'. The 'Save' and 'Cancel' buttons are at the bottom. The footer of the window indicates 'Manage your service settings' and '2 Services'.

Figure 152 Settings – Services

The services that you can configure (if you have been assigned the services) are:

- *Do Not Disturb* – When you activate this service, you are not available to take calls, and all your calls are automatically sent to your voice mail.
- *Call Forwarding Always* – When you activate this service, you must provide the phone number to forward your calls to. When the service is active, all your calls are forwarded to the specified number.

To activate a service:

1. Select the service and check the *Is Active* box. The service is moved from the *Inactive* to *Active* category.
2. If you enabled the *Call Forwarding Always* service, in the *Forward To* box that appears, enter the number to forward your calls to.
3. To generate a ring splash for incoming calls, check the *RingSplash* option.
4. To save your changes, click **Save**.

SETTINGS – PLUG-INS

You use the Plugins tab to configure the plug-in software used by Call Center to provide functionality such call notification, program shortcuts, and call log (which are called desktop integration features).

Plugins

☐ Disable All Plug-ins

Notification

☒ Focus window for incoming calls

☒ Show notifications for calls when auto answer is off

Microsoft® Outlook®

Enable Outlook Integration ...

Retrieve contacts from : Default Contact Folder

☒ Use Outlook contacts as preferred CLID lookup

LDAP v3

Enable LDAP Integration ...

389

☒ Recursive

☐ Encrypt Connection

(cn=*__SEARCH_TEXT__*)

Attribute Mapping

Remote Attribute	Local Attribute	Dialable
cn	cn	☐
sn	sn	☐
displayName	displayName	☐
telephoneNumber	telephoneNumber	☒
mobile	mobile	☒
homePhone	homePhone	☐

☐ Authentication Required

Figure 153 Settings – Plugins (Top of Page)

PLUG-INS

Check the *Disable All Plug-ins* box to disable all desktop integration components of Receptionist.

Disable All Plug-ins – This setting allows you to enable or disable all desktop integration features. When this option is checked, the JNLP file required to run the desktop integration components will not be downloaded and the desktop integration features will not work.

NOTIFICATION

These options control when and how call notifications are displayed. The options you can set are as follows:

- *Focus window for incoming calls* – When this option is checked and the browser window that is running Call Center is minimized, Call Center automatically restores the window on incoming calls.

This does not work in Firefox. In Internet Explorer, you must have only one tab open in the web browser running Call Center.

- *Show notification for calls* – When this option is checked, Call Center displays the *Call Notification* pop-up window on top of other applications' windows when you receive a call. When you check this box, you need to select an option from the drop-down list to specify the condition under which notifications are displayed.

This does not work if other tabs are open in the same web browser window as Call Center. In addition, if calls come within eight seconds of each other, the *Call Notification* pop-up window appears only for the first call of that series.

MICROSOFT OUTLOOK

The Microsoft Outlook options control Outlook integration with Call Center. They are only visible if Outlook integration is enabled in Call Center.

The options you can set are as follows:

- *Enable/Disable Outlook Integration* – This determines whether Call Center integrates with Outlook to provide you with access to your Outlook contacts. If Outlook integration is disabled, the corresponding desktop plug-in software components are not downloaded from Clearspan.
- *Retrieve contacts from* – This option allows you to specify where to look for your Outlook contacts.
- *Use Outlook contacts as preferred CLID lookup* – When this option is checked, Call Center uses Outlook to try to identify a caller, when the caller ID is unknown.



Note: The Outlook Integration feature provides the following functionality: CLID lookup, saving vCards, and accessing and searching Outlook contacts. When using Microsoft Outlook 2010 or 2013 (32- or 64-bit edition), Outlook must be running before Call Center is launched for these functions to work.

LDAP V3

LDAP settings allow you to integrate an LDAP directory with Call Center. These options are only visible if LDAP integration is enabled in Call Center. If you do not know the appropriate settings, contact your system administrator.

Make sure you have correctly imported a valid certificate in the Java Keystore (JKS) with the keytool.

To import a certificate:

1. Click **Start** and then select *Run...*
2. Type "cmd" and click **OK**.
3. Type "<Java Runtime Path>\bin\keytool -import -alias <aliasname> -file <path><certificate file name> -keystore %JAVA_HOME%\jre\lib\security\cacerts".

To verify the certificate:

1. Click **Start** and select *Run...*
2. Type "cmd" and click **OK**.
3. Type "<Java Runtime Path>\bin\keytool -printcert -file <path><certificate file name>".

The LDAP directory options are as follows:

- *Enable/Disable LDAP Integration* – This determines whether Call Center provides LDAP directory lookup services. Clicking the **Enable LDAP Integration** button enables the controls for LDAP settings.
- *LDAP Hostname* – This is the network address of the LDAP server.
- *LDAP Port* – This is the port number for the LDAP server. This is compulsory and can be obtained from your system administrator.
- *Search Base:*
 - The text box determines the location in the LDAP server tree that Call Center looks in when executing a search.
 - The check box, when checked, searches all sub-trees within the search base until the specifications are found.
- *Encrypt Connection* – This option determines whether Call Center uses encryption when connecting to the LDAP server. Note that if encryption is enabled, you may have to use of a different port.
- *("cn=__Search__Text")* – This option specifies an additional search filter to apply to all directory searches. For example, to include the search criteria in the filter you must include (cn=*__SEARCH_TEXT__*). Alternatively, in another example, (telephoneNumber=*) restricts search results to users who have a telephone number assigned.

- *Attribute Mapping* – This table controls the way that Call Center maps attributes returned from the directory server to columns displayed on the list of search results.
 - In each row of the table, enter an LDAP attribute in the *Remote Attribute* column.
 - In the *Local Attribute* column, enter a corresponding local attribute. Typical Remote Attribute values are “cn”, “sn”, “telephoneNumber”, “mobile”, “homePhone”, and “mail”.
 - Check the box in the *Dialable* column for attributes that you want to be able to use to call the contact, for example “telephoneNumber”, or “mobile”.
- *Authentication Required* – When this box is checked, Call Center must provide a user name and password to the directory server to conduct searches.
- *DN* – This is the user name Call Center uses when connecting to the LDAP server when *Authentication Required* is checked.
- *Password* – This is the password that corresponds to the authentication *DN*.

PROGRAM SHORTCUTS

You use the program shortcuts settings to create call center shortcuts on your desktop for convenient access to Call Center.

The program shortcuts plug-in allows for the creation of desktop shortcuts on a Windows platform, which when clicked, launches the applications in your default web browser.

- *Add Shortcut* – This button, when clicked, creates a call center shortcut on your desktop.
- *Remove Shortcut* – This button, when clicked, removes the previously created Call Center shortcut. If you did not create a shortcut using the Add Shortcut button, the Remove Shortcut button has no effect.

CALL EVENT LOG

This plug-in software provides the ability to store call event statistics content locally on your computer.

- *Enable/Disable Call Event Log Integration* – This double-action button allows you to enable or disable call log archives on your computer.
- *Rotate Log* – This parameter allows you to specify the frequency with which the call log is rotated. You select the frequency from the drop-down list.
- *Open Log Location* – Click this link to go to the place on your computer where the log is stored.

The log is saved at the desired interval as a comma-separated value (CSV) file in the following path:

<Drive>:\Documents and Settings\<Windows_Username>\Application Data\BroadSoft\BW Call Center\profiles\<BW_User_ID>\statistics

where:

- *Drive* is the drive letter where your profile is stored (typically C)
- *Windows_Username* is your Windows user name
- *BW_User_ID* is your Clearspan user ID

The following events are captured based on activity that occurs on the Agent/Supervisor client (irrespective of ACD or direct inbound or outbound calls).

Statistic	Description	Allowed Values	Example Value
Clearspan User ID	Clearspan user ID	String	jsmith@abc.net
Call Center ID	Call Center ID for inbound ACD calls only	String, null	ABCSales
Availability	Agent's joined state	Joined, Not Joined, null	Joined
ACD State	Agent's ACD state	Sign-On, Available, Unavailable, Wrap-Up, Sign-Out, null	Null
Call ID	ID of the call	String, null	192.168.1.5:1
Call State	State of the call	Idle, Incoming, Outgoing, Active, Held, Remote Held, Detached, Released, null	Incoming
Personality	The personality of the call. It indicates whether the user originated this call or whether the call was placed to the user.	Integer (0, 1, 2): ▪ 0 = Clearspan Originator ▪ 1 = Originator ▪ 2 = Terminator	0
Remote Name	External caller name	String or null	Null
Remote Number	External caller number	String or null	5555551234
Last Redirected Name	Last redirected name	String or null	Jane Doe
Last Redirected Number	Last redirected number	String or null	Null
Time	Date stamp of record	Long Date/Time Format	2008-04-03 12:08:17.859



Note: Each row in the log file records a *single* event change and as such, columns like *Availability*, *ACD State*, and *Call State* may contain null values since an alternate column value caused the event change. For example, *Wrap-Up* is stored in the ACD State while the Call State (and other columns) store null.

SETTINGS – MESSAGING

The Messaging tab allows you to configure various messaging options for Call Center. Currently, e-mail messaging and instant messaging are supported.

Figure 154 Settings – Messaging

E-MAIL MESSAGING

These options allow you to specify the mail client you use for sending e-mail messages.

From the drop-down list, select the mail client to use for e-mails.

If you selected the custom Simple Mail Transfer Protocol (SMTP) option, you also need to configure the following options:

- *Display Name* – This is the name that is displayed in the *From* field.
- *Reply-to Address* – This is the address where reply messages can be sent.
- *Default Subject* – This is the subject that appears when you generate an e-mail message in Call Center.
- *SMTP Host* – This is the IP address of the SMTP host.
- *SMTP Port* – This is the port of the SMTP host.

- *Outgoing SMTP Server requires Authentication* – When this option is set, authentication is required to send e-mails.
- *Username* – This is the name you must enter to authenticate yourself.
- *Password* – This is the password part of your authentication credentials.
- *Mail Type* – This is the type of mail to use.
- *Mail Template* – This is the mail template to use.

INSTANT MESSAGING AND PRESENCE

Check this option if you want the *Chat* windows that appear when you receive an instant message to appear in minimized format.

SETTINGS – REPORT

You use the Report tab to configure values to be used as default input parameters for generating reports. If you do not provide any values, system defaults are used. You can change these values as required when generating reports.

The screenshot displays the 'Report' tab in the Clearspan Call Center settings. The top navigation bar includes tabs for General, Application, Services, Plugins, Messaging, Report (selected), and About. The 'Report' section is divided into three main areas:

- Default Thresholds:** Contains four input fields for 'Call Completion', 'Short Duration Call', 'Service Level', and 'Abandoned Call'.
- Default Start Day Of Week:** Features a dropdown menu currently set to 'Sunday'.
- Default Service Level Calculations:** Includes five radio button options:
 - ☒ Include Overflow Time Transferred Calls
 - ☐ Include All Other Transfers
 - ☐ Exclude Abandoned Calls
 - ☒ Include all abandoned calls
 - ☐ Include all abandoned calls except before entrance completes
 - ☐ Include Abandoned Calls except in Defined Interval
 Below these options is a text input field labeled 'Defined Interval For Abandoned Calls'.

Figure 155 Settings – Report

DEFAULT THRESHOLDS

These settings allow you to configure the thresholds that are used by default when you generate reports that require you to provide thresholds. This is useful, if you often use the same threshold values. You can always change a default value, when required.

- *Call Completion* – This setting is used to count the number of ACD calls an agent has completed within a service level during the specified interval. The Call Completion service level can be set to “1” through “7200” seconds.
- *Short Duration Call* – This setting is used to count the number of ACD short duration calls completed by an agent during an interval. You can set the maximum length of a short duration call to “1” through “7200” seconds.

DEFAULT START OF THE WEEK

The following setting allows you to configure the day of the week to start reports.

- *Default Start Day of Week* – This setting applies to interval-based reports, when the selected sampling period is “Weekly”. It can be set to any day of the week.

DEFAULT SERVICE-LEVEL CALCULATIONS

The following settings allow you to configure default settings used to make service-level calculations.

- *Include Overflow Time Transferred Calls* – Check this box to include calls transferred due to time overflow in service-level calculations.
- *Include All Other Transfers* – Check this box to include calls transferred for other reasons that overflow in service-level calculations.
- *Exclude Abandoned Calls* – Check this box to exclude all abandoned calls from service-level calculations.
- *Include all abandoned calls* – Check this box to include all abandoned calls in service-level calculations.
- *Include all abandoned calls except before entrance completes* – Check this box to include calls abandoned after the entrance message has finished playing in service-level calculations.
- *Include Abandoned Calls except in Defined Interval* – Check this box to include calls abandoned after the time specified by the interval for abandoned calls parameter in service-level calculations.
- *Defined Interval for Abandoned Calls* – If you checked *Include Abandoned Calls except in Defined Interval*, enter the desired interval in this text box in seconds. The *Defined Interval for Abandoned Calls* can be set to “1” through “7200” seconds.

SETTINGS – ABOUT

You use the About tab to view the information about Call Center.




Figure 156 Settings – About

The following information is provided on this page:

- *Version* – This is the name and software version of Clearspan Call Center client.
- *Profile* – This is the Call Center client profile used.
- *Disclaimer* – This is the Call Center copyright information.
- *Diagnostics* – This allows you to access the Diagnostic Tool, available in some versions of Call Center. If the tool is not available, this information does not appear. For more information about the tool, see *Appendix B: Diagnostic Tool*.

CONFIGURE WEB BROWSER

INTERNET EXPLORER SETTINGS FOR FULL SCREEN MODE

For the supported versions of Internet Explorer, see the Clearspan Hosted Thin Call Center Agent/Supervisor Configuration and Administration Guide.

Internet Explorer needs to be configured as follows to enable the Full Screen link in Call Center. Otherwise, the link has no effect; Call Center is not displayed in full-screen mode when the Full Screen link is clicked and no error message is displayed to the user.

1. On the Internet Explorer *Menu* bar, select the *Tools* menu and then click **Internet Options**.
2. In the *Internet Options* dialog box, click the **Security** tab and then click the **Custom level...** button.




Figure 157 Security Settings – Internet Zone Dialog Box

3. In the *Security Settings – Internet Zone* dialog box, scroll down to *Initialize and script ActiveX controls not marked as safe for scripting* setting in the *ActiveX controls and plug-ins* section.
4. Select *Enable* or *Prompt*.
5. Click OK.

6. Restart Internet Explorer.

FIREFOX SETTINGS FOR QUICK LINK NAVIGATION

The *dom.disable_window_flip* preference must be set to “false” in Firefox for quick link navigation to work. If this setting is not configured, Call Center does not change focus from the Dashboard to the main application window when the user clicks on a quick link. Follow these steps to configure Firefox for quick link navigation:

1. Open a new tab in Firefox.
2. In the address bar, type “about:config” and press the **Enter** button.
3. Click the warning button that appears and a list of preferences appears.
4. Go down to *dom.disable_window_flip* and set the value to “false”. Double-clicking the flag alternates the value between “true” and “false”.

CERTIFICATE FOR DESKTOP INTEGRATION FEATURES

You need to add the desktop plug-in certificate to the browser-specific certificate store location on your machine, which is required to run Call Center desktop integration features. For the list of the desktop integration features, see *Settings – Plug-ins*.

The following table displays the list of browsers and their respective certificate trust store location.

BROWSER	WINDOWS	MAC OS
Chrome	Windows Certificate Store	System Keychain
Internet Explorer	Windows Certificate Store	Not Applicable
Safari	Not Applicable	System Keychain
Firefox	Firefox Certificate Store	Firefox Certificate Store

The following subsections provide instructions for adding the certificate in the different environments.

DOWNLOAD DESKTOP PLUG-INS CERTIFICATE

The desktop plug-ins certificate can be downloaded with the following HTTP call to the Call Center client context:

```
http(s)://<host[:port]>/<CC context>/certificate/desktopplugin.cer.
```

For example:

`https://xsp.broadsoft.com/com.broadsoft.callcenter/certificate/desktopplugin.cer`

ADD CERTIFICATE TO MICROSOFT WINDOWS CERTIFICATE STORE

Follow these steps to add the desktop plug-in certificate to the Windows certificate store.

Method 1 – Using certmgr.msc command:

1. Click the **Start** button, type “certmgr.msc” into the *Search* box and then press ENTER.
2. If you are prompted for an administrator password or confirmation, type the password or provide confirmation. The *Certificate Manager* window appears.




Figure 158 MS Windows – Certificate Manager

3. Double-click the **Trusted Root Certification Authorities** store to expand it, and then right-click **Certificates**.
4. From the menu that appears, select *All Tasks*, and then *Import*. The *Certificate Import Wizard* dialog box appears.




Figure 159 Certificate Import Wizard

5. Follow the instructions of the wizard to install the certificate.

Method 2 – Using Internet Explorer

1. From the Internet Explorer *Menu* bar, select *Tools* and then *Internet Options*. The *Internet Options* window appears.




Figure 160 Internet Explorer – Internet Options

2. Click the **Content** tab and then the **Certificates** button. The *Certificates* window appears.




Figure 161 MS Windows – Certificates Window

3. Click the **Trusted Root Certification Authorities** tab, and then click the **Import** button. The *Certificate Import Wizard* dialog box appears.




Figure 162 Certificate Import Wizard

4. Follow the instructions of the wizard to install the certificate.

Method 3 – Using Google Chrome:

1. Open the Chrome browser.
2. In the top right of the browser window, click the Chrome menu .
3. Click **Settings**. The *Settings* tab appears.
4. At the bottom, click **Show advanced settings** and scroll down to the *HTTPS/SSL* section.




Figure 163 Chrome – Advanced Settings

5. Click **Manage certificates**. The *Certificates* window appears.




Figure 164 MS Windows – Certificates

- Click the **Trusted Root Certification Authorities** tab, and then click the **Import** button. The *Certificate Import Wizard* dialog box appears.




Figure 165 Certificate Import Wizard

- Follow the instructions of the wizard to install the certificate.

ADD CERTIFICATE TO APPLE SYSTEM KEYCHAIN

To add the certificate into the system keychain on a Mac computer, do the following:

1. In the *Dock*, open *Finder*.




Figure 166 Mac OS – Finder

2. Select *Applications* and then *Utilities*.
3. In the list of utilities, double-click **Keychain Access**.
4. In the *Keychain Access* window, under *Keychains*, click **System** and then under *Category*, click **Certificates**.




Figure 167 Mac OS – Keychain Access

5. In the *Keychain Access* toolbar, select *File* and then *Import Items*.
6. Follow the instructions of the browser to import the certificate file. The certificate appears in the list of certificates as 127.0.0.1.
7. In the *Keychain Access* window, double-click the certificate. The certificate window appears.




Figure 168 Mac OS – Certificate Window

8. In the *Trust* section, select *Always Trust* for *When using this certificate*.

9. Close the browser.

ADD CERTIFICATE TO FIREFOX CERTIFICATE STORE

Mozilla Firefox has its own certificate store. Follow these steps to add the certificate to the Firefox Certificate store.

1. Open the Firefox browser.
2. Open the *Options/Preferences* window:
 - On Windows: From the *Tools* menu, select *Options*.
 - On Mac: From the *Firefox* menu, select *Preferences*.

The *Options/Preferences* window appears.




Figure 169 Firefox – Options

1. Click **Advanced** and then click the **Certificates** tab.
2. Click **View Certificates** to open the *Certificate Manager*.




Figure 170 Firefox – Certificate Manager

3. Click the **Servers** tab.
4. Click **Import**.
5. Select the certificate file on your computer and import it.
6. Click the **Add Exception** button. The *Add Security Exception* window appears.




Figure 171 Firefox – Add Security Exception

7. In the *Location* textbox, enter `https://127.0.0.1:5555/` and click **Get Certificate** (assuming that “5555” is the default port of the local HTTPS [127.0.0.1] server).
8. Click **Confirm Security Exception**.
9. In the *Certificate Manager*, click **OK**.

UPDATE CERTIFICATE

The new certificate requirements of Google Chrome (version 58.0 or later) and Mozilla Firefox (version 54.0 or later) require a new version of the desktop plug-in certificate.



Note: This applies to Call Center clients version 22.0.26 or later.

1. The first time you sign in to Call Center version 22.0.26 or later and have the older version of the certificate (created on December 30, 2015) in the Windows Certificate Store, the following pop-up appears. Click **Yes** to delete this certificate from the store.




Figure 172 Root Certificate Store Dialog Box

10. Once the older version of the certificate is deleted or if it was not previously imported, the following dialog box appears. Click **Yes** to import the new certificate.




Figure 173 Security Warning Dialog Box

11. After the certificate is successfully imported, restart the browser.
12. If the old version of the certificate was previously imported to the Firefox certificate store, it will be automatically deleted while running the JNLP file. Once the old certificate is deleted or if it was not previously imported, the following dialog box appears if the Firefox browser is open during the current session even if you started the client in a different browser. Click **OK** to import the new certificate.




Figure 174 CallCenter.jnlp Dialog Box



Note: The new desktop plug-in certificate will not work for Call Center clients released prior to version 22.0.26. If you have imported the new certificate and want to run desktop integration features in an older version of the client, manually delete the new certificate.

SECURITY SETTINGS FOR DESKTOP INTEGRATION FEATURES

JNLP DOWNLOAD

As you sign to Call Center, a JNLP file is downloaded and you are asked to click the link shown in the browser. Due to security restrictions, the application may not run. If this occurs, perform the steps specified in the following subsections.

NOTE: You should run Java JRE 1.6 or higher.

ON MAC OS X

In MAC OS X, due to security-related restrictions, the JNLP may not execute even if you click on it. If this occurs, perform the following steps:

1. Open *System Preferences* and select *Security and Privacy*. The Security & Privacy window appears displaying the *General* tab.




Figure 175 Mac OS X – Security & Privacy

2. Unlock the panel with the lock icon.
3. In the *Allow applications downloaded from* section, select **Anywhere**.

INTERNET EXPLORER

If you are running Internet Explorer, you must perform the following steps to run JNLP.



Note: You must run Call Center over HTTPS with Internet Explorer.

1. From the Internet Explorer *Menu* bar, select **Tools** and then **Internet Options**. The *Internet Options* window appears.




Figure 176 Internet Explorer – Internet Options – Security

2. Click the **Security** tab.
3. Click **Trusted sites** and then click **Sites**. The *Trusted sites* window appears.




Figure 177–Internet Explorer – Trusted Sites

4. In the *Add this website to the zone* text box, enter the Call Center client URL and then click **Add**. The URL appears in the *Websites* box.
5. Click **Close**.
6. In the *Internet Options* window, click **Custom level**. The *Security Settings – Trusted Sites Zone* window appears.




Figure 178 Internet Explorer – Security Settings – Trusted Sites Zone

7. Scroll down to *Miscellaneous* settings section and select *Enable* for the *Access data sources across domains*.
8. Click **Yes** in the *Warning!* window that appears.
9. Click **OK** and then click **OK** in the *Internet Options* window.

RESTRICTIONS AND LIMITATIONS

Receptionist limitations are due mainly to the restrictions imposed by the web browsers.

TAB BUTTON AND PDF REPORTS IN MICROSOFT EDGE

When running in the Edge browser, Call Center experiences the following limitations:

The Tab button does not work.

When you run a report in PDF format, the report does not display in the window. Instead, a dialog box appears asking you to download the report to your computer.

QUICK LINK NAVIGATION IN CHROME AND FIREFOX

Navigating from the Dashboard to an agent in the Agents directory or to a call center in the Queued Calls pane does not work in Google Chrome and requires to set the Mozilla Firefox `dom.disable_window_flip` flag to “false”. For details on setting the flag, see section [Firefox Settings for Quick Link Navigation](#).

APPENDIX A: GLOSSARY AND DEFINITIONS

ACD STATES

ACD states specify the agent's availability to take calls. The possible call states are those listed in the following table.

An agent can be in one of the ACD states.

ACD STATE	ICON	DESCRIPTION
<i>Available</i>		Agent is available to receive ACD calls. (Agent can also receive direct calls.) This is the primary ACD state of an agent during the workday. It indicates that the agent is at their workstation and either ready to take a call or on an active call. ACD calls may be delivered to an agent who is in an <i>Available</i> state. Clearspan uses both the ACD state and the phone state of the agent to determine whether to route a call to the agent. By default, agents receive calls when they are available and their phone is <i>Idle</i>. However, this behavior can be overridden if Call Waiting on agents is enabled for the call center, which allows for new calls when the agent is available and on an active call.
<i>Unavailable</i>		Agent is unavailable to receive ACD calls. (Agent can still receive direct calls.) The <i>Unavailable</i> state should be used when the agent is away from their workstation and not available to take calls. ACD calls are not delivered to agents in an <i>Unavailable</i> state. This state should be used when the agent is at lunch, on a break, in a meeting, or engaged in some other activity while they are at work, but unavailable to take calls.
<i>Wrap-Up</i>		Agent is performing post call work. This state is designed to allow the agent to complete paperwork or other post call procedures associated with the last call. Calls may be delivered to agents in <i>Wrap-Up</i> state depending on the call center configuration. By default, calls are not routed to agents in <i>Wrap-Up</i> state, except when the call center is configured to enable calls to agents in the <i>Wrap-Up</i> state.

ACD STATE	ICON	DESCRIPTION
<i>Sign-In</i>		The <i>Sign-In</i> state is equivalent to a “clock in”, which means that the agent is at their work location but not yet ready to accept incoming calls. Calls are not delivered to the agent in this state. <i>Sign-In</i> is a transitional state and agents do not remain in this state; rather they transition to their post sign-in state. It is recommended that agents only be in this state between the time they arrive at work and the time they become available to accept calls.
<i>Sign-Out</i>		The <i>Sign-Out</i> state is equivalent to a “clock out”, which means that the agent’s workday or shift is completed and they are leaving. Calls are not delivered to the agent in this state. It is recommended not to use this state when agents leave for lunch or breaks during the day. The <i>Unavailable</i> state should be used for that.

In Call Center, an agent can only set their ACD state to “Available”, “Unavailable”, or “Wrap-Up”. A supervisor can set the ACD state of an agent to “Available”, “Unavailable”, “Wrap-Up”, or “Sign-Out”.

The *Sign-In* state can only be assigned to an agent through the web portal.

AGENT SKILL LEVELS (PREMIUM CALL CENTERS)

Agent skill levels are used to rate the ability of an agent to handle calls in call centers with skill-based routing.

- An agent skill level is an integer between 1 and 20, where 1 indicates the highest skill level.
- A skill level is assigned to an agent for each call center with skill-based routing to which the agent is assigned.
- A skill level is shown as “N/A” for Standard call centers and for call centers with priority-based routing.

PHONE STATES

Phone states show the state of the monitored agent's telephone line or the supervisor's telephone line.

For supervisors, the phone states are displayed as shown in the following table:

PHONE STATE	ICON	DESCRIPTION
<i>Idle</i>		Supervisor's phone is on-hook, which means the supervisor is not on a call.
<i>Busy</i>		Supervisor's phone is off-hook, which means that the supervisor is on a call.
<i>Ringing</i>		Supervisor's phone is in alerting state; a call is currently being delivered to the supervisor.
<i>Do Not Disturb</i>		Supervisor has enabled the Do Not Disturb service.
<i>Private</i>		Supervisor has enabled phone status privacy. NOTE: This terminates monitoring of the supervisor's phone state for the current login session. To be able to monitor their phone state again, you must sign out and then sign in after the supervisor has disabled their phone state privacy.
<i>Call Forwarding Always</i>		Supervisor has enabled the Call Forwarding Always service.
<i>Unknown</i>		Supervisor is currently not monitored.

For agents, the phone states are combined with their ACD states and are displayed as shown in the following table:

PHONE STATE	ACD STATE	ICON	DESCRIPTION
<i>Idle</i>	<i>Available</i>		Agent's phone is on-hook and the agent is available to take ACD calls.
<i>Ringing</i>	<i>Available</i>		Agent's phone is ringing and the agent is available to take the call.
<i>Any</i>	<i>Unavailable, Sign-In, Sign-Out</i>		Agent is not available to take ACD calls.
<i>Idle, Ringing</i>	<i>Wrap-Up</i>		Agent is performing post call work. They may or may not be available to take calls.
<i>Busy</i>	<i>Available, Wrap-Up</i>		Agent's phone is off-hook, which means that the agent is on a call. Calls may be delivered to agents depending on their call waiting settings and the call center's call waiting and wrap-up settings.

PHONE STATE	ACD STATE	ICON	DESCRIPTION
<i>Do Not Disturb</i>	Any		Agent has enabled the Do Not Disturb service. ACD calls are not delivered to an agent in the Do Not Disturb call state. This state is not recommended for Call Center agents. Agents should use the Unavailable ACD state when they need to block new incoming calls temporarily.
<i>Call Forwarding Always</i>	Any		Agent has enabled the Call Forwarding Always service.
<i>Private</i>	Any		Agent has enabled phone status privacy. NOTE: This terminates monitoring of the agent's phone state for the current login session. To be able to monitor their phone state again, you must sign out and then sign in after the agent has disabled their phone state privacy.
<i>Unknown</i>	Any		Agent is currently not monitored.

UNIFIED INSTANT MESSAGING PRESENCE STATES

Unified instant messaging presence states indicate you or your contacts' availability to communicate using client applications such as Hosted Thin Call Center, Hosted Thin Receptionist, Clearspan Communicator Desktop, or Clearspan Communicator Mobile. The possible states are as shown in the following table:

IM&P STATE	ICON	DESCRIPTION
Subscribed states		
<i>Available</i>		The contact is online, available on one or more devices, and not busy on any device.
<i>Busy</i>		The contact is online, but currently busy on one or more devices. Do not disturb.
<i>Away</i>		The contact is connected but away from one or more devices and not busy on any device.
<i>Offline</i>		The contact is offline on all devices. If you are offline, you do not receive any presence updates or instant messages. Also, your Instant Message pane is empty and the presence state of your contacts in other <i>Contact</i> panels is set to "Offline".
Unsubscribed states		
<i>Pending Subscription</i>		You sent a subscribe request to the contact, but it has not yet been accepted. Clicking the icon resends the request.
<i>Not subscribed</i>		The contact has IM&P but you are not subscribed to monitor their state. The contact is not listed in the <i>Instant Message</i> directory. Clicking this icon sends a subscription request to

IM&P STATE	ICON	DESCRIPTION
		the contact.

CALL STATES

Call states are the states that your current calls can be in. They are shown in the following table:

CALL STATE	DISPLAY NAME	DISPLAY ICON	CALL PERSONALITY	CALL ACTIONS
<i>Ringing In (Local)</i>	Incoming Local		Click To Dial	Answer, End
<i>Ringing In (Remote)</i>	Incoming		Terminator	Answer, Conference, End
<i>Ringing Out, Outgoing</i>	Outgoing		Originator	Conference, End
<i>Active</i>	Active		Any	Transfer, Hold, End, Conference
<i>On Hold</i>	Held		Any	Transfer, Resume, End, Conference
<i>On Hold (Remote)</i>	Held		Any	Transfer, Hold, End, Conference
<i>Active (In Conference)</i>	Active		Conference	Transfer, Hold, End
<i>On Hold (In Conference)</i>	Held		Conference	Resume, Transfer, End
<i>Ringing In (Recalled Call)</i>	Call Recalled		Terminator	Answer, Conference, End

CALL TYPES

This section defines different types of calls measured in call center statistics.

NAME	DESCRIPTION
ACD Call	This is a call delivered to a call center pilot number that is directed to an agent via the ACD function.
Inbound Call	This is a direct call to an agent. Other calls treated as inbound calls include: • Calls that a supervisor retrieves from a queue • Calls that an agent receives due to a transfer from another agent (Note that they may have originated as ACD calls.)
Outbound Call	This is an outbound call made by an agent.
Held Call	This is an ACD call that was placed on hold by an agent. Each time an agent places a call on hold, it is counted as a held call.
Transferred Call	This is an ACD call that was transferred to another number.

NAME	DESCRIPTION
	Transfers can be the result of manual transfers by agents, transfers to voice mail because the calls were timed out, and transfers by supervisors to alternate queues. Note: A timed-out call is a call that is transferred due to exceeding the maximum wait time in a queue.
Answered Call	This is an ACD call that was answered by an agent.
Abandoned Call	This is an ACD call that entered the queue, but the caller hung up before the call was answered or transferred.
Received Call	This is an ACD call that was received and either answered or abandoned. Overflowed calls are not included.
Overflowed Call	This is an ACD call that was received, but immediately transferred to another destination due to the queue's exceeding the configured maximum queue size or the configured maximum wait time.
Queued Call	This is an ACD call that is not immediately diverted using the Night Service, Holiday Service, Forced Forwarding, or Overflow, and goes to a queue to be distributed to an agent or to wait for an available agent.
Bounced Call	This is a call that has been transferred back to queue because it was not answered by an agent in the specified time. Note: As of Clearspan release 20, Bounced Call is now supported in Basic Call Center as well as Premium Call Center.
Stranded Call	This is a call that is in a queue after all agents assigned to the queue have moved to the <i>Sign-Out</i> ACD state.

CALL REDIRECTION REASONS

The following table lists the possible reasons for redirecting calls.

NAME	DESCRIPTION
busy	The call was redirected to a specified destination because the Call Forwarding Busy service was activated and the subscriber was busy. A subscriber is considered busy when there are too many active calls.
no answer	The call was redirected because the Call Forwarding No Answer service was activated and the subscriber did not answer within the specified number of rings.
unavailable	The call was redirected because the Call Forwarding Not Reachable service was activated and the subscriber's device was either unreachable or unregistered.
unconditional	The call was redirected because the Call Forwarding Always service was activated. When active, the Call Forwarding Always service redirects all incoming calls.
time of day	The call was redirected because the Call Forwarding Selective service was activated and the incoming call matched the specified time of day value.
do not disturb	The call was redirected because the Call Forwarding Busy service

NAME	DESCRIPTION
	was enabled and the Do Not Disturb service was activated.
deflection	The call was transferred before being answered.
follow me	The call was redirected because one of the following services was activated: Simultaneous Ringing, Sequential Ringing, or Clearspan Anywhere.
out-of-service	The call session was redirected by the network with the reason set to "out-of-service?".
away	The call was redirected by the network with the reason set to "away".
transfer	The call was transferred after being answered.
voice mail	The call was redirected because the Call Forwarding Always to Voice Mail service was activated, the Call Forwarding Busy to Voice Mail service was activated, and the subscriber was busy, or the Call Forwarding No Answer to Voice Mail service was activated and there was no answer.
hunt group	The call was redirected to an agent by a hunt group.
call center	The call was redirected to an agent by a call center.
route point	The call was redirected to an agent by a route point.
unknown	The call was redirected for an unknown reason.

APPENDIX B: DIAGNOSTIC TOOL

The Diagnostic Tool provides client-side performance measurements for the Call Center client to help troubleshoot client application performance problems. It should only be used when performance problems occur and with the assistance of a support person.



Note: The Diagnostic Tool is available in Release 20.0.30 or later, and only if enabled by the service provider.

LAUNCHING DIAGNOSTIC TOOL

To start the Diagnostic Tool, go to the *Settings – About* page and click the **Run Client Diagnostics** link.




Figure 179 Settings – About (Launching Diagnostic Tool)

DIAGNOSTIC TOOL GUI

The Diagnostic Tool runs in a separate browser window. Its user interface consists of six tabs: Session, Long Polling, Calls, Service, Monitoring, and Support. Each tab is described in a separate subsection.

SESSION TAB

The Session tab displays session information stored for the user on Clearspan. It provides information about the logged user, connection, and subscriptions.

- The user information includes your name, user ID, phone number, extension, and the list of services assigned to you.
- The connection information includes the session ID for the current session, the channel ID for the OCI-C channel, and the address of the Xtended Services Platform the client is running on.
- The subscription table shows all active subscriptions for the logged-in user and is updated in real-time.

Clearspan
Call Center

[Email Support](#) [CK](#)

Diagnostics

Session Long Polling Calls Service Monitoring Support

User Name: Tester 07
User ID: Tester07@remotesoho.aastra.com
Licenses: Anonymous Call Rejection, Authentication, Call Forwarding Always, Call Forwarding Busy, Call Forwarding No Answer, Call Notify, Calling Line ID Delivery Blocking, CommPilot Express, CommPilot Call Manager, Do Not Disturb, Intercept User, Last Number Redial, Outlook Integration, Priority Alert, Call Return, Remote Office, Selective Call Acceptance, Call Forwarding Selective, Selective Call Rejection, Service Scripts User, Simultaneous Ring Personal, Voice Messaging User, Alternate Numbers, Shared Call Appearance, Speed Dial 6, Customer Originated Trace, Attendant Console, Third-Party MVI Control, Client Call Control, Shared Call Appearance 5, Shared Call Appearance 10, Shared Call Appearance 15, Shared Call Appearance 20, Shared Call Appearance 25, Shared Call Appearance 30, Shared Call Appearance 35, Calling Name Retrieval, Flash Call Hold, Speed Dial 100, Directed Call Pickup, Third-Party Voice Mail Support, Directed Call Pickup with Barge-in, Voice Portal Calling, External Calling Line ID Delivery, Internal Calling Line ID Delivery, Automatic Callback, Call Waiting, Calling Line ID Blocking Override, Calling Party Category, Barge-in Exempt, Video Add-On, Preferred Carrier User, Push to Talk, Basic Call Logs, Enhanced Call Logs, Hoteling Host, Hoteling Guest, Voice Messaging User - Video, Diversion Inhibitor, Multiple Call Arrangement, Custom Ringback User, Custom Ringback User - Video, Automatic Hold/Retrieve, Busy Lamp Field, Three-Way Call, Call Transfer, Privacy, Fax Messaging, Physical Location, Charge Number, BroadWorks Supervisor, BroadWorks Agent, N-Way Call, Two-Stage Dialing, Call Forwarding Not Reachable, MVI Delivery to Mobile Endpoint, BroadWorks Receptionist - Small Business, BroadWorks Receptionist - Office, In-Call Service Activation, Connected Line Identification Presentation, Connected Line Identification Restriction, BroadWorks Anywhere Zone Calling Restrictions, Polycom Phone Services, Custom Ringback User - Call Waiting, Music On Hold User, Video On Hold User, Call Center - Basic, Call Center - Standard, Call Center - Premium, Communication Barring User-Control, Classmark, Calling Name Delivery, Calling Number Delivery, Virtual On-Net Enterprise Extensions, Office Communicator Tab Pre-alerting Announcement, Call Center Monitoring, Call Recording, Integrated IMP Group Night Forwarding, BroadTouch Business Communicator Desktop, BroadTouch Business Communicator Desktop - Audio, BroadTouch Business Communicator Mobile, BroadTouch Business Communicator Mobile - Audio, BroadTouch Business Communicator Tablet, BroadTouch Business Communicator Tablet - Audio, BroadTouch Business Communicator Tablet - Video, Executive, Executive-Assistant, Client License 3, BroadWorks Receptionist - Enterprise, Client License 16, Client License 17, Client License 18, Flexible Seating Guest, Sequential Ring

Session/Channel Set ID: b523850b-3ea7-4d13-88fe-1314c94332a3
Channel ID: 844206c8-abc0-412f-8248-2d745440fe92
XSP Address: 20.20.20.50

Subscriptions: 12

Subscription ID	Event Pkg	Target ID	Expires	Request Timestamp	Response Timestamp	Latency (ms)	Initial Event Times	Shared Subscription
ef2a989b-2e2b-4b06-810e-4aebaf	Call Center	A:Tester07@remo	14400	10:44:36:894	10:44:36:911	17	10:44:36:911	
bf3da106-74e9-419f-b5bc-6cb8f9	Basic Call	Tester07@remo	14400	10:44:36:804	10:44:36:822	18	10:44:36:823	
27a876b8-ddc7-4273-a1b3-41425f	Call Center	C:CallCenter@aa	14400	10:45:54:973	10:45:54:992	19	10:45:54:994	
a1c5efbc-1042-4775-8531-028598	Call Waiting	Tester07@remo	14400	10:44:36:894	10:44:36:918	24	10:44:36:918	
5592dd2f-2351-4134-99fd-843104	Hoteling Guest	Tester07@remo	14400	10:44:36:804	10:44:36:856	52	10:44:36:856	
62d5b687-10e0-458f-b111-5f18c9	Call Center	M:CallCenter2@r	14400	10:45:54:973	10:45:54:999	26	10:45:55:000	

Figure 180 Diagnostic Tool – Session Tab

LONG POLLING TAB

The Long Polling tab shows, in real-time, statistics on long polls performed by the client. The Polls table lists long polls and includes the request timestamp, response timestamp, status, and poll time of each long poll.

By default, the number of long polls retained in the Polls table is “10”.

To change the number of displayed long polls, click the drop-down arrow in the *Polls* combo box, and select a new number from the drop-down list.

The *Data* column of the Polls table indicates whether the long poll contains data or not. If the icon in the *Data* column is a green icon, then the corresponding long poll contains data. Clicking on the row for the long poll displays detailed data in the Poll Details table at the bottom of the page.

The Poll Details table displays the feature data that is contained in the update as well as the event type and event ID that triggered the data update.

To clear the tab and start fresh captures of the long polls, click the **Clear** button.

Poll	Request Timestamp	Response Timestamp	Status	Poll Time (ms)	Data
1	11:32:42:636	11:32:58:794	200	16158	
2	11:32:59:047	11:33:15:062	200	16015	
3	11:33:15:309	11:33:31:320	200	16011	
4	11:33:31:575	11:33:47:588	200	16013	
5	11:33:47:837	11:34:03:843	200	16006	

Poll	Feature Data	Event	Event ID
No items to show			

Figure 181 Diagnostic Tool – Long Polling Tab

CALLS TAB

The Calls tab shows call statistics for calls placed through the dialer. For each call, the following information is displayed: the called destination, the call ID of the outbound call, the time the number was dialed, the time the client received the incoming alerting call update, the client answer time (if the call was answered from the client), and the time the client received the outgoing call update.

Destination	Call ID	Dial Time	Client Alerting - Incoming	Client Answer	Client Alerting - Outgoing
No items to show					

Figure 182 Diagnostic Tool – Calls Tab

SERVICE TAB

The Service tab measures the time for enabling/disabling the DND service from the client. It is only shown if you have the DND service assigned.

For each service action, the tool displays the command that was invoked (DND On or DND Off), the time the command was invoked from the client, the time the command response was received by the client, and the time difference in milliseconds between the request time and the response time.




Figure 183 Diagnostic Tool – Service Tab

MONITORING TAB

The Monitoring tab displays statistics on monitored agents (if you are a supervisor) or supervisors (if you are an agent). The *Target* column displays the user ID of the agents or supervisors being monitored.




Figure 184 Diagnostic Tool – Monitoring Tab

SUPPORT TAB

The Support tab is a textual representation of all data contained in the other tabs. The text in this tab should be copied and pasted into the body of the e-mail that you send to the technical support of your service provider.

The Email Support link in the upper right-hand corner of the Diagnostic Tool can be used to open the default e-mail client on your machine. If the “To” address is not preconfigured by the service provider, the support person should provide it to you.

BroadWorks Call Center Diagnostic Report generated at Tue Mar 17 11:35:55 CDT 2015

Session Information

User Name: Tester 07
 User Id: Tester07@remotesoho.aastra.com
 Number: 9733336007
 Ext: 6007
 Licenses: Anonymous Call Rejection, Authentication, Call Forwarding Always, Call Forwarding Busy, Call Forwarding No Answer, Call Notify, Calling Line ID Delivery Blocking, CommPilot Express, CommPilot Call Manager, Do Not Disturb, Intercept User, Last Number Redial, Outlook Integration, Priority Alert, Call Return, Remote Office, Selective Call Acceptance, Call Forwarding Selective, Selective Call Rejection, Service Scripts User, Simultaneous Ring Personal, Voice Messaging User, Alternate Numbers, Shared Call Appearance, Speed Dial 8, Customer Originated Trace, Attendant Console, Third-Party MWI Control, Client Call Control, Shared Call Appearance 5, Shared Call Appearance 10, Shared Call Appearance 15, Shared Call Appearance 20, Shared Call Appearance 25, Shared Call Appearance 30, Shared Call Appearance 35, Calling Name Retrieval, Flash Call Hold, Speed Dial 100, Directed Call Pickup, Third-Party Voice Mail Support, Directed Call Pickup with Barge-in, Voice Portal Calling, External Calling Line ID Delivery, Internal Calling Line ID Delivery, Automatic Callback, Call Waiting, Calling Line ID Blocking Override, Calling Party Category, Barge-in Exempt, Video Add-On, Preferred Carrier User, Push to Talk, Basic Call Logs, Enhanced Call Logs, Hoteling Host, Hoteling Guest, Voice Messaging User - Video, Diversion Inhibitor, Multiple Call Arrangement, Custom Ringback User, Custom Ringback User - Video, Automatic Hold/Retrieve, Busy Lamp Field, Three-Way Call, Call Transfer, Privacy, Fax Messaging, Physical Location, Charge Number, BroadWorks Supervisor, BroadWorks Agent, N-Way Call, Two-Stage Dialing, Call Forwarding Not Reachable, MWI Delivery to Mobile Endpoint, BroadWorks Receptionist - Small Business, BroadWorks Receptionist - Office, In-Call Service Activation, Connected Line Identification Presentation, Connected Line Identification Restriction, BroadWorks Anywhere, Zone Calling Restrictions, Polycom Phone Services, Custom Ringback User - Call Waiting, Music On Hold User, Video On Hold User, Call Center - Basic, Call Center - Standard, Call Center - Premium, Communication Barring User-Control, Classmark, Calling Name Delivery, Calling Number Delivery, Virtual On-Net Enterprise Extensions, Office Communicator Tab, Pre-alerting Announcement, Call Center Monitoring, Call Recording, Integrated IMP, Group Night Forwarding, BroadTouch Business Communicator Desktop, BroadTouch Business Communicator Desktop - Audio, BroadTouch Business Communicator Mobile, BroadTouch Business Communicator Tablet, BroadTouch Business Communicator Tablet - Audio, BroadTouch Business Communicator Tablet - Video, Executive, Executive-Assistant, Client License 3, BroadWorks Receptionist - Enterprise, Client License 16, Client License 17, Client License 18, Flexible Seating Guest, Sequential Ring

Session/Channel SetID: b523850b-3ea7-4d13-80fe-1314c94332a3
 Xsp Address: 20.20.20.50
 Channel: 844206c8-abc0-412f-8248-2d745440fe92

Subscriptions: 12

SubscriptionId	EventPkg	TargetId	Expires	RequestTime	ResponseTime	Latency (ms)	InitialEventTime	SharedSubscriptionId
ef2a989b-2e2b-4b06-810e-4aebaff1f35da	Call Center Agent	Tester07@remotesoho.aastra.com	14400	10:44:36:894	10:44:36:911	17	10:44:36:911	
bf3da106-74e9-419f-b5bc-6cb894ffc4c	Basic Call	Tester07@remotesoho.aastra.com	14400	10:44:36:804	10:44:36:822	18	10:44:36:823	
27a876b8-ddc7-4273-a1b3-41425f9ffa68	Call Center Configuration	CallCenter@aastra.com	14400	10:45:54:973	10:45:54:992	19	10:45:54:994	

Figure 185 Diagnostic Tool – Support Tab

KNOWN ISSUES

If you are using the Chrome browser to run Call Center, and you click the Diagnostic Tool *Email Support* link, an untitled tab opens in the Call Center window, in addition to the new message window of your default e-mail application.

The issue can occur if the Chrome browser attempts to process the request with a different mail protocol than the one defined on your computer.

APPENDIX C: KEYBOARD SHORTCUTS

When using keyboard shortcuts, make sure that the main interface window is in focus.

KEY	EQUIVALENT MOUSE ACTION	DESCRIPTION
ESC	Click the Close button in a dialog box.	This closes the open dialog box.
ESC	Cancel the changes.	This exits the currently selected editable item, such as a text box.
/	Click the <i>Dialer</i> text box.	This places the cursor in the <i>Dialer</i> text box; it retains the currently selected item (if applicable). NOTE: In Internet Explorer 8, the “/” shortcut key does not always work. Pressing the key clears the default <i>Enter Number</i> text, but does not place the cursor in the input box.
?	Click the <i>Search</i> text box.	This places the cursor in the <i>Search</i> text box; it retains the currently selected item (if applicable).
ARROW DOWN	Click the scroll bar or the next item on a list.	This selects the next item in the <i>Call Console</i> or the <i>Queued Calls</i> pane.
ARROW UP	Click the scroll bar or the previous item in a list.	This selects the previous item in the <i>Call Console</i> or the <i>Queued Calls</i> pane.
PAGE DOWN	Scroll down one page.	This goes to the next page in the <i>Call Console</i> or the <i>Queued Calls</i> pane.
PAGE UP	Scroll up one page.	This goes to the previous page in the <i>Call Console</i> or the <i>Queued Calls</i> pane.
1....9	Select a call in the <i>Call Console</i> .	Pressing 1 selects the first call, pressing 2 selects the second call, and so on.
SPACEBAR	Click Answer on the selected incoming call in the <i>Call Console</i> .	This answers the selected incoming call or if no call is selected, the incoming call that has been waiting the longest. Pressing the SPACEBAR again answers the next longest waiting incoming call, which puts the previously answered call on hold.
<PERIOD>	Click End on the selected call in the <i>Call Console</i> .	This ends the selected call.
ENTER	Click Dial .	If the cursor is placed in the <i>Enter Number</i> text box in the <i>Dialer</i> , the entered digits are dialed.
ENTER	Click Search .	If the cursor is placed in the <i>Search</i> text box, a search is performed.
+	Click Transfer in the <i>Dialer</i> .	This transfers the selected call to the ad

KEY	EQUIVALENT MOUSE ACTION	DESCRIPTION
		hoc number entered in the <i>Dialer</i> .
SHIFT+1..9	Select a ringing call and click Answer .	Pressing SHIFT+1 selects and answers the first ringing call, pressing SHIFT+2 selects and answers the second ringing call, and so on.
SHIFT+1..9	Select an active call and click Hold .	Pressing SHIFT+1 selects and places on hold the first active call, pressing SHIFT+2 selects and answers the second active call, and so on.
SHIFT+1..9	Select a held call and click Retrieve .	Pressing SHIFT+1 selects and retrieves the first held call, pressing SHIFT+2 selects and retrieves the second held call, and so on.
S or s	Click the Settings link.	This goes from the main page to the <i>Settings</i> page.
B or b	Click the Back to Application link.	This goes back from the <i>Settings</i> page to the main page.
R or r	Click the Call History button.	This opens the <i>Call History</i> dialog box.
H or h	Click the Help link.	This opens this guide in a PDF format.
D or d	Click the Dashboard link (Supervisor)	This opens the <i>Dashboard</i> or brings the <i>Dashboard</i> to the front if it is already open.
SHIFT+L or SHIFT+I	Click the Sign Out link.	This signs the user out of the application.
SHIFT+A	Select <i>Available</i> (Agent).	This sets the agent's ACD state to "Available".
SHIFT+U	Select <i>Unavailable</i> (Agent).	This sets the agent's ACD state to "Unavailable".
SHIFT+W	Select <i>Wrap-Up</i> (Agent).	This sets the agent's ACD state to "Wrap-Up".

Index

A

About Call Center	166
Accept IM&P subscription request.....	93
ACD states.....	111, 186
Changing by agent.....	16
Changing for agent	113
Actions on calls.....	29
Ad hoc number, dialing	59
Adding	
Conference participant.....	70
Instant Message directory entry	91
Personal contact	85
Speed dial number.....	87
Users to chat.....	98
Agents	
ACD states.....	186
Barging in on.....	114
Changing ACD state by	16
Changing ACD state for.....	113
Changing IM&P presence state by	17
Managing	108
Panel.....	34
Phone and ACD states	111
Picking up calls	115
Real-time statistics about.....	129
Selecting call centers to monitor.....	105
Selecting to monitor	108
Silently monitoring	113
Viewing details	112
Answering call.....	56
Application policies, configuring	155
Application settings, configuring	154, 156
Assigning disposition codes	52
Current call	52
Wrap-Up.....	52
Auto Answering calls	57

B

Barge-in and monitoring settings, configuring.....	155
Barging in on agent.....	114
Blind escalating call	67
Blind transferring calls	64
Busy Camp On.....	63

C

Call Center	
Client, agent.....	4
Client, supervisor	5
Configuring.....	147, 149
Getting started	8
Launching from web portal.....	8
Overview	3
Panels, viewing	120
Selecting for monitoring by agent	105
Selecting for monitoring by supervisor	119
Setting up	15
Signing in, hot desk.....	11
Signing in, web browser.....	9
Call Centers	
Monitoring by agent	103
Order in agent's Dashboard.....	107
Call Console.....	24
Call states and actions.....	29
Conference Call panel	28
Current calls	26
Dialer.....	26
Header bar	25
Call Displaying directories below Call Console	78
Call History.....	38
Deleting	73
Dialing from.....	61
Managing	72
Viewing.....	72

Call Pickup.....	115	States and actions	29
Call redirection reasons.....	21, 30, 191	Transferring.....	64
Calls		Transferring to queue.....	65
Action buttons	41	Transferring to top of queue.....	126
Answering	56	Transferring with consultation.....	64
Assigning disposition codes	52	Types	190
Auto Answering.....	57	Viewing.....	48
Blind escalating.....	67	Camping calls	63
Blind transferring.....	64	Changing	
Camping	63	ACD state.....	16
Dialing		IM&P presence state.....	17
Ad hoc number	59	Password	16, 150
Contact	60	Changing Security Classification	56
History	61	Chatting	
Search	61	Managing sessions	99
Dragging and dropping	48	Starting multiuser session.....	98
Emergency.....	65	Starting one-on-one session.....	96
Ending.....	58	Classification, security level of calls.....	55
Escalating	65	Common panel.....	33
Conference and handover.....	67	Conference	
Consultation.....	67	Adding participant	70
Mid-conference hold.....	68	Ending	71
Event log, configuring	161	Ending participant	71
Generating trace	53	Escalating call	67
Last released call	53	Holding	70
Selected call	53	Holding participant	70
Making outbound	58	Leaving.....	71
Managing	45	Managing	68
Managing conference	68	Resuming.....	70
Modify number to display.....	120	Resuming participant	71
Open URL	57	Starting.....	69
Operations quick reference	46	Three-Way	69
Placing on hold	63	Conference Call, panel	28
Recording	54	Configuring	
Redialing number.....	59	Application policies	155
Resuming held.....	63	Application settings	154, 156
Saving vCard	58	Barge-in and monitoring settings	155
Security Classification.....	55	Call Center client.....	147
Silently monitoring		Call event log	161
Agent	113	Call notification settings	159
In queue.....	122		
States.....	190		

E-mail messaging	163	Agents panel	34
Firefox	168, 185	Common panel.....	33
General settings.....	149	Custom directory panel	36
General settings, account.....	150	Directories panel	37
Hotel Guest	150	Enterprise/Group panel.....	33
IM&P messaging.....	164	Instant Message panel.....	36
Internet Explorer	167	Outlook panel	37
Language	150	Personal panel	34
LDAP settings	160	Queues panel.....	35
Messaging	163	Search panel.....	33
Outlook integration.....	159	Speed Dial panel.....	35
Plug-ins	158	Supervisors panel	35
Program shortcuts	161	Controls	
Queues membership	154	Action buttons	41
Report settings.....	164	Call Center	39
Screen Pop	151	Current calls.....	26
Web browser.....	167	Viewing.....	48
Workspace settings	153	Custom directory panel	36
Consultation		Customer Originated Trace	53
Escalating calls	67	D	
Transferring calls	64	Dashboard	
Contacts		Agent.....	103
Dialing	60	Supervisor	127
Displaying directories below Call Console		Default service-level calculations, report	
.....	78	settings.....	165
E-mailing	74	Definitions	186
IM&P, accept subscription request	93	ACD states	186
IM&P, chatting with	95	Agent phone and ACD states	111
IM&P, subscribe to.....	91	Call states	190
IM&P, unsubscribe from	93	Call types	190
IM&P, viewing presence state	94	IM&P states.....	189
Managing	75	Phone states	188
Organizing	82	Deleting	
Searching.....	83	Call History.....	73
Selecting display order	81	Personal contact	86
Showing or hiding contact details	80	Speed dial number	88
Showing or hiding directories	77	Dialer.....	26
Showing or hiding directory content	80	Dialing	
Sorting.....	82	Ad hoc number.....	59
Viewing	77	Contact.....	60
Contacts pane.....	30		

From chat window.....	97	Escalating call	65
History.....	61	Blind	67
Search.....	61	Conference	67
Directories		Consultation	67
Displaying below Call Console	78	Emergency.....	65
Directories panel.....	37	Handover.....	67
Directory		Mid-conference hold	68
Agents.....	34	Exploring workspace.....	20
Custom.....	36	F	
Enterprise/Group	33	Firefox	
Instant Message	36	Configuring for quick link navigation ...	185
Outlook.....	37	Forced Forwarding, enabling	123
Personal.....	34, 85	G	
Queues	35	General settings, configuring	149
Search.....	33	Generating	
Searching.....	83	Call trace	53
Sort	82	Reports.....	134
Speed Dial	35, 87	Enhanced.....	134
Supervisors.....	35	Global Message Area	23
Viewing	77	Glossary.....	186
Disabling, services.....	18	Group panel	33
Disposition codes, assigning to calls	52	Grouping, queued calls	121
Dragging and dropping calls.....	48	H	
E		Handover, escalating call.....	67
Edge browser limitations	184	Header bar	25
Editing, Instant Message directory	92	Help, getting.....	14
E-mail		Holding	
Configuring options for.....	163	Call	63
E-mailing contacts	74	Conference	70
Emergency call	65	Conference participant.....	70
Enabling		Hot desk sign in	11
Forced Forwarding.....	123	Hotel Guest settings, configuring	150
Night Service Override.....	123	I	
Services	18	IM&P	
Ending		Accepting subscription requests	93
Call.....	58	Configuring options for.....	164
Conference	71	Contacts, chatting with.....	95
Conference participant.....	71	Subscribing to contact.....	91
Enterprise panel.....	33		

Unsubscribing from contact	93	Reordering, calls in queue	125
Viewing presence state of contacts	94	Speed dial numbers	87
IM&P presence		Transferring calls between queues	124
Changing by agent	17	Transferring calls from queue to agent	125
IM&P states	189	Transferring calls to ad hoc number ...	125
Incoming call, viewing details	50	Messaging, configuring	163
Instant Message directory		Modifying number of calls to display	120
Adding entries	91	Modifying speed dial number	88
Editing entries	92	Modifying, Instant Message directory	92
Instant Messaging and Presence		Monitoring	
Configuring options for	164	Call centers by agent	103
Interface		Contact's IM&P presence	90
Dashboard pane for agent	103	Phone state	
Supervisor's Dashboard	127	Agents	111
K		Supervisors	101
Keyboard shortcuts	197, 198	Silently	
L		Agent's call	113
Language, configuring	150	Next queued call	122
Launching Call Center from web portal	8	Multiusers chat, starting	98
LDAP, configuring	160	N	
Leaving conference	71	Night Service Override, enabling	123
Logged user information	23	Notification, configuring	159
Logo pane	23	O	
Global Message Area	23	Ordering	
Links	23	Call centers in agent's Dashboard	107
Logged user information	23	Queued calls	122
M		Organizing, contacts	82
Making outbound calls	58	Outgoing CLID, setting	58
Managing		Outlook integration, configuring	159
Agents	108	Outlook panel	36, 37
Call History	72	P	
Calls	45	Pane	
Chat sessions	99	Call Console	24
Conference calls	68	Contacts	30
Contacts	75	Queued Calls	116
Personal contacts	85	Panel	
Queued calls	116	Agents	34
Queued calls, promoting	124	Conference Call	28
Queued calls, retrieving	124	Custom directory	36
		Directories	37

Enterprise/Group	33	Transferring calls to ad hoc number ...	125
Instant Message	36	Transferring calls to agent	125
Outlook.....	37	Transferring calls to top	126
Personal.....	34	Queued calls	
Queues	35	Grouping	121
Search.....	33	Managing	116
Speed Dial	35	Monitoring	122
Supervisors.....	35	Ordering	122
Participant		Viewing details	121
Adding to conference.....	70	Queued Calls, pane	116
Ending in conference	71	Queues panel.....	35
Holding in conference	70	Quick link navigation	
Resuming in conference	71	Firefox	185
Password, changing	16, 150	Quick reference, call operations	46
Pausing call recording	54	R	
Personal contacts		Real-time statistics.....	127
Adding.....	85	Recording calls	
Deleting.....	86	Pausing	54
Managing	85	Stopping	55
Personal panel.....	34	Recording Calls.....	54
Phone states.....	102, 111, 188	Redialing number.....	59
Monitoring for supervisors	101	Redirection reasons	21, 30, 191
Picking up agent's call	115	Reordering, calls in queue	125
Plug-ins settings, configuring.....	158	Report settings	
Pop-up notification	50	Configuring.....	164
Presence state of IM&P contacts	94	Date and time.....	165
Presence states	189	Default service-level calculations.....	165
Program shortcuts, configuring.....	161	Default thresholds	165
Promoting calls in queue	124	Reports	
Pulling out directories	78	Generating	134
Q		Managing scheduled	145
Queue		Running enhanced	134
Membership, configuring	154	Scheduling enhanced	140
Position call in, reorder	125	Resuming	
Promoting calls	124	Call recording	54
Real-time statistics about.....	128	Conference	70
Retrieving calls from	124	Conference participant.....	71
Transferring call	65	Held call	63
Transferring calls between.....	124		

S

Scheduling Enhanced Report.....	140
Screen Pop, configuring	151
Search panel.....	33
Search, dialing from.....	61
Searching for contacts.....	83
Selecting	
Agents to monitor.....	108
Call centers to monitor by agent.....	105
Call Centers to monitor by supervisor ..	119
Supervisors to monitor.....	101
Services, enabling or disabling.....	18
Setting, outgoing CLID	58
Settings	
About.....	166
Application	154, 156
Queue membership.....	154
Application policies	155
Barge-in and monitoring	155
General	149
Hotel Guest.....	150
Language.....	150
Screen Pop.....	151
Workspace.....	153
Messaging	163
E-mail messaging.....	163
IM&P.....	164
Plug-ins	158
Call event log.....	161
LDAP	160
Notification.....	159
Outlook	159
Program shortcuts	161
Report	164
Shortcuts, keyboard.....	197, 198
Sign in	
Hot desk.....	11
Web browser.....	9
Sign out.....	14
Sign-in	
Restrictions	13
Silent Monitoring.....	113
Sorting, contacts	82

Speed dial numbers	
Adding	87
Deleting	88
Managing	87
Modifying.....	88
Speed Dial panel.....	35
Starting	
Chat session	96
Multiuser chat.....	98
Starting Three-Way Conference	69
States	
ACD.....	186
Calls	190
User's phone line	188
User's presence states	189
Statistics	
Agent information	129
Agents and queues, real-time.....	127
Dashboard	127
Navigating to agent	132
Queue information	128
Selecting information to display	131
Stopping call recording	55
Subscribe to IM&P contact	91
Subscription request, accept from IM&P contacts.....	93
Supervisors	
Changing agent's ACD state.....	113
Monitoring phone state	101
Panel	35
Phone states	102
Selecting call centers to monitor	119
Selecting to monitor	101
Viewing agent statistics.....	129
Viewing queue statistics.....	128

T

Tab button not working	184
Trace, generating for calls	53
Transferring calls	64
Blind	64

Consultation	64	Speed Dial panel.....	35
Queue	65	Supervisors panel	35
Supervisor		V	
Queue to ad hoc number.....	125	vCard, saving	58
Queue to agent.....	125	Viewing	
Queues, between	124	Agent details	112
Top of queue.....	126	Call Center panels	120
U		Call History.....	72
Unsubscribe from IM&P contact	93	Calls	48
URL, opening for a call	57	Contacts.....	77
User interface		Current calls	48
Action buttons	41	Directory.....	77
Agents panel.....	34	Incoming call details.....	50
Call Console	24	Queued calls details.....	121
Call History	38	Show or hide	120
Common panel	33	Viewing IM&P presence state	94
Conference Call panel	28	W	
Contacts pane.....	30	Web Browser	
Controls.....	39	Configuring.....	167
Custom directory panel.....	36	Configuring Firefox.....	168
Dialer.....	26	Configuring Internet Explorer	167
Directories panel.....	37	Web browser sign in	9
Enterprise/Group panel.....	33	Workspace	
Header bar	25	Call Console.....	24
Instant Message panel.....	36	Call History.....	38
Logged user state	23	Configuring settings	153
Outlook panel.....	37	Contacts pane	30
Personal panel.....	34	Controls.....	39
Queued Calls pane	116	Exploring	20
Queues panel	35	Logo pane	23
Search panel.....	33		

